

Control Commands

Model No. PT-RQ35K2
PT-RZ34K2
PT-SRQ350KC
PT-SRZ340KC
PT-SRZ330KC



- Please refer to the Operating Instructions for the serial command format, limitations, connection and other details.
- シリアルコマンドのフォーマット、制限事項、接続方法およびその他詳細につきましては、各モデルの取扱説明書をご覧ください。
- 有关串行控制命令的格式、限制事项、连接方法以及其他详情、请参阅各机型的使用说明书。

Panasonic

(2025-08)

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ35K2 SERIES	RZ34K2 SERIES	SZ330KC SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K2 SRQ350KC	RZ34K2 SRZ340KC	SZ330C
BASIC OPERATION REMOTE CONTROL	POWER	ON		PON	QPW	001	✓	✓	✓
		OFF (STANDBY)		POF		000	✓	✓	✓
	INPUT SELECT	DVI		IIS:DVI	QIN	DVI	✓	✓	✓
		HDMI1		IIS:HD1		HD1	✓	✓	✓
		SD1		IIS:SD1		SD1	✓	✓	✓
		DIGITAL LINK		IIS:DL1		DL1	✓	✓	✓
	INPUT SELECT (DIGITAL LINK)	COMPUTER1		IIS:DL1:PC1	QIN	DL1:PC1	✓	✓	✓
		COMPUTER2		IIS:DL1:PC2		DL1:PC2	✓	✓	✓
		VIDEO		IIS:DL1:VID		DL1:VID	✓	✓	✓
		HDMI1		IIS:DL1:HD1		DL1:HD1	✓	✓	✓
		HDMI2		IIS:DL1:HD2		DL1:HD2	✓	✓	✓
		S-VIDEO		IIS:DL1:SVD		DL1:SVD	✓	✓	✓
	INPUT SELECT (SLOT)	SLOT1 : SD11		IIS:AU1,SD1	QIN	AU1,SD1	✓	✓	✓
		SLOT1 : SD12		IIS:AU1,SD2		AU1,SD2	✓	✓	✓
		SLOT1 : SD13		IIS:AU1,SD3		AU1,SD3	✓	✓	✓
		SLOT1 : SD14		IIS:AU1,SD4		AU1,SD4	✓	✓	✓
		SLOT2 : SD11		IIS:AU2,SD1		AU2,SD1	✓		
		SLOT2 : SD12		IIS:AU2,SD2		AU2,SD2	✓		
		SLOT2 : SD13		IIS:AU2,SD3		AU2,SD3	✓		
		SLOT2 : SD14		IIS:AU2,SD4		AU2,SD4	✓		
		SLOT1 : HDMI1		IIS:AU1,HD1		AU1,HD1	✓	✓	✓
		SLOT1 : HDMI2		IIS:AU1,HD2		AU1,HD2	✓	✓	✓
		SLOT2 : HDMI3		IIS:AU2,HD3		AU2,HD3	✓		
		SLOT2 : HDMI4		IIS:AU2,HD4		AU2,HD4	✓		
		SLOT1 : DVI1		IIS:AU1,DV1		AU1,DV1	✓	✓	✓
		SLOT1 : DVI2		IIS:AU1,DV2		AU1,DV2	✓	✓	✓
		SLOT2 : DVI3		IIS:AU2,DV3		AU2,DV3	✓		
		SLOT2 : DVI4		IIS:AU2,DV4		AU2,DV4	✓		
		SLOT1 : DisplayPort1		IIS:AU1,DP1		AU1,DP1	✓	✓	✓
		SLOT1 : DisplayPort2		IIS:AU1,DP2		AU1,DP2	✓	✓	✓
		SLOT2 : DisplayPort3		IIS:AU2,DP3		AU2,DP3	✓		
		SLOT2 : DisplayPort4		IIS:AU2,DP4		AU2,DP4	✓		
		SLOT1 : 12G SDI OPT1		IIS:AU1,OP1		AU1,OP1	✓	✓	✓
		SLOT1 : 12G SDI OPT2		IIS:AU1,OP2		AU1,OP2	✓	✓	✓
		SLOT2 : 12G SDI OPT1		IIS:AU2,OP1		AU2,OP1	✓		
		SLOT2 : 12G SDI OPT2		IIS:AU2,OP2		AU2,OP2	✓		
	FREEZE	OFF		OFZ:0	QFZ	0	✓	✓	✓
		ON		OFZ:1		1	✓	✓	✓
	MENU KEY			OMN			✓	✓	✓
	ENTER KEY			OEN			✓	✓	✓
	UP KEY			OCU			✓	✓	✓
	DOWN KEY			OCD			✓	✓	✓
	LEFT KEY			OCL			✓	✓	✓
	RIGHT KEY			OCR			✓	✓	✓
	DEFAULT KEY			OST			✓	✓	✓
	AUTO SETUP KEY			OAS			✓	✓	✓
	SHUTTER	OFF		OSH:0	QSH	0	✓	✓	✓
		ON		OSH:1		1	✓	✓	✓
	SHUTTER(Toggle)	OFF		OSH	QSH	0	✓	✓	✓
		ON				1	✓	✓	✓
	FUNCTION KEY			FC1			✓	✓	✓
	SYSTEM SELECTOR KEY			OSL			✓	✓	✓
	ASPECT KEY			VS1			✓	✓	✓
	NUMERIC KEY	0		ONK:0			✓	✓	✓
		1		ONK:1			✓	✓	✓
		2		ONK:2			✓	✓	✓
		3		ONK:3			✓	✓	✓
		4		ONK:4			✓	✓	✓
		5		ONK:5			✓	✓	✓
		6		ONK:6			✓	✓	✓
		7		ONK:7			✓	✓	✓
		8		ONK:8			✓	✓	✓
		9		ONK:9			✓	✓	✓
	LENS HOME POSITION	EXECUTE		VXX:LNSI1=+00001			✓	✓	✓
	ACTIVE FOCUS OPTIMIZER-ACTIVE FOCUS	OFF		VXX:AF0I1=+00000	QVX:AF0I1	AF0I1=+00000	✓	✓	✓
		ON		VXX:AF0I1=+00001		AF0I1=+00001		✓	✓
	ACTIVE FOCUS OPTIMIZER-FOCUS OFFSET BRIGHT	-00299		VXX:FOB11=-00299	QVX:FOB11	FOB11=-00299	-299	-299	-299
		+00299		VXX:FOB11=+00299		FOB11=+00299	+299	+299	+299
	ACTIVE FOCUS OPTIMIZER-FOCUS OFFSET DARK	-00299		VXX:FOD11=-00299	QVX:FOD11	FOD11=-00299	-299	-299	-299
		+00299		VXX:FOD11=+00299		FOD11=+00299	+299	+299	+299
	ACTIVE FOCUS OPTIMIZER-INITILIZE	EXECUTE		VXX:FOI11=+00001			✓	✓	✓
	LENS SHIFT-HORIZONTAL	SLOW+		VXX:LNSI2=+00000			✓	✓	✓
		SLOW-		VXX:LNSI2=+00001			✓	✓	✓
		NORMAL+		VXX:LNSI2=+00100			✓	✓	✓
		NORMAL-		VXX:LNSI2=+00101			✓	✓	✓
		FAST+		VXX:LNSI2=+00200			✓	✓	✓
		FAST-		VXX:LNSI2=+00201			✓	✓	✓
	LENS SHIFT-VERTICAL	SLOW+		VXX:LNSI3=+00000			✓	✓	✓
		SLOW-		VXX:LNSI3=+00001			✓	✓	✓
		NORMAL+		VXX:LNSI3=+00100			✓	✓	✓
		NORMAL-		VXX:LNSI3=+00101			✓	✓	✓
		FAST+		VXX:LNSI3=+00200			✓	✓	✓
		FAST-		VXX:LNSI3=+00201			✓	✓	✓
	LENS FOCUS	SLOW+		VXX:LNSI4=+00000			✓	✓	✓
		SLOW-		VXX:LNSI4=+00001			✓	✓	✓
		NORMAL+		VXX:LNSI4=+00100			✓	✓	✓
		NORMAL-		VXX:LNSI4=+00101			✓	✓	✓
		FAST+		VXX:LNSI4=+00200			✓	✓	✓
		FAST-		VXX:LNSI4=+00201			✓	✓	✓
	LENS ZOOM	SLOW+		VXX:LNSI5=+00000			✓	✓	✓
		SLOW-		VXX:LNSI5=+00001			✓	✓	✓
		NORMAL+		VXX:LNSI5=+00100			✓	✓	✓
		NORMAL-		VXX:LNSI5=+00101			✓	✓	✓
		FAST+		VXX:LNSI5=+00200			✓	✓	✓
		FAST-		VXX:LNSI5=+00201			✓	✓	✓
	LENS POSITION	HORIZONTAL(H)		VXX:LNSI7=*HORIZONTAL	QVX:LNSI7	LNSI7=*HORIZONTAL	✓	✓	✓
		VERTICAL(V)		VXX:LNSI8=*VERTICAL	QVX:LNSI8	LNSI8=*VERTICAL	✓	✓	✓
		FOCUS(F)		VXX:LNSI9=*FOCUS	QVX:LNSI9	LNSI9=*FOCUS	✓	✓	✓
		ZOOM(Z)		VXX:LNSIA=*ZOOM	QVX:LNSIA	LNSIA=*ZOOM	✓	✓	✓
		H/V		VXX:LNSSB=*H*V	QVX:LNSSB	LNSSB=*H*V	✓	✓	✓
		H/V F		VXX:LNSSC=*H*V*F	QVX:LNSSC	LNSSC=*H*V*F	✓	✓	✓
		H/V F Z		VXX:LNSSD=*H*V*F*Z	QVX:LNSSD	LNSSD=*H*V*F*Z	✓	✓	✓
		*HORIZONTAL(H)	min.	-*****		-*****	*by lens type(-3306)	*by lens type(-3306)	*by lens type(-3306)
			max.	+*****		+*****	*by lens type(+3306)	*by lens type(+3306)	*by lens type(+3306)
		*VERTICAL(V)	min.	-*****		-*****	*by lens type(-4266)	*by lens type(-4266)	*by lens type(-4266)
			max.	+*****		+*****	*by lens type(+7034)	*by lens type(+7034)	*by lens type(+7034)
		*FOCUS(F)	min.	+*****		+*****	0	0	0
			max.	+*****		+*****	3466	3466	3466
		*ZOOM(Z)	min.	+*****		+*****	*by lens type	*by lens type	*by lens type
			max.	+*****		+*****	*by lens type	*by lens type	*by lens type
	STATUS KEY			STS			✓	✓	✓
	LENS FOCUS KEY			OLF			✓	✓	✓
	LENS SHIFT KEY			OLH			✓	✓	✓
	LENS ZOOM KEY			OLZ			✓	✓	✓
	DIGITAL LINK KEY			DLK			✓	✓	✓
	INPUT MENU KEY			IPT			✓	✓	✓
	SELF DIAGNOSIS				QVX:ERRS1	ERRS1=*****.....	✓	✓	✓
					QVX:ERRS2	ERRS2=*****.....	✓	✓	✓
	PICTURE MODE	DYNAMIC		VPM:DYN	QPM	DYN	✓	✓	✓
		NATURAL		VPM:NAT		NAT	✓	✓	✓
		STANDARD		VPM:STD		STD	✓	✓	✓
		CINEMA		VPM:CIN		CIN	✓	✓	✓
		GRAPHIC		VPM:GRA		GRA	✓	✓	✓
		DICOM SIM. USER		VPM:DIC		DIC	✓	✓	✓
				VPM:USR		USR	✓	✓	✓
	PICTURE MODE-NAME SETTING USER	PICTUREMODE		VXX:NCGS0=PICTUREMODE	QVX:NCGS0	NCGS0=PICTUREMODE	✓	✓	✓
	PICTURE MODE-NAME CLEAR USER	PICTUREMODE		VXX:NCL10=+00000			✓	✓	✓
	CONTRAST	+1		VCN:001	QVR	001	✓	✓	✓
		+63		VCN:063		063	✓	✓	✓
	BRIGHTNESS	+1		VBR:001	QVB	001	✓	✓	✓
		+63		VBR:063		063	✓	✓	✓
	COLOR	+1		VCO:001	QVC	001	✓	✓	✓
		+63		VCO:063		063	✓	✓	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ35K2 SERIES	RZ34K2 SERIES	Z330KC SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K2C	RZ34K2C	SRZ330C
PICTURE	TINT	+1		VTN:001	QVT	001	✓	✓	✓
		+63		VTN:063		063	✓	✓	✓
	SHARPNESS	0		VSR:000	QVS	000	✓	✓	✓
		15		VSR:015		015	✓	✓	✓
	COLOR TEMPERATURE	USER1(USER)		OTE:04	QTE	4	✓	✓	✓
		USER2		OTE:09		9	✓	✓	✓
		DEFAULT		OTE:10		10	✓	✓	✓
		3200K		OTE:3200		3200	✓	✓	✓
		3300K		OTE:3300		3300	✓	✓	✓
		9200K		OTE:9200		9200	✓	✓	✓
		9300K		OTE:9300		9300	✓	✓	✓
		9400K		OTE:9400		9400	✓	✓	✓
		12900K		OTE:12900		12900	✓	✓	✓
		13000K		OTE:13000		13000	✓	✓	✓
	COLOR TEMP-NAME SETTING USER1	COLORTEMP1		VXX:NCGS1=COLORTEMP1	QVX:NCGS1	NCGS1=COLORTEMP1	✓	✓	✓
	COLOR TEMP-NAME SETTING USER2	COLORTEMP2		VXX:NCGS3=COLORTEMP2	QVX:NCGS3	NCGS3=COLORTEMP2	✓	✓	✓
	COLOR TEMP-NAME CLEAR USER1	COLORTEMP1		VXX:NCLI1=+00000			✓	✓	✓
	COLOR TEMP-NAME CLEAR USER2	COLORTEMP2		VXX:NCLI3=+00000			✓	✓	✓
	WHITE BALANCE LOW-RED	-127		VOR:001	QOR	001	✓	✓	✓
		+127		VOR:255		255	✓	✓	✓
	WHITE BALANCE LOW-GREEN	-127		VOG:001	QOG	001	✓	✓	✓
		+127		VOG:255		255	✓	✓	✓
	WHITE BALANCE LOW-BLUE	-127		VOB:001	QOB	001	✓	✓	✓
		+127		VOB:255		255	✓	✓	✓
	WHITE BALANCE HIGH-RED	0		VHR:000	QHR	000	✓	✓	✓
		+255		VHR:255		255	✓	✓	✓
	WHITE BALANCE HIGH-GREEN	0		VHG:000	QHG	000	✓	✓	✓
		+255		VHG:255		255	✓	✓	✓
	WHITE BALANCE HIGH-BLUE	0		VHB:000	QHB	000	✓	✓	✓
		+255		VHB:255		255	✓	✓	✓
	GAMMA	1.0		VGA:1.0	QGA	1.0	✓	✓	✓
		1.8		VGA:1.8		1.8	✓	✓	✓
		2.0		VGA:2.0		2.0	✓	✓	✓
		2.1		VGA:2.1		2.1	✓	✓	✓
		2.2		VGA:2.2		2.2	✓	✓	✓
		2.3		VGA:2.3		2.3	✓	✓	✓
		2.4		VGA:2.4		2.4	✓	✓	✓
		2.5		VGA:2.5		2.5	✓	✓	✓
		2.6		VGA:2.6		2.6	✓	✓	✓
		2.7		VGA:2.7		2.7	✓	✓	✓
		2.8		VGA:2.8		2.8	✓	✓	✓
		USER1		VGA:US1		US1	✓	✓	✓
		USER2		VGA:US2		US2	✓	✓	✓
		DICOM		VGA:DIC		DIC	✓	✓	✓
		HDR HLG		VGA:HD1		HD1	✓	✓	✓
		HDR ST2048-500		VGA:HD2		HD2	✓	✓	✓
		HDR ST2048-1000		VGA:HD3		HD3	✓	✓	✓
		DEFAULT		VGA:DEF		DEF	✓	✓	✓
	GAMMA-HDR HLG SYSTEM GAMMA	min.	(0.1step)	VXX:HLGS1=+1.00	QVX:HLGS1	HLGS1=1.00	✓	✓	✓
		max.		VXX:HLGS1=+1.62		HLGS1=1.62	✓	✓	✓
	GAMMA-NAME SETTING USER1	GAMMAUSER1		VXX:NCGS2=GAMMAUSER1	QVX:NCGS2	NCGS2=GAMMAUSER1	✓	✓	✓
	GAMMA-NAME SETTING USER2	GAMMAUSER2		VXX:NCGS4=GAMMAUSER2	QVX:NCGS4	NCGS4=GAMMAUSER2	✓	✓	✓
	GAMMA-NAME CLEAR USER1	GAMMAUSER1		VXX:NCLI2=+00000			✓	✓	✓
	GAMMA-NAME CLEAR USER2	GAMMAUSER2		VXX:NCLI4=+00000			✓	✓	✓
	DAYLIGHT VIEW FRONT INSTALL	OFF		VXX:DLVI0=+00000	QVX:DLVI0	DLVI0=+00000	✓	✓	✓
		AUTO(1)		VXX:DLVI0=+00001		DLVI0=+00001	✓	✓	✓
		ON(2)		VXX:DLVI0=+00002		DLVI0=+00002	✓	✓	✓
		ON(3)		VXX:DLVI0=+00003		DLVI0=+00003	✓	✓	✓
		4		VXX:DLVI0=+00004		DLVI0=+00004	✓	✓	✓
		5		VXX:DLVI0=+00005		DLVI0=+00005	✓	✓	✓
		6		VXX:DLVI0=+00006		DLVI0=+00006	✓	✓	✓
	NOISE REDUCTION	OFF		VNS:0	QNS	0	✓	✓	✓
		1		VNS:1		1	✓	✓	✓
		2		VNS:2		2	✓	✓	✓
		3		VNS:3		3	✓	✓	✓
		4		VNS:4		4	✓	✓	✓
		5		VNS:5		5	✓	✓	✓
		6		VNS:6		6	✓	✓	✓
	DYNAMIC CONTRAST/IRIS	OFF		OAI:0	QAI	0	✓	✓	✓
		1		OAI:1		1	✓	✓	✓
		2		OAI:2		2	✓	✓	✓
		3		OAI:3		3	✓	✓	✓
		USER		OAI:4		4	✓	✓	✓
	DYNAMIC CONTRAST/AUTO IRIS (AUTO CONTRAST)	OFF		OAI:A000	QAI:A	000	✓	✓	✓
		1		OAI:A001		001	✓	✓	✓
		255		OAI:A255		255	✓	✓	✓
	DYNAMIC CONTRAST (BRIGHT SIGNAL LEVEL)	6%		VXX:DYCI1=+00006	QVX:DYCI1	00006	✓	✓	✓
		50%		VXX:DYCI1=+00050		00050	✓	✓	✓
	DYNAMIC CONTRAST (LIGHTS OUT TIMER)	DISABLE		VXX:DYCS2=OFF	QVX:DYCS2	OFF	✓	✓	✓
		0.0s		VXX:DYCS2=0.0		0.0	✓	✓	✓
		10.0s		VXX:DYCS2=10.0		10.0	✓	✓	✓
	DYNAMIC CONTRAST (LIGHTS OUT SIGNAL LEVEL)	0		VXX:DYCI3=+00000	QVX:DYCI3	00000	✓	✓	✓
		5		VXX:DYCI3=+00005		00005	✓	✓	✓
	DYNAMIC CONTRAST (LIGHTS OUT FADE-IN)	0.0s(OFF)		VXX:DYCS4=0.0	QVX:DYCS4	DYCS4=0.0	✓	✓	✓
		0.5s		VXX:DYCS4=0.5		DYCS4=0.5	✓	✓	✓
		1.0s		VXX:DYCS4=1.0		DYCS4=1.0	✓	✓	✓
		1.5s		VXX:DYCS4=1.5		DYCS4=1.5	✓	✓	✓
		2.0s		VXX:DYCS4=2.0		DYCS4=2.0	✓	✓	✓
		2.5s		VXX:DYCS4=2.5		DYCS4=2.5	✓	✓	✓
		3.0s		VXX:DYCS4=3.0		DYCS4=3.0	✓	✓	✓
		3.5s		VXX:DYCS4=3.5		DYCS4=3.5	✓	✓	✓
		4.0s		VXX:DYCS4=4.0		DYCS4=4.0	✓	✓	✓
		5.0s		VXX:DYCS4=5.0		DYCS4=5.0	✓	✓	✓
		7.0s		VXX:DYCS4=7.0		DYCS4=7.0	✓	✓	✓
		10.0s		VXX:DYCS4=10.0		DYCS4=10.0	✓	✓	✓
	DYNAMIC CONTRAST (LIGHTS OUT FADE-OUT)	0.0s(OFF)		VXX:DYCS5=0.0	QVX:DYCS5	DYCS5=0.0	✓	✓	✓
		0.5s		VXX:DYCS5=0.5		DYCS5=0.5	✓	✓	✓
		1.0s		VXX:DYCS5=1.0		DYCS5=1.0	✓	✓	✓
		1.5s		VXX:DYCS5=1.5		DYCS5=1.5	✓	✓	✓
		2.0s		VXX:DYCS5=2.0		DYCS5=2.0	✓	✓	✓
		2.5s		VXX:DYCS5=2.5		DYCS5=2.5	✓	✓	✓
		3.0s		VXX:DYCS5=3.0		DYCS5=3.0	✓	✓	✓
		3.5s		VXX:DYCS5=3.5		DYCS5=3.5	✓	✓	✓
		4.0s		VXX:DYCS5=4.0		DYCS5=4.0	✓	✓	✓
		5.0s		VXX:DYCS5=5.0		DYCS5=5.0	✓	✓	✓
		7.0s		VXX:DYCS5=7.0		DYCS5=7.0	✓	✓	✓
		10.0s		VXX:DYCS5=10.0		DYCS5=10.0	✓	✓	✓
	DYNAMIC CONTRAST/MANUAL IRIS (MANUAL INTENSITY)	OFF		OAI:M000	QAI:M	000	✓	✓	✓
		1		OAI:M001		001	✓	✓	✓
		255		OAI:M255		255	✓	✓	✓
	DYNAMIC CONTRAST (DYNAMIC GAMMA)	OFF		OAI:D0	QAI:D	0	✓	✓	✓
		1		OAI:D1		1	✓	✓	✓
		2		OAI:D2		2	✓	✓	✓
		3		OAI:D3		3	✓	✓	✓
	COLOR SPACE	NATIVE		VXX:CSPI1=+00000	QVX:CSPI1	CSPI1=+00000	✓	✓	✓
		ITU-709		VXX:CSPI1=+00001		CSPI1=+00001	✓	✓	✓
		DCI-P3		VXX:CSPI1=+00002		CSPI1=+00002	✓	✓	✓
		ITU2020		VXX:CSPI1=+00003		CSPI1=+00003	✓	✓	✓
	SYSTEM SELECTOR RGB(VGA/480P)	VGA60		ORF:0	QRF	0	✓	✓	✓
		480P(YCbCr)		ORF:1		1	✓	✓	✓
		480p(RGB)		ORF:3		3	✓	✓	✓
	SYSTEM SELECTOR RGB(Other)/DVI/SLOT-DVI	RGB		ORF:0	QRF	0	✓	✓	✓
		YPbPr		ORF:1		1	✓	✓	✓
	SYSTEM SELECTOR HDMI/DIGITAL LINK/DisplayPort/	RGB		ORF:0	QRF	0	✓	✓	✓
	SLOT-HDMI/SLOT-DIGITAL LINK/	YPbPr		ORF:1		1	✓	✓	✓
	AUTO	AUTO		ORF:2		2	✓	✓	✓
	DIGITAL IMAGE SHIFT-HORIZONTAL	min.		VXX:DISI1=-00192	QVX:DISI1	DISI1=-00192	✓	✓	✓
		max.				DISI1=00192	✓	✓	✓
	DIGITAL IMAGE SHIFT-VERTICAL	min.		VXX:DISI2=-00120	QVX:DISI2	DISI2=-00120	✓	✓	✓
		max.		VXX:DISI2=00120		DISI2=-00120	✓	✓	✓
	DIGITAL IMAGE SHIFT-HORIZONTAL(relative)	min.		VXX:DISI3=-00001			✓	✓	✓
		max.		VXX:DISI3=+00001			✓	✓	✓
	DIGITAL IMAGE SHIFT-VERTICAL(relative)	min.		VXX:DISI4=-00001			✓	✓	✓
		max.							

				CONTROL	QUERY		RQ35K2 SERIES	RZ34K2 SERIES	SRZ330KC SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K2 SRQ350KC	RZ34K2 SRZ340KC	SRZ330C
POSITION	GEOMETRY	max.		VXX:DISI4=+00001			✓	✓	✓
		OFF		VXX:GMMI0=+00000	QVX:GMMI0	GMMI0=+00000	✓	✓	✓
		KEYSTONE		VXX:GMMI0=+00001		GMMI0=+00001	✓	✓	✓
		CURVED		VXX:GMMI0=+00002		GMMI0=+00002	✓	✓	✓
		PC-1		VXX:GMMI0=+00003		GMMI0=+00003	✓	✓	✓
		PC-2		VXX:GMMI0=+00004		GMMI0=+00004	✓	✓	✓
		PC-3		VXX:GMMI0=+00005		GMMI0=+00005	✓	✓	✓
		CORNER-CORRECTION		VXX:GMMI0=+00010		GMMI0=+00010	✓	✓	✓
		DIGITAL ZOOM EXTENDER		VXX:GMMI0=+00011		GMMI0=+00011	✓	✓	✓
		6POINT CORRECTION		VXX:GMMI0=+00012		GMMI0=+00012	✓	✓	✓
	GEOMETRY-KEYSTONE-LENS THROW RATIO	0.7	0.1 step	VXX:GMKS0=+00.7	QVX:GMKS0	GMKS0=+00.7	✓	✓	✓
		16.5		VXX:GMKS0=+16.5		GMKS0=+16.5	✓	✓	✓
	GEOMETRY-KEYSTONE-VERTICAL BALANCE	-60		VXX:GMKI4=-00060	QVX:GMKI4	GMKI4=-00060	✓	✓	✓
		+60		VXX:GMKI4=+00060		GMKI4=+00060	✓	✓	✓
	GEOMETRY-KEYSTONE-HORIZONTAL BALANCE	-30		VXX:GMKI7=-00030	QVX:GMKI7	GMKI7=-00030	✓	✓	✓
		+30		VXX:GMKI7=+00030		GMKI7=+00030	✓	✓	✓
	GEOMETRY-KEYSTONE-VERTICAL KEYSTONE	-40.0 (-45.0)*	0.2 step	VXX:GMKS8=-40.0	QVX:GMKS8	GMKS8=-40.0	✓	✓	✓
		+40.0 (+45.0)*		VXX:GMKS8=+40.0		GMKS8=+40.0	✓	✓	✓
	GEOMETRY-KEYSTONE-HORIZONTAL KEYSTONE	-15.0 (-40.0)*	0.2 step	VXX:GMKS9=-15.0	QVX:GMKS9	GMKS9=-15.0	✓	✓	✓
		+15.0 (+40.0)*		VXX:GMKS9=+15.0		GMKS9=+15.0	✓	✓	✓
	GEOMETRY-CURVED-LENS THROW RATIO	0.7	0.1 step	VXX:GMCS0=+00.7	QVX:GMCS0	GMCS0=+00.7	✓	✓	✓
		16.5		VXX:GMCS0=+16.5		GMCS0=+16.5	✓	✓	✓
	GEOMETRY-CURVED-VERTICAL ARC	-50 (-100)*		VXX:GMCI3=-00050	QVX:GMCI3	GMCI3=-00050	✓	✓	✓
		+50 (+100)*		VXX:GMCI3=+00050		GMCI3=+00050	✓	✓	✓
	GEOMETRY-CURVED-HORIZONTAL ARC	-50 (-100)*		VXX:GMCI7=-00050	QVX:GMCI7	GMCI7=-00050	✓	✓	✓
		+50 (+100)*		VXX:GMCI7=+00050		GMCI7=+00050	✓	✓	✓
	GEOMETRY-CURVED-VERTICAL BALANCE	-60		VXX:GMCI2=-00060	QVX:GMCI2	GMCI2=-00060	✓	✓	✓
		+60		VXX:GMCI2=+00060		GMCI2=+00060	✓	✓	✓
	GEOMETRY-CURVED-HORIZONTAL BALANCE	-30		VXX:GMCI6=-00030	QVX:GMCI6	GMCI6=-00030	✓	✓	✓
		+30		VXX:GMCI6=+00030		GMCI6=+00030	✓	✓	✓
	GEOMETRY-CURVED-VERTICAL KEYSTONE	-40.0 (-45.0)*	0.2 step	VXX:GMCS8=-40.0	QVX:GMCS8	GMCS8=-40.0	✓	✓	✓
		+40.0 (+45.0)*		VXX:GMCS8=+40.0		GMCS8=+40.0	✓	✓	✓
	GEOMETRY-CURVED-HORIZONTAL KEYSTONE	-15.0 (-40.0)*	0.2 step	VXX:GMCS9=-15.0	QVX:GMCS9	GMCS9=-15.0	✓	✓	✓
		+15.0 (+40.0)*		VXX:GMCS9=+15.0		GMCS9=+15.0	✓	✓	✓
	GEOMETRY-CURVED-MAINTAIN ASPECT RATIO	OFF		VXX:GMCIA=+00000	QVX:GMCIA	GMCIA=+00000	✓	✓	✓
		ON		VXX:GMCIA=+00001		GMCIA=+00001	✓	✓	✓
	GEOMETRY-CORNER CORRECTION-UPPER LEFT(V)	min.		VXX:GMFI1=+00000	QVX:GMFI1	GMFI1=+00000	0	0	0
		max.		VXX:GMFI1=+00300		GMFI1=+00300	+300	+300	+300
	GEOMETRY-CORNER CORRECTION-UPPER RIGHT(V)	min.		VXX:GMFI2=+00000	QVX:GMFI2	GMFI2=+00000	0	0	0
		max.		VXX:GMFI2=+00300		GMFI2=+00300	+300	+300	+300
	GEOMETRY-CORNER CORRECTION-LOWER LEFT(V)	min.		VXX:GMFI3=-00300	QVX:GMFI3	GMFI3=-00300	-300	-300	-300
		max.		VXX:GMFI3=+00000		GMFI3=+00000	0	0	0
	GEOMETRY-CORNER CORRECTION-LOWER RIGHT(V)	min.		VXX:GMFI4=-00300	QVX:GMFI4	GMFI4=-00300	-300	-300	-300
		max.		VXX:GMFI4=+00000		GMFI4=+00000	0	0	0
	GEOMETRY-CORNER CORRECTION-LINEARITY(V)	min.		VXX:GMFI5=-00127	QVX:GMFI5	GMFI5=-00127	-127	-127	-127
		max.		VXX:GMFI5=+00127		GMFI5=+00127	+127	+127	+127
	GEOMETRY-CORNER CORRECTION-UPPER LEFT(H)	min.		VXX:GMFI6=+00000	QVX:GMFI6	GMFI6=+00000	0	0	0
		max.		VXX:GMFI6=+00480		GMFI6=+00480	+480	+480	+480
	GEOMETRY-CORNER CORRECTION-UPPER RIGHT(H)	min.		VXX:GMFI7=-00480	QVX:GMFI7	GMFI7=-00480	-480	-480	-480
		max.		VXX:GMFI7=+00000		GMFI7=+00000	0	0	0
	GEOMETRY-CORNER CORRECTION-LOWER LEFT(H)	min.		VXX:GMFI8=+00000	QVX:GMFI8	GMFI8=+00000	0	0	0
		max.		VXX:GMFI8=+00480		GMFI8=+00480	+480	+480	+480
	GEOMETRY-CORNER CORRECTION-LOWER RIGHT(H)	min.		VXX:GMFI9=-00480	QVX:GMFI9	GMFI9=-00480	-480	-480	-480
		max.		VXX:GMFI9=+00000		GMFI9=+00000	0	0	0
	GEOMETRY-CORNER CORRECTION-LINEARITY(H)	min.		VXX:GMFIA=-00127	QVX:GMFIA	GMFIA=-00127	-127	-127	-127
		max.		VXX:GMFIA=+00127		GMFIA=+00127	+127	+127	+127
	GEOMETRY-CORNER/PINCUSHION-PINCUSHION UPPER	min.		VXX:GMFIB=-00100	QVX:GMFIB	GMFIB=-00100	✓	✓	✓
		max.		VXX:GMFIB=+00100		GMFIB=+00100	✓	✓	✓
	GEOMETRY-CORNER/PINCUSHION-PINCUSHION LOWER	min.		VXX:GMFIC=-00100	QVX:GMFIC	GMFIC=-00100	✓	✓	✓
		max.		VXX:GMFIC=+00100		GMFIC=+00100	✓	✓	✓
	GEOMETRY-CORNER/PINCUSHION-PINCUSHION LEFT	min.		VXX:GMFID=-00100	QVX:GMFID	GMFID=-00100	✓	✓	✓
		max.		VXX:GMFID=+00100		GMFID=+00100	✓	✓	✓
	GEOMETRY-CORNER/PINCUSHION-PINCUSHION RIGHT	min.		VXX:GMFIE=-00100	QVX:GMFIE	GMFIE=-00100	✓	✓	✓
		max.		VXX:GMFIE=+00100		GMFIE=+00100	✓	✓	✓
	GEOMETRY-CORNER/PINCUSHION-LINEARITY	AUTO		VXX:GMFIF=+00000	QVX:GMFIF	GMFIF=+00000	✓	✓	✓
		MANUAL		VXX:GMFIF=+00001		GMFIF=+00001	✓	✓	✓
	GEOMETRY - FREE GRID(ON/OFF)	OFF		VXX:GMGI1=+00000	QVX:GMGI1	GMGI1=+00000	✓	✓	✓
		ON		VXX:GMGI1=+00001		GMGI1=+00001	✓	✓	✓
	GEOMETRY - FREE GRID - INITIALIZE			VXX:GMGI2=+00001			✓	✓	✓
	GEOMETRY - FREE GRID - GRID RESOLUTION	2x2		VXX:GMGI3=+00002	QVX:GMGI3	GMGI3=+00002	✓	✓	✓
		3x3		VXX:GMGI3=+00003		GMGI3=+00003	✓	✓	✓
		5x5		VXX:GMGI3=+00005		GMGI3=+00005	✓	✓	✓
		9x9		VXX:GMGI3=+00009		GMGI3=+00009	✓	✓	✓
		17x17		VXX:GMGI3=+00017		GMGI3=+00017	✓	✓	✓
							✓	✓	✓
	GEOMETRY - FREE GRID - GRID COLOR	OFF		VXX:GMGI4=+00000	QVX:GMGI4	GMGI4=+00000	✓	✓	✓
		WHITE		VXX:GMGI4=+00001		GMGI4=+00001	✓	✓	✓
		BLACK		VXX:GMGI4=+00002		GMGI4=+00002	✓	✓	✓
		RED		VXX:GMGI4=+00003		GMGI4=+00003	✓	✓	✓
		GREEN		VXX:GMGI4=+00004		GMGI4=+00004	✓	✓	✓
		BLUE		VXX:GMGI4=+00005		GMGI4=+00005	✓	✓	✓
		CYAN		VXX:GMGI4=+00006		GMGI4=+00006	✓	✓	✓
		MAGENTA		VXX:GMGI4=+00007		GMGI4=+00007	✓	✓	✓
		YELLOW		VXX:GMGI4=+00008		GMGI4=+00008	✓	✓	✓
							✓	✓	✓
	GEOMETRY - FREE GRID - CONTROL POINTS	POINT		VXX:GMGI5=+00000	QVX:GMGI5	GMGI5=+00000	✓	✓	✓
		HORIZONTAL LINE		VXX:GMGI5=+00001		GMGI5=+00001	✓	✓	✓
		VERTICAL LINE		VXX:GMGI5=+00002		GMGI5=+00002	✓	✓	✓
	GEOMETRY - FREE GRID - GRID WIDTH	1		VXX:GMGI7=+00001	QVX:GMGI7	GMGI7=+00001	✓	✓	✓
		10		VXX:GMGI7=+00010		GMGI7=+00010	✓	✓	✓
	GEOMETRY - FREE GRID - CONTROL POINTS COLOR	WHITE		VXX:GMGI8=+00001	QVX:GMGI8	GMGI8=+00001	✓	✓	✓
		BLACK		VXX:GMGI8=+00002		GMGI8=+00002	✓	✓	✓
		RED		VXX:GMGI8=+00003		GMGI8=+00003	✓	✓	✓
		GREEN		VXX:GMGI8=+00004		GMGI8=+00004	✓	✓	✓
		BLUE		VXX:GMGI8=+00005		GMGI8=+00005	✓	✓	✓
		CYAN		VXX:GMGI8=+00006		GMGI8=+00006	✓	✓	✓
		MAGENTA		VXX:GMGI8=+00007		GMGI8=+00007	✓	✓	✓
		YELLOW		VXX:GMGI8=+00008		GMGI8=+00008	✓	✓	✓
	CONVERGENCE	OFF		VXX:CNVI1=+00000	QVX:CNVI1	CNVI1=+00000	✓	✓	✓
		ON		VXX:CNVI1=+00001		CNVI1=+00001	✓	✓	✓
CONVERGENCE - UPPER LEFT VERTICAL			VXX:CNVS2=:*****	QVX:CNVS2	CNVS2=:*****	✓	✓	✓	
			VXX:CNVS2=R:*****		CNVS2=R:*****	✓	✓	✓	
			VXX:CNVS2=G:*****		CNVS2=G:*****	✓	✓	✓	
			VXX:CNVS2=B:*****		CNVS2=B:*****	✓	✓	✓	
			VXX:CNVS2=:+00.00		CNVS2=:+00.00	✓	✓	✓	
			VXX:CNVS2=:+03.75		CNVS2=:+03.75	✓	✓	✓	
CONVERGENCE - UPPER LEFT HORIZONTAL			VXX:CNVS3=:*****	QVX:CNVS3	CNVS3=:*****	✓	✓	✓	
			VXX:CNVS3=R:*****		CNVS3=R:*****	✓	✓	✓	
			VXX:CNVS3=G:*****		CNVS3=G:*****	✓	✓	✓	
			VXX:CNVS3=B:*****		CNVS3=B:*****	✓	✓	✓	
			VXX:CNVS3=:+00.00		CNVS3=:+00.00	✓	✓	✓	
			VXX:CNVS3=:+03.75		CNVS3=:+03.75	✓	✓	✓	
CONVERGENCE - UPPER RIGHT VERTICAL			VXX:CNVS4=:*****	QVX:CNVS4	CNVS4=:*****	✓	✓	✓	
			VXX:CNVS4=R:*****		CNVS4=R:*****	✓	✓	✓	
			VXX:CNVS4=G:*****		CNVS4=G:*****	✓	✓	✓	
			VXX:CNVS4=B:*****		CNVS4=B:*****	✓	✓	✓	
			VXX:CNVS4=:+00.00		CNVS4=:+00.00	✓	✓	✓	
			VXX:CNVS4=:+03.75		CNVS4=:+03.75	✓	✓	✓	
CONVERGENCE - UPPER RIGHT HORIZONTAL			VXX:CNVS5=:*****	QVX:CNVS5	CNVS5=:*****	✓	✓	✓	
			VXX:CNVS5=R:*****		CNVS5=R:*****	✓	✓	✓	
			VXX:CNVS5=G:*****		CNVS5=G:*****	✓	✓	✓	
			VXX:CNVS5=B:*****		CNVS5=B:*****	✓	✓	✓	
			VXX:CNVS5=: -03.75		CNVS5=: -03.75	✓	✓	✓	
			VXX:CNVS5=:+00.00		CNVS5=:+00.00	✓	✓	✓	
CONVERGENCE - LOWER LEFT VERTICAL			VXX:CNVS6=:*****						

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ35K2 SERIES	RZ34K2 SERIES	Z330KC SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K2 SRQ350KC	RZ34K2 SRZ340KC	SRZ330C
	CONVERGENCE - LOWER RIGHT VERTICAL			VXX:CNVS7=*:+00.00		CNVS7=*:+00.00	✓	✓	✓
				VXX:CNVS8=*:*****	QVX:CNVS8	CNVS8=*:*****	✓	✓	✓
				VXX:CNVS8=R:*****		CNVS8=R:*****	✓	✓	✓
				VXX:CNVS8=G:*****		CNVS8=G:*****	✓	✓	✓
				VXX:CNVS8=B:*****		CNVS8=B:*****	✓	✓	✓
				VXX:CNVS8=*:-03.75		CNVS8=*:-03.75	✓	✓	✓
	CONVERGENCE - LOWER RIGHT HORIZONTAL			VXX:CNVS8=*:+00.00	QVX:CNVS9	CNVS8=*:+00.00	✓	✓	✓
				VXX:CNVS9=*:*****		CNVS9=*:*****	✓	✓	✓
				VXX:CNVS9=R:*****		CNVS9=R:*****	✓	✓	✓
				VXX:CNVS9=G:*****		CNVS9=G:*****	✓	✓	✓
				VXX:CNVS9=B:*****		CNVS9=B:*****	✓	✓	✓
				VXX:CNVS9=*:-03.75		CNVS9=*:-03.75	✓	✓	✓
	SHIFT-HORIZONTAL	0		VTH:0000	QTH	0000	✓	✓	✓
	SHIFT-VERTICAL	+4095		VTH:4095		4095	✓	✓	✓
		0		VTV:0000	QTV	0000	✓	✓	✓
		+4094		VTV:4094		4094	✓	✓	✓
	ASPECT	AUTO/VID AUTO/DEFAULT		VSE:0	QSE	0	✓	✓	✓
		NORMAL(4:3)		VSE:1		1	✓	✓	✓
		WIDE(16:9)		VSE:2		2	✓	✓	✓
		NATIVE(through)		VSE:5		5	✓	✓	✓
		FULL(HV FIT)		VSE:6		6	✓	✓	✓
		H-FIT		VSE:9		9	✓	✓	✓
	ZOOM-HORIZONTAL	50		OZH:050	QZH	050	✓	✓	✓
		999		OZH:999		999	✓	✓	✓
	ZOOM-VERTICAL	50		OZV:050	QZV	050	✓	✓	✓
		999		OZV:999		999	✓	✓	✓
	ZOOM-BOTH	50		OZO:050	QZO	050	✓	✓	✓
		999		OZO:999		999	✓	✓	✓
	ZOOM-INTERLOCKED	OFF		OZS:0	QZS	0	✓	✓	✓
		ON		OZS:1		1	✓	✓	✓
	ZOOM-MODE	INTERNAL		OZT:0	QZT	0	✓	✓	✓
		FULL		OZT:1		1	✓	✓	✓
ADVANCED	DIGITAL CINEMA REALITY	AUTO		OPD:0	QPD	0	✓	✓	✓
		OFF		OPD:1		1	✓	✓	✓
		30p/25p FIXED		OPD:2		2	✓	✓	✓
	GRADATION SMOOTHER	OFF		VXX:GRSI1=+00000	QVX:GRSI1	GRSI1=+00000	✓		
		1		VXX:GRSI1=+00001		GRSI1=+00001	✓		
		2		VXX:GRSI1=+00002		GRSI1=+00002	✓		
		3		VXX:GRSI1=+00003		GRSI1=+00003	✓		
	BLANKING-UPPER	min.		DBU:0000	QLU	0000	0	0	0
		max.		DBU:2398		2398	2398	1198	1198
	BLANKING-LOWER	min.		DBB:0000	QLB	0000	0	0	0
		max.		DBB:2398		2398	2398	1198	1198
	BLANKING-RIGHT	min.		DBR:0000	QLR	0000	0	0	0
		max.		DBR:3838		3838	3838	1918	1918
	BLANKING-LEFT	min.		DBL:0000	QLL	0000	0	0	0
		max.		DBL:3838		3838	3838	1918	1918
	CUSTOM MASKING *	OFF		VXX:MSKI1=+00000	QVX:MSKI1	MSKI1=+00000	✓	✓	✓
		PC-1		VXX:MSKI1=+00001		MSKI1=+00001	✓	✓	✓
		PC-2		VXX:MSKI1=+00002		MSKI1=+00002	✓	✓	✓
		PC-3		VXX:MSKI1=+00003		MSKI1=+00003	✓	✓	✓
	EDGE BLENDING	OFF		VXX:EDBI0=+00000	QVX:EDBI0	EDBI0=+00000	✓	✓	✓
		ON		VXX:EDBI0=+00001		EDBI0=+00001	✓	✓	✓
		USER		VXX:EDBI0=+00002		EDBI0=+00002	✓	✓	✓
	EDGE BLENDING-UPPER ON/OFF	OFF		VGU:0	QGU	0	✓	✓	✓
		ON		VGU:1		1	✓	✓	✓
	EDGE BLENDING-LOWER ON/OFF	OFF		VGB:0	QGB	0	✓	✓	✓
		ON		VGB:1		1	✓	✓	✓
	EDGE BLENDING-LEFT ON/OFF	OFF		VGL:0	QGL	0	✓	✓	✓
		ON		VGL:1		1	✓	✓	✓
	EDGE BLENDING-RIGHT ON/OFF	OFF		VGR:0	QGR	0	✓	✓	✓
		ON		VGR:1		1	✓	✓	✓
	EDGE BLENDING-START-UPPER	min.		VEU:0000	QEU	0000	0	0	0
		max.		VEU:2272		2272	2272	1023	1023
	EDGE BLENDING-START-LOWER	min.		VEB:0000	QEB	0000	0	0	0
		max.		VEB:2272		2272	2272	1199	1199
	EDGE BLENDING-START-LEFT	min.		VEL:0000	QEL	0000	0	0	0
		max.		VEL:3712		3712	3712	1023	1023
	EDGE BLENDING-START-RIGHT	min.		VER:0000	QER	0000	0	0	0
		max.		VER:3712		3712	3712	1919	1919
	EDGE BLENDING-WIDTH-UPPER	min.		VXX:EUIW0=+00000	QVX:EUIW0	EUIW0=+00000	0	0	0
		max.		VXX:EUIW0=+02272		EUIW0=+02272	2272	1023	1023
	EDGE BLENDING-WIDTH-LOWER	min.		VXX:EBWI0=+00000	QVX:EBWI0	EBWI0=+00000	0	0	0
		max.		VXX:EBWI0=+02272		EBWI0=+02272	2272	1199	1199
	EDGE BLENDING-WIDTH-LEFT	min.		VXX:ELWI0=+00000	QVX:ELWI0	ELWI0=+00000	0	0	0
		max.		VXX:ELWI0=+03712		ELWI0=+03712	3712	1023	1023
	EDGE BLENDING-WIDTH-RIGHT	min.		VXX:ERWI0=+00000	QVX:ERWI0	ERWI0=+00000	0	0	0
		max.		VXX:ERWI0=+03712		ERWI0=+03712	3712	1919	1919
	EDGE BLENDING-MARKER-ON/OFF	OFF		VGM:0	QGM	0	✓	✓	✓
		ON		VGM:1		1	✓	✓	✓
	EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL	0 (W,R,G,B)		VJI:000,000,000,000	QJI	000,000,000,000	✓	✓	✓
		255 (W,R,G,B)		VJI:255,255,255,255		255,255,255,255	✓	✓	✓
	EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL-INTERLOCKED	OFF		VXX:EBII1=+00000	QVX:EBII1	EBII1=+00000	✓	✓	✓
		ON		VXX:EBII1=+00001		EBII1=+00001	✓	✓	✓
	EDGE BLENDING-BLACK BORDER LEVEL	0 (W,R,G,B)		VJO:000,000,000,000	QJO	000,000,000,000	✓	✓	✓
		255 (W,R,G,B)		VJO:255,255,255,255		255,255,255,255	✓	✓	✓
	EDGE BLENDING-BLACK BORDER LEVEL-INTERLOCKED	OFF		VXX:EBII2=+00000	QVX:EBII2	EBII2=+00000	✓	✓	✓
		ON		VXX:EBII2=+00001		EBII2=+00001	✓	✓	✓
	EDGE BLENDING-BLACK BORDER WIDTH-UPPER	min.		VJU:0000	QJU	0000	0	0	0
		max.		VJU:2272		2272	2272	1023	1023
	EDGE BLENDING-BLACK BORDER WIDTH-LOWER	min.		VJB:0000	QJB	0000	0	0	0
		max.		VJB:2272		2272	2272	1199	1199
	EDGE BLENDING-BLACK BORDER WIDTH-LEFT	min.		VJL:0000	QJL	0000	0	0	0
		max.		VJL:3712		3712	3712	1023	1023
	EDGE BLENDING-BLACK BORDER WIDTH-RIGHT	min.		VJR:0000	QJR	0000	0	0	0
		max.		VJR:3712		3712	3712	1919	1919
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE	OFF		VXX:EBFI1=+00000	QVX:EBFI1	EBFI1=+00000	✓	✓	✓
		ON		VXX:EBFI1=+00001		EBFI1=+00001	✓	✓	✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE	OFF		VXX:EBFI2=+00000	QVX:EBFI2	EBFI2=+00000	✓	✓	✓
		ON		VXX:EBFI2=+00001		EBFI2=+00001	✓	✓	✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE	OFF		VXX:EBFI3=+00000	QVX:EBFI3	EBFI3=+00000	✓	✓	✓
		ON		VXX:EBFI3=+00001		EBFI3=+00001	✓	✓	✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE	OFF		VXX:EBFI4=+00000	QVX:EBFI4	EBFI4=+00000	✓	✓	✓
		ON		VXX:EBFI4=+00001		EBFI4=+00001	✓	✓	✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - UPPER - ADJUSTMENT POINTS	2		VXX:EFPI1=+00002	QVX:EFPI1	EFPI1=+00002	✓	✓	✓
		3		VXX:EFPI1=+00003		EFPI1=+00003	✓	✓	✓
		5		VXX:EFPI1=+00005		EFPI1=+00005	✓	✓	✓
		9		VXX:EFPI1=+00009		EFPI1=+00009	✓	✓	✓
		17		VXX:EFPI1=+00017		EFPI1=+00017	✓	✓	✓
		EXECUTE		VXX:EFII1=+00001			✓	✓	✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - LEFT - ADJUSTMENT POINTS	2		VXX:EFPI2=+00002	QVX:EFPI2	EFPI2=+00002	✓	✓	✓
		3		VXX:EFPI2=+00003		EFPI2=+00003	✓	✓	✓
		5		VXX:EFPI2=+00005		EFPI2=+00005	✓	✓	✓
		9		VXX:EFPI2=+00009		EFPI2=+00009	✓	✓	✓
		17		VXX:EFPI2=+00017		EFPI2=+00017	✓	✓	✓
		EXECUTE		VXX:EFII2=+00001			✓	✓	✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - LEFT - ADJUSTMENT POINTS	2		VXX:EFPI3=+00002	QVX:EFPI3	EFPI3=+00002	✓	✓	✓
		3		VXX:EFPI3=+00003		EFPI3=+00003	✓	✓	✓
		5		VXX:EFPI3=+00005		EFPI3=+00005	✓	✓	✓
		9		VXX:EFPI3=+00009		EFPI3=+00009	✓	✓	✓
		17		VXX:EFPI3=+00017		EFPI3=+00017	✓	✓	✓
		EXECUTE		VXX:EFII3=+00001			✓	✓	✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - RIGHT - ADJUSTMENT POINTS	2		VXX:EFPI4=+00002	QVX:EFPI4	EFPI4=+00002	✓	✓	✓
		3		VXX:EFPI4=+00003		EFPI4=+00003	✓	✓	✓
		5		VXX:EFPI4=+00005		EFPI4=+00005	✓	✓	✓
		9		VXX:EFPI4=+00009		EFPI4=+00009	✓	✓	✓
		17		VXX:EFPI4=+00017		EFPI4=+00017	✓	✓	✓
		EXECUTE		VXX:EFII4=+00001			✓	✓	✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-UPPER	0 (W,R,G,B)		VXX:EBBS0=000,000,000,000	QVX:EBBS0	EBBS0=000,000,000,000	✓	✓	✓
		255 (W,R,G,B)		VXX:EBBS0=255,255,255,255		EBBS0=255,255,255,255	✓	✓	✓
	EDGE BLENDING-OVERLAPPED BLACK	0 (W,R,G,B)		VXX:EBBS1=000,000,000,000	QVX:EBBS1	EBBS1=000,000,000,000	✓	✓	✓

				CONTROL	QUERY		RQ35K2 SERIES	RZ34K2 SERIES	Z330KC SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K2 SRQ350KC	RZ34K2 SRZ340KC	SRZ330C
	LEVEL-LOWER	255 (W,R,G,B)		VXX:EBBS1=255,255,255,255		EBBS1=255,255,255,255	✓	✓	✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LEFT	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS2=000,000,000,000 VXX:EBBS2=255,255,255,255	QVX:EBBS2	EBBS2=000,000,000,000 EBBS2=255,255,255,255	✓	✓	✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-RIGHT	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS3=000,000,000,000 VXX:EBBS3=255,255,255,255	QVX:EBBS3	EBBS3=000,000,000,000 EBBS3=255,255,255,255	✓	✓	✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-UPPER INTERLOCKED	OFF ON		VXX:EBII3=+00000 VXX:EBII3=+00001	QVX:EBII3	EBII3=+00000 EBII3=+00001	✓	✓	✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LOWER INTERLOCKED	OFF ON		VXX:EBII4=+00000 VXX:EBII4=+00001	QVX:EBII4	EBII4=+00000 EBII4=+00001	✓	✓	✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LEFT INTERLOCKED	OFF ON		VXX:EBII5=+00000 VXX:EBII5=+00001	QVX:EBII5	EBII5=+00000 EBII5=+00001	✓	✓	✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-RIGHT INTERLOCKED	OFF ON		VXX:EBII6=+00000 VXX:EBII6=+00001	QVX:EBII6	EBII6=+00000 EBII6=+00001	✓	✓	✓
	EDGE BLENDING-MODE	SOFTEDGE/BLACK LEVEL BLACK LEVEL ONLY		VXX:EBMI1=+00000 VXX:EBMI1=+00001	QVX:EBMI1	EBMI1=+00000 EBMI1=+00001	✓	✓	✓
	EDGE BLENDING-AUTO TESTPATTERN	OFF ON		VXX:EAT11=+00000 VXX:EAT11=+00001	QVX:EAT11	EAT11=+00000 EAT11=+00001	✓	✓	✓
	FRAME RESPONSE	NORMAL FAST FIXED		VXX:FDYI0=+00000 VXX:FDYI0=+00001 VXX:FDYI0=+00005	QVX:FDYI0	FDYI0=+00000 FDYI0=+00001 FDYI0=+00005	✓	✓	✓
	FRAME DELAY	0.00 100.00		VXX:FDYS1=+0.00 VXX:FDYS1=+100.00	QVX:FDYS1	FDYS1=+0.00 FDYS1=+100.00	✓	✓	✓
	FILM DETECTION	OFF ON		VXX:FDTI1=+00000 VXX:FDTI1=+00001	QVX:FDTI1	FDTI1=+00000 FDTI1=+00001	✓	✓	✓
	QUAD PIXEL DRIVE	OFF ON		VXX:QPD11=+00000 VXX:QPD11=+00001	QVX:QPD11	QPD11=+00000 QPD11=+00001	✓		
	RASTER POSITION-HORIZONTAL	-2048 +2047		VRH:2952 VRH:7047	QRH	2952 7047	✓	✓	✓
	RASTER POSITION-VERTICAL	-2048 +2047		VRV:2952 VRV:7047	QRV	2952 7047	✓	✓	✓
DISPLAY LANGUAGE	LANGUAGE	English German French Spanish Italian Japanese Chinese Russian Korea Portuguse		OLG:ENG OLG:DEU OLG:FRA OLG:ESP OLG:ITL OLG:JPN OLG:CHI OLG:RUS OLG:KOR OLG:POR	QLG	ENG DEU FRA ESP ITL JPN CHI RUS KOR POR	✓	✓	✓
	3D SYSTEM SETTING	SINGLE DUAL(LEFT) DUAL(RIGHT)		VXX:DSYI1=+00000 VXX:DSYI1=+00001 VXX:DSYI1=+00002	QVX:DSYI1	DSYI1=+00000 DSYI1=+00001 DSYI1=+00002		✓	✓
	3D SYNC SETTING	OFF 1 2 3 4 5 6 7 8 9 10 11		VXX:DSNI1=+00000 VXX:DSNI1=+00001 VXX:DSNI1=+00002 VXX:DSNI1=+00003 VXX:DSNI1=+00004 VXX:DSNI1=+00005 VXX:DSNI1=+00006 VXX:DSNI1=+00007 VXX:DSNI1=+00008 VXX:DSNI1=+00009 VXX:DSNI1=+00010 VXX:DSNI1=+00011	QVX:DSNI1	DSNI1=+00000 DSNI1=+00001 DSNI1=+00002 DSNI1=+00003 DSNI1=+00004 DSNI1=+00005 DSNI1=+00006 DSNI1=+00007 DSNI1=+00008 DSNI1=+00009 DSNI1=+00010 DSNI1=+00011		✓	✓
	3D SYNC SETTING-STEREO SYNC OUTPUT DELAY	0 25000	10 step	VXX:DSNI2=+00000 VXX:DSNI2=+25000	QVX:DSNI2	DSNI2=+00000 DSNI2=+25000		✓	✓
	3D INPUT FORMAT	AUTO NATIVE(2D) SIDE BY SIDE TOP AND BOTTOM FRAME SEQUENTIAL		VXX:DIFI1=+00000 VXX:DIFI1=+00001 VXX:DIFI1=+00003 VXX:DIFI1=+00004 VXX:DIFI1=+00006	QVX:DIFI1	DIFI1=+00000 DIFI1=+00001 DIFI1=+00003 DIFI1=+00004 DIFI1=+00006		✓	✓
	3D LEFT/RIGHT SWAP	NORMAL SWAPPED		VXX:DSWI1=+00000 VXX:DSWI1=+00001	QVX:DSWI1	DSWI1=+00000 DSWI1=+00001		✓	✓
	3D COLOR MATCHING	SHARED 2D/3D SEPARATE 2D/3D		VXX:DCMI1=+00000 VXX:DCMI1=+00001	QVX:DCMI1	DCMI1=+00000 DCMI1=+00001		✓	✓
	3D DARK TIME SETTING	0.5 1.0 1.5 2.0 2.5 2.7		VXX:DDTS1=+0.5 VXX:DDTS1=+1.0 VXX:DDTS1=+1.5 VXX:DDTS1=+2.0 VXX:DDTS1=+2.5 VXX:DDTS1=+2.7	QVX:DDTS1	DDTS1=+0.5 DDTS1=+1.0 DDTS1=+1.5 DDTS1=+2.0 DDTS1=+2.5 DDTS1=+2.7		✓	✓
	3D TEST MODE	NORMAL SIDE BY SIDE LEFT/LEFT RIGHT/RIGHT LEFT/BLACK BLACK/RIGHT		VXX:DTSI1=+00000 VXX:DTSI1=+00001 VXX:DTSI1=+00002 VXX:DTSI1=+00003 VXX:DTSI1=+00004 VXX:DTSI1=+00005	QVX:DTSI1	DTSI1=+00000 DTSI1=+00001 DTSI1=+00002 DTSI1=+00003 DTSI1=+00004 DTSI1=+00005		✓	✓
	3D SAFETY PRECAUTIONS MESSAGE	OFF ON		VXX:DMGI1=+00000 VXX:DMGI1=+00001	QVX:DMGI1	DMGI1=+00000 DMGI1=+00001		✓	✓
	COLOR MATCHING	OFF 3COLORS 7COLORS MEASURED		VXX:CMAI0=+00000 VXX:CMAI0=+00001 VXX:CMAI0=+00002 VXX:CMAI0=+00004	QVX:CMAI0	CMAI0=+00000 CMAI0=+00001 CMAI0=+00002 CMAI0=+00004	✓	✓	✓
	COLOR MATCHING-RESET MODE	NATIVE PICTURE REC709		VXX:CRMI1=+00000 VXX:CRMI1=+00001 VXX:CRMI1=+00002	QVX:CRMI1	CRMI1=+00000 CRMI1=+00001 CRMI1=+00002	✓	✓	✓
	COLOR MATCHING-3COLORS-RED	0 (R,G,B) 2048,2048,2048(R,G,B)		VMR:0000,0000,0000 VMR:2048,2048,2048	QMR	0000,0000,0000 2048,2048,2048	✓	✓	✓
	COLOR MATCHING-3COLORS-GREEN	0 (R,G,B) 2048,2048,2048(R,G,B)		VMG:0000,0000,0000 VMG:2048,2048,2048	QMG	0000,0000,0000 2048,2048,2048	✓	✓	✓
	COLOR MATCHING-3COLORS-BLUE	0 (R,G,B) 2048,2048,2048(R,G,B)		VMB:0000,0000,0000 VMB:2048,2048,2048	QMB	0000,0000,0000 2048,2048,2048	✓	✓	✓
	COLOR MATCHING-3COLORS-AUTO TESTPATTERN	OFF ON		VXX:CATI0=+00000 VXX:CATI0=+00001	QVX:CATI0	CATI0=+00000 CATI0=+00001	✓	✓	✓
	COLOR MATCHING-3COLORS-RESET	EXECUTE		VXX:CREI1=+00001			✓	✓	✓
	COLOR MATCHING-7COLORS-RED	0 (R,G,B) 2048(R,G,B)		VXX:C7CS0=0000,0000,0000 VXX:C7CS0=2048,2048,2048	QVX:C7CS0	C7CS0=0000,0000,0000 C7CS0=2048,2048,2048	✓	✓	✓
	COLOR MATCHING-7COLORS-GREEN	0 (R,G,B) 2048(R,G,B)		VXX:C7CS1=0000,0000,0000 VXX:C7CS1=2048,2048,2048	QVX:C7CS1	C7CS1=0000,0000,0000 C7CS1=2048,2048,2048	✓	✓	✓
	COLOR MATCHING-7COLORS-BLUE	0 (R,G,B) 2048(R,G,B)		VXX:C7CS2=0000,0000,0000 VXX:C7CS2=2048,2048,2048	QVX:C7CS2	C7CS2=0000,0000,0000 C7CS2=2048,2048,2048	✓	✓	✓
	COLOR MATCHING-7COLORS-CYAN	0 (R,G,B) 2048(R,G,B)		VXX:C7CS3=0000,0000,0000 VXX:C7CS3=2048,2048,2048	QVX:C7CS3	C7CS3=0000,0000,0000 C7CS3=2048,2048,2048	✓	✓	✓
	COLOR MATCHING-7COLORS-MAGENTA	0 (R,G,B) 2048(R,G,B)		VXX:C7CS4=0000,0000,0000 VXX:C7CS4=2048,2048,2048	QVX:C7CS4	C7CS4=0000,0000,0000 C7CS4=2048,2048,2048	✓	✓	✓
	COLOR MATCHING-7COLORS-YELLOW	0 (R,G,B) 2048(R,G,B)		VXX:C7CS5=0000,0000,0000 VXX:C7CS5=2048,2048,2048	QVX:C7CS5	C7CS5=0000,0000,0000 C7CS5=2048,2048,2048	✓	✓	✓
	COLOR MATCHING-7COLORS-WHITE	0 (R,G,B) 2048(R,G,B)		VXX:C7CS6=0000,0000,0000 VXX:C7CS6=2048,2048,2048	QVX:C7CS6	C7CS6=0000,0000,0000 C7CS6=2048,2048,2048	✓	✓	✓
	COLOR MATCHING-7COLORS-AUTO TESTPATTERN	OFF ON		VXX:CATI1=+00000 VXX:CATI1=+00001	QVX:CATI1	CATI1=+00000 CATI1=+00001	✓	✓	✓
	COLOR MATCHING-7COLORS-RESET	EXECUTE		VXX:CREI2=+00001			✓	✓	✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA BLACK	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS0=00000,0001,0001 VXX:CMMS0=65535,0999,0999	QVX:CMMS0	CMMS0=00000,0001,0001 CMMS0=65535,0999,0999	✓	✓	✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA RED	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS1=00000,0001,0001 VXX:CMMS1=65535,0999,0999	QVX:CMMS1	CMMS1=00000,0001,0001 CMMS1=65535,0999,0999	✓	✓	✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA GREEN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS2=00000,0001,0001 VXX:CMMS2=65535,0999,0999	QVX:CMMS2	CMMS2=00000,0001,0001 CMMS2=65535,0999,0999	✓	✓	✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA BLUE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS3=00000,0001,0001 VXX:CMMS3=65535,0999,0999	QVX:CMMS3	CMMS3=00000,0001,0001 CMMS3=65535,0999,0999	✓	✓	✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA WHITE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS4=00000,0001,0001 VXX:CMMS4=65535,0999,0999	QVX:CMMS4	CMMS4=00000,0001,0001 CMMS4=65535,0999,0999	✓	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA RED	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS0=00000,0001,0001 VXX:CMTS0=65535,0999,0999	QVX:CMTS0	CMTS0=00000,0001,0001 CMTS0=65535,0999,0999	✓	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA GREEN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS1=00000,0001,0001 VXX:CMTS1=65535,0999,0999	QVX:CMTS1	CMTS1=00000,0001,0001 CMTS1=65535,0999,0999	✓	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA BLUE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS2=00000,0001,0001 VXX:CMTS2=65535,0999,0999	QVX:CMTS2	CMTS2=00000,0001,0001 CMTS2=65535,0999,0999	✓	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA CYAN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS3=00000,0001,0001 VXX:CMTS3=65535,0999,0999	QVX:CMTS3	CMTS3=00000,0001,0001 CMTS3=65535,0999,0999	✓	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA MAGENTA	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS4=00000,0001,0001 VXX:CMTS4=65535,0999,0999	QVX:CMTS4	CMTS4=00000,0001,0001 CMTS4=65535,0999,0999	✓	✓	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ35K2 SERIES	RZ34K2 SERIES	RZ330KC SERIES		
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K2 SRQ350KC	RZ34K2 SRZ340KC	SRZ330C		
	COLOR MATCHING-MEASURED MODE-TARGET DATA YELLOW	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS5=00000,0001,0001 VXX:CMTS5=65535,0999,0999	QVX:CMTS5	CMTS5=00000,0001,0001 CMTS5=65535,0999,0999	✓	✓	✓		
	COLOR MATCHING-MEASURED MODE-TARGET DATA WHITE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS6=00000,0001,0001 VXX:CMTS6=65535,0999,0999	QVX:CMTS6	CMTS6=00000,0001,0001 CMTS6=65535,0999,0999	✓	✓	✓		
	COLOR MATCHING-MEASURED MODE-AUTO TESTPATTERN	OFF ON		VXX:CATI3=+00000 VXX:CATI3=+00001	QVX:CATI3	CATI3=+00000 CATI3=+00001	✓	✓	✓		
	COLOR MATCHING-MEASURED MODE-RESET	EXECUTE		VXX:CREI3=+00001			✓	✓	✓		
	AUTO SIGNAL	OFF ON		VXX:AASI0=+00000 VXX:AASI0=+00001	QVX:AASI0	AASI0=+00000 AASI0=+00001	✓	✓	✓		
	AUTO SETUP -POSITION ADJ.	OFF ON		VXX:APAI0=+00000 VXX:APAI0=+00001	QVX:APAI0	APAI0=+00000 APAI0=+00001	✓	✓	✓		
	AUTO SETUP -SIGNAL LEVEL ADJ.	OFF ON		VXX:ASLI0=+00000 VXX:ASLI0=+00001	QVX:ASLI0	ASLI0=+00000 ASLI0=+00001	✓	✓	✓		
	BACKUP INPUT SETTING-BACKUP INPUT	PRIMARY SECONDARY TOGGLE		VXX:BACI1=+00001 VXX:BACI1=+00002 VXX:BACI1=+00010	QVX:BACI1	BACI1=+00001 BACI1=+00002 BACI1=+00010	✓	✓	✓		
	BACKUP INPUT SETTING-BACKUP INPUT MODE	OFF 2 3 4		VXX:BACI2=+00000 VXX:BACI2=+00002 VXX:BACI2=+00003 VXX:BACI2=+00004	QVX:BACI2	BACI2=+00000 BACI2=+00002 BACI2=+00003 BACI2=+00004		✓	✓		
	BACKUP INPUT SETTING-BACKUP INPUT MODE	OFF HDMI1 (SLOT1) / HDMI2 (SLOT1) DVI1 (SLOT1) / DVI2 (SLOT1) SDI1 (SLOT1) / SDI3 (SLOT1) HDMI3 (SLOT2) / HDMI4 (SLOT2) DVI3 (SLOT2) / DVI4 (SLOT2) SDI1 (SLOT2) / SDI3 (SLOT2) Displayport1 (SLOT1) / Displayport3 (SLOT2) 135 SER OPT1 (SLOT1) / 135 SER OPT1 (SLOT2) HDMI1-2 (SLOT1) / HDMI3-4 (SLOT2) SDI1-3 (SLOT1) / SDI1-3 (SLOT2) SDI1-2-3-4 (SLOT1) / SDI1-2-3-4 (SLOT2)		VXX:BACI6=+00000 VXX:BACI6=+00012 VXX:BACI6=+00013 VXX:BACI6=+00014 VXX:BACI6=+00022 VXX:BACI6=+00023 VXX:BACI6=+00024 VXX:BACI6=+00055 VXX:BACI6=+00056 VXX:BACI6=+00102 VXX:BACI6=+00104 VXX:BACI6=+01003	QVX:BACI6	BACI6=+00000 BACI6=+00012 BACI6=+00013 BACI6=+00014 BACI6=+00022 BACI6=+00023 BACI6=+00024 BACI6=+00055 BACI6=+00056 BACI6=+00102 BACI6=+00104 BACI6=+01003	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓				
	BACKUP INPUT SETTING-AUTOMATIC SWITCHING	DISABLE ENABLE		VXX:BACI3=+00000 VXX:BACI3=+00001	QVX:BACI3	BACI3=+00000 BACI3=+00001	✓ ✓		✓ ✓	✓ ✓	
	BACKUP INPUT SETTING-BACKUP INPUT STATUS	INACTIVE ACTIVE			QVX:BACI4	BACI4=+00000 BACI4=+00001	✓ ✓	✓ ✓	✓ ✓	✓ ✓	
	SIMUL INPUT SETTING - SLOT IN (SDI In/Slot In Correspondence)	OFF AUTO (3D)		VXX:SMLI2=+00000 VXX:SMLI2=+00002	QVX:SMLI2	SMLI2=+00000 SMLI2=+00002			✓ ✓	✓ ✓	
	DVI-D IN-EDID	EDID1 EDID2(PC) EDID3		OED:1 OED:2 OED:3	QED	1 2 3			✓ ✓ ✓	✓ ✓ ✓	
	DVI-D IN-SIGNAL LEVEL	0-255 PC 15-235 AUTO		VXX:DVII0=+00000 VXX:DVII0=+00001 VXX:DVII0=+00002	QVX:DVII0	DVII0=+00000 DVII0=+00001 DVII0=+00002			✓ ✓ ✓	✓ ✓ ✓	
	DVI-D IN-EDID MODE	DEFAULT SCREEN FIT USER		VXX:EDMI2=+00000 VXX:EDMI2=+00001 VXX:EDMI2=+00010	QVX:EDMI0	EDMI2=+00000 EDMI2=+00001 EDMI2=+00010			✓ ✓ ✓	✓ ✓ ✓	
	DVI-D IN-EDID RESOLUTION	1024x768p 1280x720p 1280x800p 1280x1024p 1366x768p 1400x1050p 1440x900p 1600x900p 1600x1200p 1680x1050p 1920x1080p 1920x1080i 1920x1200p		VXX:EDRS2=1024:0768:p VXX:EDRS2=1280:0720:p VXX:EDRS2=1280:0800:p VXX:EDRS2=1280:1024:p VXX:EDRS2=1366:0768:p VXX:EDRS2=1400:1050:p VXX:EDRS2=1440:0900:p VXX:EDRS2=1600:0900:p VXX:EDRS2=1600:1200:p VXX:EDRS2=1680:1050:p VXX:EDRS2=1920:1080:p VXX:EDRS2=1920:1080:i VXX:EDRS2=1920:1200:p	QVX:EDRS2	EDRS2=1024:0768:p EDRS2=1280:0720:p EDRS2=1280:0800:p EDRS2=1280:1024:p EDRS2=1366:0768:p EDRS2=1400:1050:p EDRS2=1440:0900:p EDRS2=1600:0900:p EDRS2=1600:1200:p EDRS2=1680:1050:p EDRS2=1920:1080:p EDRS2=1920:1080:i EDRS2=1920:1200:p		✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓		✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	DVI-D IN-EDID VERTICAL SCAN FREQUENCY	60Hz 50Hz 48Hz 30Hz 25Hz 24Hz		VXX:EDVI2=+06000 VXX:EDVI2=+05000 VXX:EDVI2=+04800 VXX:EDVI2=+03000 VXX:EDVI2=+02500 VXX:EDVI2=+02400	QVX:EDVI2	EDVI2=+06000 EDVI2=+05000 EDVI2=+04800 EDVI2=+03000 EDVI2=+02500 EDVI2=+02400			✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓	
	DVI-D IN-EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER * PARAMETER1 * PARAMETER2 * PARAMETER3	 1024x768 1280x720 1280x800 1280x1024 1366x768 1400x1050 1440x900 1600x900 1600x1200 1680x1050 1920x1080 1920x1200 Progressive Interface 60Hz 50Hz 48Hz 30Hz 25Hz 24Hz	 VXX:EDDS1=1024:0768:*:**** VXX:EDDS1=1280:0720:*:**** VXX:EDDS1=1280:0800:*:**** VXX:EDDS1=1280:1024:*:**** VXX:EDDS1=1366:0768:*:**** VXX:EDDS1=1400:1050:*:**** VXX:EDDS1=1440:0900:*:**** VXX:EDDS1=1600:0900:*:**** VXX:EDDS1=1600:1200:*:**** VXX:EDDS1=1680:1050:*:**** VXX:EDDS1=1920:1080:*:**** VXX:EDDS1=1920:1200:*:**** VXX:EDDS1=*****:p:**** VXX:EDDS1=*****:i:**** VXX:EDDS1=*****:*:6000 VXX:EDDS1=*****:*:5000 VXX:EDDS1=*****:*:4800 VXX:EDDS1=*****:*:3000 VXX:EDDS1=*****:*:2500 VXX:EDDS1=*****:*:2400	QVX:EDDS1	EDDS1=*****:*:**** EDDS1=1024:0768:*:**** EDDS1=1280:0720:*:**** EDDS1=1280:0800:*:**** EDDS1=1280:1024:*:**** EDDS1=1366:0768:*:**** EDDS1=1400:1050:*:**** EDDS1=1440:0900:*:**** EDDS1=1600:0900:*:**** EDDS1=1600:1200:*:**** EDDS1=1680:1050:*:**** EDDS1=1920:1080:*:**** EDDS1=1920:1200:*:**** EDDS1=*****:p:**** EDDS1=*****:i:**** EDDS1=*****:*:6000 EDDS1=*****:*:5000 EDDS1=*****:*:4800 EDDS1=*****:*:3000 EDDS1=*****:*:2500 EDDS1=*****:*:2400			✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	DVI-D IN-EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER * PARAMETER1 * PARAMETER2 * PARAMETER3	 1024x768 1280x720 1280x800 1280x1024 1366x768 1400x1050 1440x900 1600x900 1600x1200 1680x1050 1920x1080 1920x1200 Progressive Interface 60Hz 50Hz 48Hz 30Hz 25Hz 24Hz	 <							

				CONTROL	QUERY		RQ35K2 SERIES	RZ34K2 SERIES	SRZ330KC SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K2 SRQ350KC	RZ34K2 SRZ340KC	SRZ330C	
		1920x1080p		VXX:EDRS3=1920:1080:p		EDRS3=1920:1080:p	✓	✓	✓	
		1920x1080i		VXX:EDRS3=1920:1080:i		EDRS3=1920:1080:i	✓	✓	✓	
		1920x1200p		VXX:EDRS3=1920:1200:p		EDRS3=1920:1200:p	✓	✓	✓	
		2048x1080p		VXX:EDRS3=2048:1080:p		EDRS3=2048:1080:p	✓			
		2560x1600p		VXX:EDRS3=2560:1600:p		EDRS3=2560:1600:p	✓			
		3840x2400p		VXX:EDRS3=3840:2400:p		EDRS3=3840:2400:p	✓	✓	✓	
		HDMI IN-EDID VERTICAL SCAN FREQUENCY	120Hz		VXX:EDVI3=+12000	QVX:EDVI3	EDVI3=+12000	✓	✓	✓
			60Hz		VXX:EDVI3=+06000		EDVI3=+06000	✓	✓	✓
			50Hz		VXX:EDVI3=+05000		EDVI3=+05000	✓	✓	✓
			48Hz		VXX:EDVI3=+04800		EDVI3=+04800	✓	✓	✓
	30Hz			VXX:EDVI3=+03000		EDVI3=+03000	✓	✓	✓	
	25Hz			VXX:EDVI3=+02500		EDVI3=+02500	✓	✓	✓	
	24Hz		VXX:EDVI3=+02400		EDVI3=+02400	✓	✓	✓		
	HDMI IN-HDMI1 EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX:EDHS1=*****:*:*****	QVX:EDHS1	EDHS1=*****:*:*****	✓	✓	✓	
		* PARAMETER1	1024x768	VXX:EDHS1=1024:0768:*:*****		EDHS1=1024:0768:*:*****	✓	✓	✓	
			1280x720	VXX:EDHS1=1280:0720:*:*****		EDHS1=1280:0720:*:*****	✓	✓	✓	
			1280x800	VXX:EDHS1=1280:0800:*:*****		EDHS1=1280:0800:*:*****	✓	✓	✓	
			1280x1024	VXX:EDHS1=1280:1024:*:*****		EDHS1=1280:1024:*:*****	✓	✓	✓	
			1366x768	VXX:EDHS1=1366:0768:*:*****		EDHS1=1366:0768:*:*****	✓	✓	✓	
			1400x1050	VXX:EDHS1=1400:1050:*:*****		EDHS1=1400:1050:*:*****	✓	✓	✓	
			1440x900	VXX:EDHS1=1440:0900:*:*****		EDHS1=1440:0900:*:*****	✓	✓	✓	
			1600x900	VXX:EDHS1=1600:0900:*:*****		EDHS1=1600:0900:*:*****	✓	✓	✓	
			1600x1200	VXX:EDHS1=1600:1200:*:*****		EDHS1=1600:1200:*:*****	✓	✓	✓	
			1680x1050	VXX:EDHS1=1680:1050:*:*****		EDHS1=1680:1050:*:*****	✓	✓	✓	
			1920x1080	VXX:EDHS1=1920:1080:*:*****		EDHS1=1920:1080:*:*****	✓	✓	✓	
			1920x1200	VXX:EDHS1=1920:1200:*:*****		EDHS1=1920:1200:*:*****	✓	✓	✓	
			2048x1080	VXX:EDHS1=2048:1080:*:*****		EDHS1=2048:1080:*:*****	✓			
			2560x1600	VXX:EDHS1=2560:1600:*:*****		EDHS1=2560:1600:*:*****	✓			
			3840x2400	VXX:EDHS1=3840:2400:*:*****		EDHS1=3840:2400:*:*****	✓	✓	✓	
		* PARAMETER2	Progressive Interlace	VXX:EDHS1=*****:p:***** VXX:EDHS1=*****:i:*****		EDHS1=*****:p:***** EDHS1=*****:i:*****	✓	✓	✓	
			120Hz	VXX:EDHS1=*****:*:12000		EDHS1=*****:*:12000	✓	✓	✓	
			60Hz	VXX:EDHS1=*****:*:06000		EDHS1=*****:*:06000	✓	✓	✓	
			50Hz	VXX:EDHS1=*****:*:05000		EDHS1=*****:*:05000	✓	✓	✓	
			48Hz	VXX:EDHS1=*****:*:04800		EDHS1=*****:*:04800	✓	✓	✓	
			30Hz	VXX:EDHS1=*****:*:03000		EDHS1=*****:*:03000	✓	✓	✓	
			25Hz	VXX:EDHS1=*****:*:02500		EDHS1=*****:*:02500	✓	✓	✓	
			24Hz	VXX:EDHS1=*****:*:02400		EDHS1=*****:*:02400	✓	✓	✓	
					VXX:EDHS1=*****:*:02400	QVX:ESHS1	ESHS1=*****:*:*****	✓	✓	✓
	HDMI IN-HDMI1 EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER					ESHS1=1024:0768:*:*****	✓	✓	✓
		* PARAMETER1	1024x768				ESHS1=1280:0720:*:*****	✓	✓	✓
			1280x720				ESHS1=1280:0800:*:*****	✓	✓	✓
			1280x800				ESHS1=1280:1024:*:*****	✓	✓	✓
			1280x1024				ESHS1=1366:0768:*:*****	✓	✓	✓
			1366x768				ESHS1=1400:1050:*:*****	✓	✓	✓
			1400x1050				ESHS1=1440:0900:*:*****	✓	✓	✓
			1440x900				ESHS1=1600:0900:*:*****	✓	✓	✓
			1600x900				ESHS1=1600:1200:*:*****	✓	✓	✓
			1600x1200				ESHS1=1680:1050:*:*****	✓	✓	✓
			1680x1050				ESHS1=1920:1080:*:*****	✓	✓	✓
			1920x1080				ESHS1=1920:1200:*:*****	✓	✓	✓
			1920x1200				ESHS1=2048:1080:*:*****	✓		
			2048x1080				ESHS1=2560:1600:*:*****	✓		
			2560x1600				ESHS1=3840:2400:*:*****	✓	✓	✓
		3840x2400				ESHS1=*****:p:*****	✓	✓	✓	
		* PARAMETER2	Progressive Interlace			ESHS1=*****:i:*****	✓	✓	✓	
			120Hz				ESHS1=*****:*:12000	✓	✓	✓
			60Hz				ESHS1=*****:*:06000	✓	✓	✓
			50Hz				ESHS1=*****:*:05000	✓	✓	✓
			48Hz				ESHS1=*****:*:04800	✓	✓	✓
			30Hz				ESHS1=*****:*:03000	✓	✓	✓
			25Hz				ESHS1=*****:*:02500	✓	✓	✓
			24Hz				ESHS1=*****:*:02400	✓	✓	✓
						ESHS1=*****:*:02400	✓	✓	✓	
	DIGITAL LINK-SIGNAL LEVEL	AUTO		VXX:DKLI1=+00000	QVX:DKLI1	DKLI1=+00000	✓	✓	✓	
		0-1023		VXX:DKLI1=+00001		DKLI1=+00001	✓	✓	✓	
		64-940		VXX:DKLI1=+00002		DKLI1=+00002	✓	✓	✓	
	DIGITAL LINK-AUTO GAMMA SELECT	DISABLE		VXX:LAGI1=+00000	QVX:LAGI1	LAGI1=+00000	✓	✓	✓	
		ENABLE		VXX:LAGI1=+00001		LAGI1=+00001	✓	✓	✓	
	DIGITAL LINK- AUTO COLOR SPACE SELECT	DISABLE		VXX:LACI1=+00000	QVX:LACI1	LACI1=+00000	✓	✓	✓	
		ENABLE		VXX:LACI1=+00001		LACI2=+00001	✓	✓	✓	
	DIGITAL LINK-EDID SELECT (SINGLE LINK)	EDID1:4K/60p		VXX:LESI1=+00000	QVX:LESI1	LESI1=+00000	✓	✓	✓	
		EDID2:4K/30p		VXX:LESI1=+00001		LESI1=+00001	✓	✓	✓	
		EDID3:2K		VXX:LESI1=+00002		LESI1=+00002	✓	✓	✓	
		EDID4:4K/30p/HDR		VXX:LESI1=+00011		LESI1=+00011	✓	✓	✓	
	DIGITAL LINK-EDID MODE	DEFAULT		VXX:EDMI4=+00000	QVX:EDMI4	EDMI4=+00000	✓	✓	✓	
		SCREEN FIT		VXX:EDMI4=+00001		EDMI4=+00001		✓	✓	
		USER		VXX:EDMI4=+00010		EDMI4=+00010	✓	✓	✓	
	DIGITAL LINK-EDID RESOLUTION	1024x768p		VXX:EDRS4=1024:0768:p	QVX:EDRS4	EDRS4=1024:0768:p	✓	✓	✓	
		1280x720p		VXX:EDRS4=1280:0720:p		EDRS4=1280:0720:p	✓	✓	✓	
		1280x800p		VXX:EDRS4=1280:0800:p		EDRS4=1280:0800:p	✓	✓	✓	
		1280x1024p		VXX:EDRS4=1280:1024:p		EDRS4=1280:1024:p	✓	✓	✓	
		1366x768p		VXX:EDRS4=1366:0768:p		EDRS4=1366:0768:p	✓	✓	✓	
		1400x1050p		VXX:EDRS4=1400:1050:p		EDRS4=1400:1050:p	✓	✓	✓	
		1440x900p		VXX:EDRS4=1440:0900:p		EDRS4=1440:0900:p	✓	✓	✓	
		1600x900p		VXX:EDRS4=1600:0900:p		EDRS4=1600:0900:p	✓	✓	✓	
		1600x1200p		VXX:EDRS4=1600:1200:p		EDRS4=1600:1200:p	✓	✓	✓	
		1680x1050p		VXX:EDRS4=1680:1050:p		EDRS4=1680:1050:p	✓	✓	✓	
		1920x1080p		VXX:EDRS4=1920:1080:p		EDRS4=1920:1080:p	✓	✓	✓	
		1920x1080i		VXX:EDRS4=1920:1080:i		EDRS4=1920:1080:i	✓	✓	✓	
		1920x1200p		VXX:EDRS4=1920:1200:p		EDRS4=1920:1200:p	✓	✓	✓	
		2048x1080p		VXX:EDRS4=2048:1080:p		EDRS4=2048:1080:p	✓			
		2560x1600p		VXX:EDRS4=2560:1600:p		EDRS4=2560:1600:p	✓			
		3840x2400p		VXX:EDRS4=3840:2400:p		EDRS4=3840:2400:p	✓	✓	✓	
	DIGITAL LINK-EDID VERTICAL SCAN FREQUENCY	60Hz		VXX:EDVI4=+06000	QVX:EDVI4	EDVI4=+06000	✓	✓	✓	
		50Hz		VXX:EDVI4=+05000		EDVI4=+05000	✓	✓	✓	
		48Hz		VXX:EDVI4=+04800		EDVI4=+04800	✓	✓	✓	
		30Hz		VXX:EDVI4=+03000		EDVI4=+03000	✓	✓	✓	
		25Hz		VXX:EDVI4=+02500		EDVI4=+02500	✓	✓	✓	
		24Hz		VXX:EDVI4=+02400		EDVI4=+02400	✓	✓	✓	
	DIGITAL LINK-EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX:EDLS1=*****:*:****	QVX:EDLS1	EDLS1=*****:*:****	✓	✓	✓	
	* PARAMETER1	1024x768	VXX:EDLS1=1024:0768:*:****		EDLS1=1024:0768:*:****	✓	✓	✓		
		1280x720	VXX:EDLS1=1280:0720:*:****		EDLS1=1280:0720:*:****	✓	✓	✓		
		1280x800	VXX:EDLS1=1280:0800:*:****		EDLS1=1280:0800:*:****	✓	✓	✓		
		1280x1024	VXX:EDLS1=1280:1024:*:****		EDLS1=1280:1024:*:****	✓	✓	✓		
		1366x768	VXX:EDLS1=1366:0768:*:****		EDLS1=1366:0768:*:****	✓	✓	✓		
		1400x1050	VXX:EDLS1=1400:1050:*:****		EDLS1=1400:1050:*:****	✓	✓	✓		
		1440x900	VXX:EDLS1=1440:0900:*:****		EDLS1=1440:0900:*:****	✓	✓	✓		
		1600x900	VXX:EDLS1=1600:0900:*:****		EDLS1=1600:0900:*:****	✓	✓	✓		
		1600x1200	VXX:EDLS1=1600:1200:*:****		EDLS1=1600:1200:*:****	✓	✓	✓		
		1680x1050	VXX:EDLS1=1680:1050:*:****		EDLS1=1680:1050:*:****	✓	✓	✓		
		1920x1080	VXX:EDLS1=1920:1080:*:****		EDLS1=1920:1080:*:****	✓	✓	✓		
		1920x1200	VXX:EDLS1=1920:1200:*:****		EDLS1=1920:1200:*:****	✓	✓	✓		
		2048x1080	VXX:EDLS1=2048:1080:*:****		EDLS1=2048:1080:*:****	✓				
		2560x1600	VXX:EDLS1=2560:1600:*:****		EDLS1=2560:1600:*:****	✓				
		3840x2400	VXX:EDLS1=3840:2400:*:****		EDLS1=3840:2400:*:****	✓	✓	✓		
	* PARAMETER2	Progressive Interlace	VXX:EDLS1=*****:p:**** VXX:EDLS1=*****:i:****		EDLS1=*****:p:**** EDLS1=*****:i:****	✓	✓	✓		
	* PARAMETER3	60Hz	VXX:EDLS1=*****:*:6000		EDLS1=*****:*:6000	✓	✓	✓		
		50Hz	VXX:EDLS1=*****:*:5000		EDLS1=*****:*:5000	✓	✓	✓		
		48Hz	VXX:EDLS1=*****:*:4800		EDLS1=*****:*:4800	✓	✓	✓		
		30Hz	VXX:EDLS1=*****:*:3000		EDLS1=*****:*:3000	✓	✓	✓		
		25Hz	VXX:EDLS1=*****:*:2500		EDLS1=*****:*:2500	✓	✓	✓		
		24Hz	VXX:EDLS1=*****:*:2400		EDLS1=*****:*:2400	✓	✓	✓		
						EDLS1=*****:*:2400	✓	✓	✓	
					QVX:ESLS1	ESLS1=*****:*:****	✓	✓	✓	
	DIGITAL LINK-EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER				ESLS1=1024:0768:*:****	✓	✓	✓	
	1024x768				ESLS1=1280:0720:*:****	✓	✓	✓		
	1280x720				ESLS1=1280:0800:*:****	✓	✓	✓		
	1280x800				ESLS1=1280:1024:*:****	✓	✓	✓		
	1280x1024				ESLS1=13					

				CONTROL	QUERY		RQ35K2 SERIES	RZ34K2 SERIES	SRZ330KC SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K2 SRO350KC	RZ34K2 SRZ340KC	SRZ330C
			1680x1050			ESLS1=1680:1050:*:****	✓	✓	✓
			1920x1080			ESLS1=1920:1080:*:****	✓	✓	✓
			1920x1200			ESLS1=1920:1200:*:****	✓	✓	✓
			2048x1080			ESLS1=2048:1080:*:****	✓		
			2560x1600			ESLS1=2560:1600:*:****	✓		
			3440x1440			ESLS1=3440:1440:*:****	✓	✓	✓
			3840x2400			ESLS1=3840:2400:*:****	✓	✓	✓
		* PARAMETER2	Progressive Interlace			ESLS1=*****:p:****	✓	✓	✓
						ESLS1=*****:i:****	✓	✓	✓
		* PARAMETER3	60Hz			ESLS1=*****:6000	✓	✓	✓
			50Hz			ESLS1=*****:5000	✓	✓	✓
			48Hz			ESLS1=*****:4800	✓	✓	✓
			30Hz			ESLS1=*****:3000	✓	✓	✓
			25Hz			ESLS1=*****:2500	✓	✓	✓
			24Hz			ESLS1=*****:2400	✓	✓	✓
	SDI IN-SIGNAL LEVEL (SDI1)	64-940		VXX:SSLI1=+00000	QVX:SSLI1	SSLI1=+00000		✓	✓
		4-1019		VXX:SSLI1=+00001		SSLI1=+00001		✓	✓
	SDI IN-BIT DEPTH (SDI1)	AUTO		VXX:SBTI1=+00000	QVX:SBTI1	SBTI1=+00000			✓
		12-bit		VXX:SBTI1=+00001		SBTI1=+00001		✓	✓
		10-bit		VXX:SBTI1=+00002		SBTI1=+00002		✓	✓
	SDI IN-3G SDI MAPPING (SDI1)	AUTO		VXX:SGMI1=+00000	QVX:SGMI1	SGMI1=+00000		✓	✓
		LEVEL A		VXX:SGMI1=+00001		SGMI1=+00001		✓	✓
		LEVEL B		VXX:SGMI1=+00002		SGMI1=+00002		✓	✓
	SDI RESOLUTION	* PARAMETER		VXX:*****=+*****	QVX:*****	*****=+*****		✓	✓
		* PARAMETER1	SDI1	VXX:SRSI1=+*****		SRSI1=+*****		✓	✓
		* PARAMETER2	AUTO	VXX:*****=+00000		*****=+00000		✓	✓
			1280x720p	VXX:*****=+00003		*****=+00003		✓	✓
			1920x1080i	VXX:*****=+00005		*****=+00005		✓	✓
			1920x1080p	VXX:*****=+00006		*****=+00006		✓	✓
			1920x1080sF	VXX:*****=+00007		*****=+00007		✓	✓
			2048x1080p	VXX:*****=+00009		*****=+00009		✓	✓
	SDI SYSTEM SELECTOR	* PARAMETER		VXX:SYSS1=*:****:*****	QVX:SYSS1=*:****	SYSS1=*:****:*****		✓	✓
		* PARAMETER1, 2	SDI1	VXX:SYSS1=1:1		SYSS1=1:1:****		✓	✓
		* PARAMETER3	AUTO	VXX:SYSS1=*:****:00000		SYSS1=*:****:00000		✓	✓
			RGB	VXX:SYSS1=*:****:00001		SYSS1=*:****:00001		✓	✓
			YPbPr4:4:4	VXX:SYSS1=*:****:00002		SYSS1=*:****:00002		✓	✓
			YPbPr4:2:2	VXX:SYSS1=*:****:00003		SYSS1=*:****:00003		✓	✓
	SDI IN - SDI MODE(ET-MDN12G10)	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=+*****	✓	✓	✓
		* PARAMETER1, 2	SLOT1	VXX:SLSS1=VXX:SMOI1=+*****		SLSS1=SMOI1=+*****	✓	✓	✓
			SLOT2	VXX:SLSS2=VXX:SMOI1=+*****		SLSS2=SMOI1=+*****	✓		
		* PARAMETER3	INPUT	VXX:*****=VXX:*****=+00000		*****=+00000	✓	✓	✓
			OUTPUT	VXX:*****=VXX:*****=+00001		*****=+00001	✓	✓	✓
	SLOT - SDI IN - SDI LINK(ET-MDN12G10)	* PARAMETER		VXX:*****=VXX:*****=+00000		*****=+*****	✓	✓	✓
		* PARAMETER1, 2	SLOT1	VXX:SLSS1=VXX:SLKI3=+*****		SLSS1=SLKI3=+*****	✓	✓	✓
			SLOT2	VXX:SLSS2=VXX:SLKI3=+*****		SLSS2=SLKI3=+*****	✓		
		* PARAMETER3	SNGL LINK	VXX:*****=VXX:*****=+00000		*****=+00000	✓	✓	✓
			DUAL LINK	VXX:*****=VXX:*****=+00001		*****=+00001	✓	✓	✓
			QUAD LINK	VXX:*****=VXX:*****=+00002		*****=+00002	✓		
			AUTO	VXX:*****=VXX:*****=+00010		*****=+00010	✓	✓	✓
	SLOT - HDMI IN - HDMI LINK	SINGLE LINK		VXX:HLKI1=+00000	QVX:HLKI1	HLKI1=+00000	✓		
		QUAD LINK		VXX:HLKI1=+00002		HLKI1=+00002	✓		
		AUTO		VXX:HLKI1=+00010		HLKI1=+00010	✓		
		DUAL / DUAL		VXX:HLKI1=+00100		HLKI1=+00100	✓		
		DUAL / SINGLE		VXX:HLKI1=+00101		HLKI1=+00101	✓		
		SINGLE / DUAL		VXX:HLKI1=+00102		HLKI1=+00102	✓		
	SLOT - DVI IN - DVI LINK	SINGLE LINK		VXX:DLKI1=+00000	QVX:DLKI1	DLKI1=+00000	✓		
		QUAD LINK		VXX:DLKI1=+00002		DLKI1=+00002	✓		
		AUTO		VXX:DLKI1=+00010		DLKI1=+00010	✓		
	SLOT : SDI RESOLUTION	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=+*****	✓	✓	✓
		* PARAMETER1, 2 (ET-MDN12G10)	SLOT1:SDI1	VXX:SLSS1=VXX:SRSI1=+*****		SLSS1=SRSI1=+*****	✓	✓	✓
			SLOT1:SDI2	VXX:SLSS1=VXX:SRSI2=+*****		SLSS1=SRSI2=+*****	✓	✓	✓
			SLOT1:SDI3	VXX:SLSS1=VXX:SRSI3=+*****		SLSS1=SRSI3=+*****	✓	✓	✓
			SLOT1:SDI4	VXX:SLSS1=VXX:SRSI4=+*****		SLSS1=SRSI4=+*****	✓	✓	✓
			SLOT2:SDI1	VXX:SLSS2=VXX:SRSI1=+*****		SLSS2=SRSI1=+*****	✓		
			SLOT2:SDI2	VXX:SLSS2=VXX:SRSI2=+*****		SLSS2=SRSI2=+*****	✓		
			SLOT2:SDI3	VXX:SLSS2=VXX:SRSI3=+*****		SLSS2=SRSI3=+*****	✓		
			SLOT2:SDI4	VXX:SLSS2=VXX:SRSI4=+*****		SLSS2=SRSI4=+*****	✓		
			DUAL LINK(SLOT1:SDI1+3	VXX:SLSS1=VXX:SRDI1=+*****		SLSS1=SRDI1=+*****	✓	✓	✓
			DUAL LINK(SLOT2:SDI1+3	VXX:SLSS2=VXX:SRDI1=+*****		SLSS2=SRDI1=+*****	✓		
			QUAD LINK(SLOT1:SDI1+2+3+4)	VXX:SLSS1=VXX:SRQI1=+*****		SLSS1=SRQI1=+*****	✓		
			QUAD LINK(SLOT2:SDI1+2+3+4)	VXX:SLSS2=VXX:SRQI1=+*****		SLSS2=SRQI1=+*****	✓		
			AUTO	VXX:*****=VXX:*****=+00000		*****=+00000	✓	✓	✓
			1280x720p	VXX:*****=VXX:*****=+00003		*****=+00003	✓	✓	✓
		1920x1080i	VXX:*****=VXX:*****=+00005		*****=+00005	✓	✓	✓	
		1920x1080p	VXX:*****=VXX:*****=+00006		*****=+00006	✓	✓	✓	
		1920x1080sF	VXX:*****=VXX:*****=+00007		*****=+00007	✓	✓	✓	
		2048x1080p	VXX:*****=VXX:*****=+00009		*****=+00009	✓	✓	✓	
		3840x2160p	VXX:*****=VXX:*****=+00011		*****=+00011	✓	✓	✓	
		4096x2160p	VXX:*****=VXX:*****=+00013		*****=+00013	✓	✓	✓	
	SLOT : SDI : SDI 4K DIVISION	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=+*****	✓		
		* PARAMETER1, 2 (ET-MDN12G10)	SINGLE LINK(SLOT1:SDI1)	VXX:SLSS1=VXX:SKSI1=+*****		SLSS1=SKSI1=+*****	✓		
			SINGLE LINK(SLOT1:SDI3)	VXX:SLSS1=VXX:SKSI3=+*****		SLSS1=SKSI3=+*****	✓		
			SINGLE LINK(SLOT2:SDI1)	VXX:SLSS2=VXX:SKSI1=+*****		SLSS2=SKSI1=+*****	✓		
			SINGLE LINK(SLOT2:SDI3)	VXX:SLSS2=VXX:SKSI3=+*****		SLSS2=SKSI3=+*****	✓		
			DUAL LINK(SLOT1:SDI1+3	VXX:SLSS1=VXX:SKDI1=+*****		SLSS1=SKDI1=+*****	✓		
			DUAL LINK(SLOT2:SDI1+3	VXX:SLSS2=VXX:SKDI1=+*****		SLSS2=SKDI1=+*****	✓		
			QUAD LINK(SLOT1:SDI1+2+3+4)	VXX:SLSS1=VXX:SKQI1=+*****		SLSS1=SKQI1=+*****	✓		
			QUAD LINK(SLOT2:SDI1+2+3+4)	VXX:SLSS2=VXX:SKQI1=+*****		SLSS2=SKQI1=+*****	✓		
		* PARAMETER3	AUTO	VXX:*****=VXX:*****=+00000		*****=+00000	✓		
			SQUARE	VXX:*****=VXX:*****=+00001		*****=+00001	✓		
			INTERLEAVE	VXX:*****=VXX:*****=+00002		*****=+00002	✓		
	SLOT : SDI : SDI 3G-SDI MAPPING	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=+*****	✓	✓	✓
		* PARAMETER1, 2 (ET-MDN12G10)	SINGLE LINK(SLOT1:SDI1)	VXX:SLSS1=VXX:SGMI1=+*****		SLSS1=SGMI1=+*****	✓	✓	✓
			SINGLE LINK(SLOT1:SDI2)	VXX:SLSS1=VXX:SGMI2=+*****		SLSS1=SGMI2=+*****	✓	✓	✓
			SINGLE LINK(SLOT1:SDI3)	VXX:SLSS1=VXX:SGMI3=+*****		SLSS1=SGMI3=+*****	✓	✓	✓
			SINGLE LINK(SLOT1:SDI4)	VXX:SLSS1=VXX:SGMI4=+*****		SLSS1=SGMI4=+*****	✓	✓	✓
			SINGLE LINK(SLOT2:SDI1)	VXX:SLSS2=VXX:SGMI1=+*****		SLSS2=SGMI1=+*****	✓		
			SINGLE LINK(SLOT2:SDI2)	VXX:SLSS2=VXX:SGMI2=+*****		SLSS2=SGMI2=+*****	✓		
			SINGLE LINK(SLOT2:SDI3)	VXX:SLSS2=VXX:SGMI3=+*****		SLSS2=SGMI3=+*****	✓		
			SINGLE LINK(SLOT2:SDI4)	VXX:SLSS2=VXX:SGMI4=+*****		SLSS2=SGMI4=+*****	✓		
			DUAL LINK(SLOT1:SDI1+3	VXX:SLSS1=VXX:DGMI3=+*****		SLSS1=DGMI3=+*****	✓	✓	✓
			DUAL LINK(SLOT2:SDI1+3	VXX:SLSS2=VXX:DGMI3=+*****		SLSS2=DGMI3=+*****	✓		
			QUAD LINK(SLOT1:SDI1+2+3+4)	VXX:SLSS1=VXX:QGMI1=+*****		SLSS1=QGMI1=+*****	✓		
			QUAD LINK(SLOT2:SDI1+2+3+4)	VXX:SLSS2=VXX:QGMI1=+*****		SLSS2=QGMI1=+*****	✓		
		* PARAMETER3 (ET-MDN12G10)	AUTO	VXX:*****=VXX:*****=+00000		*****=+00000	✓	✓	✓
			TYPE1/LEVEL A	VXX:*****=VXX:*****=+00001		*****=+00001	✓	✓	✓
			TYPE2/LEVEL B	VXX:*****=VXX:*****=+00002		*****=+00002	✓	✓	✓
	SLOT : SDI : SDI SYSTEM SELECTOR	* PARAMETER		VXX:*****=VXX:*****=+*****:*****	QVX:*****=QVX:*****=+*****	*****=+*****:*****	✓	✓	✓
		* PARAMETER1, 2 (ET-MDN12G10)	SINGLE LINK(SLOT1:SDI1)	VXX:SLSS1=VXX:SYSS1=1:1:****	QVX:SLSS1=QVX:SYSS1=1:1	SLSS1=SYSS1=1:1:****	✓	✓	✓
			SINGLE LINK(SLOT1:SDI2)	VXX:SLSS1=VXX:SYSS1=1:2:****	QVX:SLSS1=QVX:SYSS1=1:2	SLSS1=SYSS1=1:2:****	✓	✓	✓
			SINGLE LINK(SLOT1:SDI3)	VXX:SLSS1=VXX:SYSS1=1:3:****	QVX:SLSS1=QVX:SYSS1=1:3	SLSS1=SYSS1=1:3:****	✓	✓	✓
			SINGLE LINK(SLOT1:SDI4)	VXX:SLSS1=VXX:SYSS1=1:4:****	QVX:SLSS1=QVX:SYSS1=1:4	SLSS1=SYSS1=1:4:****	✓	✓	✓

				CONTROL		QUERY	RQ35K2 SERIES	RZ34K2 SERIES	SRZ330KC SERI	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K2 SRQ350KC	RZ34K2 SRZ340KC	SRZ330C	
DISPLAY OPTION	SLOT : SDI : SIGNAL LEVEL		DUAL LINK(SDI1+3)	VXX:SLSS1=VXX:SBTI3=+*****		SLSS1=SBTI3=+*****	✓	✓	✓	
			DUAL LINK(SDI1+3)	VXX:SLSS2=VXX:SBTI3=+*****		SLSS2=SBTI3=+*****	✓			
			QUAD LINK (SDI1+2+3+4)	VXX:SLSS1=VXX:SBTI7=+*****		SLSS1=SBTI7=+*****	✓			
			QUAD LINK (SDI1+2+3+4)	VXX:SLSS2=VXX:SBTI7=+*****		SLSS2=SBTI7=+*****	✓			
		* PARAMETER3	AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	✓	
			12-bit	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓	✓	
			10-bit	VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	✓	✓	
				VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓	✓	
		* PARAMETER1, 2 (ET-MDN12G10)	SINGLE LINK(SLOT1:SDI1)	VXX:SLSS1=VXX:SSLI1=+*****		SLSS1=SSLI1=+*****	✓	✓	✓	
			SINGLE LINK(SLOT1:SDI2)	VXX:SLSS1=VXX:SSLI2=+*****		SLSS1=SSLI2=+*****	✓			
			SINGLE LINK(SLOT1:SDI3)	VXX:SLSS1=VXX:SSLI4=+*****		SLSS1=SSLI4=+*****	✓	✓	✓	
			SINGLE LINK(SLOT1:SDI4)	VXX:SLSS1=VXX:SSLI5=+*****		SLSS1=SSLI5=+*****	✓	✓	✓	
			SINGLE LINK(SLOT2:SDI1)	VXX:SLSS2=VXX:SSLI1=+*****		SLSS2=SSLI1=+*****	✓			
			SINGLE LINK(SLOT2:SDI2)	VXX:SLSS2=VXX:SSLI2=+*****		SLSS2=SSLI2=+*****	✓			
			SINGLE LINK(SLOT2:SDI3)	VXX:SLSS2=VXX:SSLI4=+*****		SLSS2=SSLI4=+*****	✓			
			SINGLE LINK(SLOT2:SDI4)	VXX:SLSS2=VXX:SSLI5=+*****		SLSS2=SSLI5=+*****	✓			
			DUAL LINK(SDI1+3)	VXX:SLSS1=VXX:SSLI3=+*****		SLSS1=SSLI3=+*****	✓	✓	✓	
			DUAL LINK(SDI1+3)	VXX:SLSS2=VXX:SSLI3=+*****		SLSS2=SSLI3=+*****	✓			
			QUAD LINK (SDI1+2+3+4)	VXX:SLSS1=VXX:SSLI7=+*****		SLSS1=SSLI7=+*****	✓			
			QUAD LINK (SDI1+2+3+4)	VXX:SLSS2=VXX:SSLI7=+*****		SLSS2=SSLI7=+*****	✓			
	* PARAMETER3	64-940	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	✓		
		4-1019	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓	✓		
			VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓	✓		
			VXX:SLSS1=VXX:HSLI1=+*****		SLSS1=HSLI1=+*****	✓	✓	✓		
	SLOT : HDMI : SIGNAL LEVEL	* PARAMETER1, 2	HDMI1	VXX:SLSS1=VXX:HSLI2=+*****		SLSS1=HSLI2=+*****	✓	✓	✓	
			HDMI2	VXX:SLSS2=VXX:HSLI1=+*****		SLSS2=HSLI1=+*****	✓			
			HDMI3	VXX:SLSS2=VXX:HSLI2=+*****		SLSS2=HSLI2=+*****	✓			
			HDMI4	VXX:SLSS1=VXX:HSDI1=+*****		SLSS1=HSDI1=+*****	✓			
		DUAL LINK 1(HDMI1+2)	VXX:SLSS2=VXX:HSDI1=+*****		SLSS2=HSDI1=+*****	✓				
		DUAL LINK 2(HDMI3+4)	VXX:SLDS1=VXX:HSQI1=+*****		SLDS1=HSQI1=+*****	✓				
		QUAD LINK (HDMI1+2+3+4)	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	✓		
		* PARAMETER3	0-1023	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓	✓	
			64-940	VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	✓	✓	
			AUTO	VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓	✓	
				VXX:SLSS1=VXX:SLSS1=VXX:SAGI1=+*****		SLSS1=SLSS1=SAGI1=+*****	✓	✓	✓	
		SLOT : HDMI : AUTO GAMMA SELECT	* PARAMETER1, 2	HDMI1	VXX:SLSS1=VXX:HAGI2=+*****		SLSS1=HAGI2=+*****	✓	✓	✓
	HDMI2			VXX:SLSS2=VXX:SLSS1=VXX:SAGI1=+*****		SLSS2=SLSS1=SAGI1=+*****	✓			
	HDMI3			VXX:SLSS2=VXX:HAGI2=+*****		SLSS2=HAGI2=+*****	✓			
	HDMI4			VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	✓	
	* PARAMETER3		DISABLE	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓	✓	
			ENABLE	VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓	✓	
				VXX:SLSS1=VXX:SLSS1=VXX:SACI1=+*****		SLSS1=SLSS1=SACI1=+*****	✓	✓	✓	
			HDMI2	VXX:SLSS1=VXX:HACI2=+*****		SLSS1=HACI2=+*****	✓	✓	✓	
	* PARAMETER1, 2		HDMI1	VXX:SLSS2=VXX:SLSS1=VXX:SACI1=+*****		SLSS2=SLSS1=SACI1=+*****	✓			
			HDMI2	VXX:SLSS2=VXX:HACI2=+*****		SLSS2=HACI2=+*****	✓			
			HDMI3	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	✓	
			HDMI4	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓	✓	
	SLOT : HDMI : EDID SELECT	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓	✓	
			HDMI1	VXX:SLSS1=VXX:HESI1=+*****		SLSS1=HESI1=+*****	✓	✓	✓	
			HDMI2	VXX:SLSS1=VXX:HESI2=+*****		SLSS1=HESI2=+*****	✓	✓	✓	
			HDMI3	VXX:SLSS2=VXX:HESI1=+*****		SLSS2=HESI1=+*****	✓			
			HDMI4	VXX:SLSS2=VXX:HESI2=+*****		SLSS2=HESI2=+*****	✓			
		* PARAMETER3	4K/60p/SDR	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	✓	
			4K/30p	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓	✓	
			2K	VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	✓	✓	
			4K/60p/HDR	VXX:*****=VXX:*****=+00010		*****=*****=+00010	✓	✓	✓	
		SLOT : HDMI : EDID MODE	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓	✓
				HDMI1	VXX:SLSS1=VXX:EDMI3=+*****		SLSS1=EDMI3=+*****	✓	✓	✓
				HDMI2	VXX:SLSS1=VXX:EDMI6=+*****		SLSS1=EDMI6=+*****	✓	✓	✓
	HDMI3			VXX:SLSS2=VXX:EDMI3=+*****		SLSS2=EDMI3=+*****	✓			
	HDMI4			VXX:SLSS2=VXX:EDMI6=+*****		SLSS2=EDMI6=+*****	✓			
	* PARAMETER3		DEFAULT	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	✓	
			SCREEN FIT	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓	✓	
			USER	VXX:*****=VXX:*****=+00010		*****=*****=+00010	✓	✓	✓	
	SLOT : HDMI : EDID RESOLUTION	* PARAMETER		VXX:*****=VXX:*****=*****.*	QVX:*****=QVX:*****	*****=*****=*****.*	✓	✓	✓	
			HDMI1	VXX:SLSS1=VXX:EDRS3=*****.*		SLSS1=EDRS3=*****.*	✓	✓	✓	
			HDMI2	VXX:SLSS1=VXX:EDRS6=*****.*		SLSS1=EDRS6=*****.*	✓	✓	✓	
			HDMI3	VXX:SLSS2=VXX:EDRS3=*****.*		SLSS2=EDRS3=*****.*	✓			
			HDMI4	VXX:SLSS2=VXX:EDRS6=*****.*		SLSS2=EDRS6=*****.*	✓			
		* PARAMETER3	1024x768	VXX:*****=VXX:*****=1024:0768.*		*****=*****=1024:0768.*	✓	✓	✓	
			1280x720	VXX:*****=VXX:*****=1280:0720.*		*****=*****=1280:0720.*	✓	✓	✓	
			1280x800	VXX:*****=VXX:*****=1280:0800.*		*****=*****=1280:0800.*	✓	✓	✓	
			1280x1024	VXX:*****=VXX:*****=1280:1024.*		*****=*****=1280:1024.*	✓	✓	✓	
			1366x768	VXX:*****=VXX:*****=1366:0768.*		*****=*****=1366:0768.*	✓	✓	✓	
			1400x1050	VXX:*****=VXX:*****=1400:1050.*		*****=*****=1400:1050.*	✓	✓	✓	
			1440x900	VXX:*****=VXX:*****=1440:0900.*		*****=*****=1440:0900.*	✓	✓	✓	
			1600x900	VXX:*****=VXX:*****=1600:0900.*		*****=*****=1600:0900.*	✓	✓	✓	
			1600x1200	VXX:*****=VXX:*****=1600:1200.*		*****=*****=1600:1200.*	✓	✓	✓	
			1680x1050	VXX:*****=VXX:*****=1680:1050.*		*****=*****=1680:1050.*	✓	✓	✓	
			1920x1080	VXX:*****=VXX:*****=1920:1080.*		*****=*****=1920:1080.*	✓	✓	✓	
			1920x1200	VXX:*****=VXX:*****=1920:1200.*		*****=*****=1920:1200.*	✓	✓	✓	
			1920x2160	VXX:*****=VXX:*****=1920:2160.*		*****=*****=1920:2160.*	✓	✓	✓	
			2048x1080	VXX:*****=VXX:*****=2048:1080.*		*****=*****=2048:1080.*	✓	✓	✓	
			2048x2160	VXX:*****=VXX:*****=2048:2160.*		*****=*****=2048:2160.*	✓	✓	✓	
			2560x1600	VXX:*****=VXX:*****=2560:1600.*		*****=*****=2560:1600.*	✓	✓	✓	
			3840x2400	VXX:*****=VXX:*****=3840:2400.*		*****=*****=3840:2400.*	✓	✓	✓	
		* PARAMETER4	Progressive	VXX:*****=VXX:*****=*****.*p		*****=*****=*****.*p	✓	✓	✓	
			Interface	VXX:*****=VXX:*****=*****.*i		*****=*****=*****.*i	✓	✓	✓	
	SLOT : HDMI : EDID VERTICAL SCAN FREQUENCY	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓	✓	
			HDMI1	VXX:SLSS1=VXX:EDVI3=+*****		SLSS1=EDVI3=+*****	✓	✓	✓	
			HDMI2	VXX:SLSS1=VXX:EDVI6=+*****		SLSS1=EDVI6=+*****	✓	✓	✓	
			HDMI3	VXX:SLSS2=VXX:EDVI3=+*****		SLSS2=EDVI3=+*****	✓			
			HDMI4	VXX:SLSS2=VXX:EDVI6=+*****		SLSS2=EDVI6=+*****	✓			
		* PARAMETER3	60Hz	VXX:*****=VXX:*****=+06000		*****=*****=+06000	✓	✓	✓	
			50Hz	VXX:*****=VXX:*****=+05000		*****=*****=+05000	✓	✓	✓	
			48Hz	VXX:*****=VXX:*****=+04800		*****=*****=+04800	✓	✓	✓	
			30Hz	VXX:*****=VXX:*****=+03000		*****=*****=+03000	✓	✓	✓	
			25Hz	VXX:*****=VXX:*****=+02500		*****=*****=+02500	✓	✓	✓	
			24Hz	VXX:*****=VXX:*****=+02400		*****=*****=+02400	✓	✓	✓	
				VXX:*****=VXX:*****=*****.*	QVX:*****=QVX:*****	*****=*****=*****.*	✓	✓	✓	
	* PARAMETER1, 2	HDMI1	VXX:SLSS1=VXX:EDHS1=*****.*		SLSS1=EDHS1=*****.*	✓	✓	✓		
		HDMI2	VXX:SLSS1=VXX:EDHS2=*****.*		SLSS1=EDHS2=*****.*	✓	✓	✓		
		HDMI3	VXX:SLSS2=VXX:EDHS1=*****.*		SLSS2=EDHS1=*****.*	✓				
		HDMI4	VXX:SLSS2=VXX:EDHS2=*****.*		SLSS2=EDHS2=*****.*	✓				
		1024x768	VXX:*****=VXX:*****=1024:0768.*		*****=*****=1024:0768.*	✓	✓	✓		
		1280x720	VXX:*****=VXX:*****=1280:0720.*		*****=*****=1280:0720.*	✓	✓	✓		
		1280x800	VXX:*****=VXX:*****=1280:0800.*		*****=*****=1280:0800.*	✓	✓	✓		
		1280x1024	VXX:*****=VXX:*****=1280:1024.*		*****=*****=1280:1024.*	✓	✓	✓		
		1366x768	VXX:*****=VXX:*****=1366:0768.*		*****=*****=1366:0768.*	✓	✓	✓		
		1400x1050	VXX:*****=VXX:*****=1400:1050.*		*****=*****=1400:1050.*	✓	✓	✓		
		1440x900	VXX:*****=VXX:*****=1440:0900.*		*****=*****=1440:0900.*	✓	✓	✓		
		1600x900	VXX:*****=VXX:*****=1600:0900.*		*****=*****=1600:0900.*	✓	✓	✓		
		1600x1200	VXX:*****=VXX:*****=1600:1200.*		*****=*****=1600:1200.*	✓	✓	✓		
		1680x1050	VXX:*****=VXX:*****=1680:1050.*		*****=*****=1680:1050.*	✓	✓	✓		
		1920x1080	VXX:*****=VXX:*****=1920:1080.*		*****=*****=1920:1080.*	✓	✓	✓		
		1920x1200	VXX:*****=VXX:*****=1920:1200.*		*****=*****=1920:1200.*	✓	✓	✓		
		1920x2160	VXX:*****=VXX:*****=1920:2160.*		*****=*****=1920:2160.*	✓	✓	✓		
	2048x1080	VXX:*****=VXX:*****=2048:1080.*		*****=*****=2048:1080.*	✓	✓	✓			
	2048x2160	VXX:*****=VXX:*****=2048:2160.*		*****=*****=2048:2160.*	✓	✓	✓			
	2560x1600	VXX:*****=VXX:*****=2560:1600.*		*****=*****=2560:1600.*	✓	✓	✓			
3840x2400	VXX:*****=VXX:*****=3840:2400.*		*****=*****=3840:2400.*	✓	✓	✓				
SLOT : HDMI : EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX:*****=VXX:*****=*****.*	QVX:*****=QVX:*****	*****=*****=*****.*	✓	✓	✓		
		HDMI1	VXX:SLSS1=VXX:EDHS1=*****.*		SLSS1=EDHS1=*****.*	✓	✓	✓		
		HDMI2	VXX:SLSS1=VXX:EDHS2=*****.*		SLSS1=EDHS2=*****.*	✓	✓	✓		
		HDMI3	VXX:SLSS2=VXX:EDHS1=*****.*		SLSS2=EDHS1=*****.*	✓				
		HDMI4	VXX:SLSS2=VXX:EDHS2=*****.*		SLSS2=EDHS2=*****.*	✓				
	* PARAMETER3	1024x768	VXX:*****=VXX:*****=1024:0768.*							

				CONTROL	QUERY		RQ35K2 SERIES	RZ34K2 SERIES	Z330KC SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K2 SERIES SRQ350KC	RZ34K2 SRZ340KC	SRZ330C
		* PARAMETER3	HDMI4			SLSS2=ESH52=*****:*.*****	✓		
			1024x768			*****=*****=1024:0768:*.*****	✓	✓	✓
			1280x720			*****=*****=1280:0720:*.*****	✓	✓	✓
			1280x800			*****=*****=1280:0800:*.*****	✓	✓	✓
			1280x1024			*****=*****=1280:1024:*.*****	✓	✓	✓
			1366x768			*****=*****=1366:0768:*.*****	✓	✓	✓
			1400x1050			*****=*****=1400:1050:*.*****	✓	✓	✓
			1440x900			*****=*****=1440:0900:*.*****	✓	✓	✓
			1600x900			*****=*****=1600:0900:*.*****	✓	✓	✓
			1600x1200			*****=*****=1600:1200:*.*****	✓	✓	✓
			1680x1050			*****=*****=1680:1050:*.*****	✓	✓	✓
			1920x1080			*****=*****=1920:1080:*.*****	✓	✓	✓
			1920x1200			*****=*****=1920:1200:*.*****	✓	✓	✓
			1920x2160			*****=*****=1920:2160:*.*****	✓	✓	✓
			2048x1080			*****=*****=2048:1080:*.*****	✓		
			2048x2160			*****=*****=2048:2160:*.*****	✓		
			2560x1600			*****=*****=2560:1600:*.*****	✓		
			3840x2400			*****=*****=3840:2400:*.*****	✓		
		* PARAMETER4	Progressive			*****=*****=*****:p:*****	✓	✓	✓
			Interlace			*****=*****=*****:j:*****	✓	✓	✓
		* PARAMETERS5	60Hz			*****=*****=*****:*.6000	✓	✓	✓
			50Hz			*****=*****=*****:*.5000	✓	✓	✓
			48Hz			*****=*****=*****:*.4800	✓	✓	✓
			30Hz			*****=*****=*****:*.3000	✓	✓	✓
			25Hz			*****=*****=*****:*.2500	✓	✓	✓
			24Hz			*****=*****=*****:*.2400	✓	✓	✓
SLOT : DVI : SIGNAL LEVEL	* PARAMETER			VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓	✓
	* PARAMETER1, 2	DVI1		VXX:SLSS1=VXX:DVII0=+*****		SLSS1=DVII0=+*****	✓	✓	✓
		DVI2		VXX:SLSS1=VXX:DVII2=+*****		SLSS1=DVII2=+*****	✓	✓	✓
		DVI3		VXX:SLSS2=VXX:DVII0=+*****		SLSS2=DVII0=+*****	✓		
		DVI4		VXX:SLSS2=VXX:DVII2=+*****		SLSS2=DVII2=+*****	✓		
		QUAD LINK (DVI1+2+3+4)		VXX:SLDS1=VXX:DVQI1=+*****		SLDS1=DVQI1=+*****	✓		
	* PARAMETER3	0-255(PC)		VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	✓
		16-235		VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓	✓
		AUTO		VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	✓	✓
SLOT : DVI : EDID SELECT	* PARAMETER			VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓	✓
	* PARAMETER1, 2	DVI1		VXX:SLSS1=VXX:DSLII1=+*****		SLSS1=DSLII1=+*****	✓	✓	✓
		DVI2		VXX:SLSS1=VXX:DSLII2=+*****		SLSS1=DSLII2=+*****	✓	✓	✓
		DVI3		VXX:SLSS2=VXX:DSLII1=+*****		SLSS2=DSLII1=+*****	✓		
		DVI4		VXX:SLSS2=VXX:DSLII2=+*****		SLSS2=DSLII2=+*****	✓		
	* PARAMETER3	EDID1:4K/60p		VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	✓
		EDID2:4K/30p		VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓	✓
		EDID3:2K		VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	✓	✓
	* PARAMETER			VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓	✓
SLOT : DVI : EDID MODE	* PARAMETER			VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓	✓
	* PARAMETER1, 2	DVI1		VXX:SLSS1=VXX:EDMI2=+*****		SLSS1=EDMI2=+*****	✓	✓	✓
		DVI2		VXX:SLSS1=VXX:EDMI5=+*****		SLSS1=EDMI5=+*****	✓	✓	✓
		DVI3		VXX:SLSS2=VXX:EDMI2=+*****		SLSS2=EDMI2=+*****	✓		
		DVI4		VXX:SLSS2=VXX:EDMI5=+*****		SLSS2=EDMI5=+*****	✓		
	* PARAMETER3	DEFAULT		VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	✓
		SCREEN FIT		VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓	✓
		USER		VXX:*****=VXX:*****=+00010		*****=*****=+00010	✓	✓	✓
	* PARAMETER			VXX:*****=VXX:*****=*****:*.*	QVX:*****=QVX:*****	*****=*****=*****:*.*	✓	✓	✓
SLOT : DVI : EDID RESOLUTION	* PARAMETER			VXX:*****=VXX:*****=*****:*.*	QVX:*****=QVX:*****	*****=*****=*****:*.*	✓	✓	✓
	* PARAMETER1, 2	DVI1		VXX:SLSS1=VXX:EDRS2=*****:*.*		SLSS1=EDRS2=*****:*.*	✓	✓	✓
		DVI2		VXX:SLSS1=VXX:EDRS5=*****:*.*		SLSS1=EDRS5=*****:*.*	✓	✓	✓
		DVI3		VXX:SLSS2=VXX:EDRS2=*****:*.*		SLSS2=EDRS2=*****:*.*	✓		
		DVI4		VXX:SLSS2=VXX:EDRS5=*****:*.*		SLSS2=EDRS5=*****:*.*	✓		
	* PARAMETER3	1024x768		VXX:*****=VXX:*****=1024:0768:*.*****		*****=*****=1024:0768:*.*****	✓	✓	✓
		1280x720		VXX:*****=VXX:*****=1280:0720:*.*****		*****=*****=1280:0720:*.*****	✓	✓	✓
		1280x800		VXX:*****=VXX:*****=1280:0800:*.*****		*****=*****=1280:0800:*.*****	✓	✓	✓
		1280x1024		VXX:*****=VXX:*****=1280:1024:*.*****		*****=*****=1280:1024:*.*****	✓	✓	✓
		1366x768		VXX:*****=VXX:*****=1366:0768:*.*****		*****=*****=1366:0768:*.*****	✓	✓	✓
		1400x1050		VXX:*****=VXX:*****=1400:1050:*.*****		*****=*****=1400:1050:*.*****	✓	✓	✓
		1440x900		VXX:*****=VXX:*****=1440:0900:*.*****		*****=*****=1440:0900:*.*****	✓	✓	✓
		1600x900		VXX:*****=VXX:*****=1600:0900:*.*****		*****=*****=1600:0900:*.*****	✓	✓	✓
		1600x1200		VXX:*****=VXX:*****=1600:1200:*.*****		*****=*****=1600:1200:*.*****	✓	✓	✓
		1680x1050		VXX:*****=VXX:*****=1680:1050:*.*****		*****=*****=1680:1050:*.*****	✓	✓	✓
		1920x1080		VXX:*****=VXX:*****=1920:1080:*.*****		*****=*****=1920:1080:*.*****	✓	✓	✓
		1920x1200		VXX:*****=VXX:*****=1920:1200:*.*****		*****=*****=1920:1200:*.*****	✓	✓	✓
		2048x1080		VXX:*****=VXX:*****=2048:1080:*.*****		*****=*****=2048:1080:*.*****	✓	✓	✓
	* PARAMETER4	Progressive		VXX:*****=VXX:*****=*****:p		*****=*****=*****:p	✓	✓	✓
		Interlace		VXX:*****=VXX:*****=*****:j		*****=*****=*****:j	✓	✓	✓
SLOT : DVI : EDID VERTICAL SCAN FREQUENCY	* PARAMETER			VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓	✓
	* PARAMETER1, 2	DVI1		VXX:SLSS1=VXX:EDVI2=+*****		SLSS1=EDVI2=+*****	✓	✓	✓
		DVI2		VXX:SLSS1=VXX:EDVI5=+*****		SLSS1=EDVI5=+*****	✓	✓	✓
		DVI3		VXX:SLSS2=VXX:EDVI2=+*****		SLSS2=EDVI2=+*****	✓		
		DVI4		VXX:SLSS2=VXX:EDVI5=+*****		SLSS2=EDVI5=+*****	✓		
	* PARAMETER3	60Hz		VXX:*****=VXX:*****=+06000		*****=*****=+06000	✓	✓	✓
		50Hz		VXX:*****=VXX:*****=+05000		*****=*****=+05000	✓	✓	✓
		48Hz		VXX:*****=VXX:*****=+04800		*****=*****=+04800	✓	✓	✓
		30Hz		VXX:*****=VXX:*****=+03000		*****=*****=+03000	✓	✓	✓
		25Hz		VXX:*****=VXX:*****=+02500		*****=*****=+02500	✓	✓	✓
		24Hz		VXX:*****=VXX:*****=+02400		*****=*****=+02400	✓	✓	✓
	* PARAMETER4	Progressive		VXX:*****=VXX:*****=*****:p		*****=*****=*****:p	✓	✓	✓
		Interlace		VXX:*****=VXX:*****=*****:j		*****=*****=*****:j	✓	✓	✓
	* PARAMETER			VXX:*****=VXX:*****=*****:*.*	QVX:*****=QVX:*****	*****=*****=*****:*.*	✓	✓	✓
	* PARAMETER1, 2	DVI1		VXX:SLSS1=VXX:EDDS1=*****:*.*****		SLSS1=EDDS1=*****:*.*****	✓	✓	✓
		DVI2		VXX:SLSS1=VXX:EDDS2=*****:*.*****		SLSS1=EDDS2=*****:*.*****	✓	✓	✓
		DVI3		VXX:SLSS2=VXX:EDDS1=*****:*.*****		SLSS2=EDDS1=*****:*.*****	✓		
		DVI4		VXX:SLSS2=VXX:EDDS2=*****:*.*****		SLSS2=EDDS2=*****:*.*****	✓		
	* PARAMETER3	1024x768		VXX:*****=VXX:*****=1024:0768:*.*****		*****=*****=1024:0768:*.*****	✓	✓	✓
		1280x720		VXX:*****=VXX:*****=1280:0720:*.*****		*****=*****=1280:0720:*.*****	✓	✓	✓
		1280x800		VXX:*****=VXX:*****=1280:0800:*.*****		*****=*****=1280:0800:*.*****	✓	✓	✓
		1280x1024		VXX:*****=VXX:*****=1280:1024:*.*****		*****=*****=1280:1024:*.*****	✓	✓	✓
		1366x768		VXX:*****=VXX:*****=1366:0768:*.*****		*****=*****=1366:0768:*.*****	✓	✓	✓
		1400x1050		VXX:*****=VXX:*****=1400:1050:*.*****		*****=*****=1400:1050:*.*****	✓	✓	✓
		1440x900		VXX:*****=VXX:*****=1440:0900:*.*****		*****=*****=1440:0900:*.*****	✓	✓	✓
		1600x900		VXX:*****=VXX:*****=1600:0900:*.*****		*****=*****=1600:0900:*.*****	✓	✓	✓
		1600x1200		VXX:*****=VXX:*****=1600:1200:*.*****		*****=*****=1600:1200:*.*****	✓	✓	✓
		1680x1050		VXX:*****=VXX:*****=1680:1050:*.*****		*****=*****=1680:1050:*.*****	✓	✓	✓
		1920x1080		VXX:*****=VXX:*****=1920:1080:*.*****		*****=*****=1920:1080:*.*****	✓	✓	✓
		1920x1200		VXX:*****=VXX:*****=1920:1200:*.*****		*****=*****=1920:1200:*.*****	✓	✓	✓
		2048x1080		VXX:*****=VXX:*****=2048:1080:*.*****		*****=*****=2048:1080:*.*****	✓	✓	✓
	* PARAMETER4	Progressive		VXX:*****=VXX:*****=*****:p		*****=*****=*****:p	✓	✓	✓
		Interlace		VXX:*****=VXX:*****=*****:j		*****=*****=*****:j	✓	✓	✓
	* PARAMETERS5	60Hz		VXX:*****=VXX:*****=*****:*.6000		*****=*****=*****:*.6000	✓	✓	✓
		50Hz		VXX:*****=VXX:*****=*****:*.5000		*****=*****=*****:*.5000	✓	✓	✓
		48Hz		VXX:*****=VXX:*****=*****:*.4800		*****=*****=*****:*.4800	✓	✓	✓
		30Hz		VXX:*****=VXX:*****=*****:*.3000		*****=*****=*****:*.3000	✓	✓	✓
		25Hz		VXX:*****=VXX:*****=*****:*.2500		*****=*****=*****:*.2500	✓	✓	✓
		24Hz		VXX:*****=VXX:*****=*****:*.2400		*****=*****=*****:*.2400	✓	✓	✓
SLOT : DVI : EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER				QVX:*****=QVX:*****	*****=*****=*****:*.*****	✓	✓	✓
	* PARAMETER1, 2	DVI1				SLSS1=ESDS1=*****:*.*****	✓	✓	✓
		DVI2				SLSS1=ESDS2=*****:*.*****	✓	✓	✓
		DVI3				SLSS2=ESDS1=*****:*.*****	✓		
		DVI4				SLSS2=ESDS2=*****:*.*****	✓		
	* PARAMETER3	1024x768				*****=*****=1024:0768:*.*****	✓	✓	✓
		1280x720				*****=*****=1280:0720:*.*****	✓	✓	✓
		1280x800				*****=*****=1280:0800:*.*****	✓	✓	✓
		1280x1024				*****=*****=1280:1024:*.*****	✓	✓	✓
		1366x768				*****=*****=1366:0768:*.*****	✓	✓	✓

				CONTROL	QUERY		RQ35K2 SERIES	RZ34K2 SERIES	SRZ330KC SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K2 SRQ350KC	RZ34K2 SRZ340KC	SRZ330C	
SLOT : DisplayPort : SIGNAL LEVEL	* PARAMETER	30Hz				*****=*****=:3000	✓	✓	✓	
		25Hz				*****=*****=:2500	✓	✓	✓	
		24Hz				*****=*****=:2400	✓	✓	✓	
						*****=*****=:*****	✓	✓	✓	
	* PARAMETER1, 2	DisplayPort1		VXX:SLSS1=VXX:DPLI1=+*****	QVX:*****=QVX:*****	*****=*****=:*****	✓	✓	✓	
		DisplayPort2		VXX:SLSS1=VXX:DPLI2=+*****		SLSS1=DPLI1=+*****	✓	✓	✓	
		DisplayPort3		VXX:SLSS2=VXX:DPLI1=+*****		SLSS1=DPLI2=+*****	✓	✓	✓	
		DisplayPort4		VXX:SLSS2=VXX:DPLI2=+*****		SLSS2=DPLI1=+*****	✓	✓	✓	
	* PARAMETER3	0-1023		VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	✓	
		64-940		VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓	✓	
		AUTO		VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	✓	✓	
				VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=:*****	✓	✓	✓	
	* PARAMETER	DisplayPort1		VXX:SLSS1=VXX:DAGI1=+*****		SLSS1=DAGI1=+*****	✓	✓	✓	
		DisplayPort2		VXX:SLSS1=VXX:DAGI2=+*****		SLSS1=DAGI2=+*****	✓	✓	✓	
		DisplayPort3		VXX:SLSS2=VXX:DAGI1=+*****		SLSS2=DAGI1=+*****	✓	✓	✓	
		DisplayPort4		VXX:SLSS2=VXX:DAGI2=+*****		SLSS2=DAGI2=+*****	✓	✓	✓	
	* PARAMETER3	DISABLE		VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	✓	
		ENABLE		VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓	✓	
				VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=:*****	✓	✓	✓	
				VXX:SLSS1=VXX:DACI1=+*****		SLSS1=DACI1=+*****	✓	✓	✓	
	* PARAMETER1, 2	DisplayPort1		VXX:SLSS1=VXX:DACI2=+*****		SLSS1=DACI2=+*****	✓	✓	✓	
		DisplayPort2		VXX:SLSS2=VXX:DACI1=+*****		SLSS2=DACI1=+*****	✓	✓	✓	
		DisplayPort3		VXX:SLSS2=VXX:DACI2=+*****		SLSS2=DACI2=+*****	✓	✓	✓	
		DisplayPort4		VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	✓	
	* PARAMETER3	DISABLE		VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓	✓	
		ENABLE		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=:*****	✓	✓	✓	
				VXX:SLSS1=VXX:DESI1=+*****		SLSS1=DESI1=+*****	✓	✓	✓	
				VXX:SLSS2=VXX:DESI2=+*****		SLSS2=DESI2=+*****	✓	✓	✓	
	* PARAMETER3	4K/60p		VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	✓	
		4K/30p		VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓	✓	
		2K		VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	✓	✓	
		4K/60p/HDR		VXX:*****=VXX:*****=+00010		*****=*****=+00010	✓	✓	✓	
	* PARAMETER			VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=:*****	✓	✓	✓	
		DisplayPort1		VXX:SLSS1=VXX:EDMI8=+*****		SLSS1=EDMI8=+*****	✓	✓	✓	
		DisplayPort2		VXX:SLSS1=VXX:EDMI9=+*****		SLSS1=EDMI9=+*****	✓	✓	✓	
		DisplayPort3		VXX:SLSS2=VXX:EDMI8=+*****		SLSS2=EDMI8=+*****	✓	✓	✓	
	* PARAMETER3	DisplayPort4		VXX:SLSS2=VXX:EDMI9=+*****		SLSS2=EDMI9=+*****	✓	✓	✓	
		DEFAULT		VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	✓	
		USER		VXX:*****=VXX:*****=+00010		*****=*****=+00010	✓	✓	✓	
				VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=:*****	✓	✓	✓	
	SLOT : DisplayPort : EDID RESOLUTION	* PARAMETER			VXX:*****=VXX:*****=*****:*	QVX:*****=QVX:*****	*****=*****=:*****	✓	✓	✓
			DisplayPort1		VXX:SLSS1=VXX:EDRS8=*****		SLSS1=EDRS8=*****	✓	✓	✓
			DisplayPort2		VXX:SLSS1=VXX:EDRS9=*****		SLSS1=EDRS9=*****	✓	✓	✓
DisplayPort3				VXX:SLSS2=VXX:EDRS8=*****		SLSS2=EDRS8=*****	✓	✓	✓	
* PARAMETER1, 2		DisplayPort4		VXX:SLSS2=VXX:EDRS9=*****		SLSS2=EDRS9=*****	✓	✓	✓	
		1024x768		VXX:*****=VXX:*****=1024:0768:*		*****=*****=1024:0768:*	✓	✓	✓	
		1280x720		VXX:*****=VXX:*****=1280:0720:*		*****=*****=1280:0720:*	✓	✓	✓	
		1280x800		VXX:*****=VXX:*****=1280:0800:*		*****=*****=1280:0800:*	✓	✓	✓	
		1400x1050		VXX:*****=VXX:*****=1400:1050:*		*****=*****=1400:1050:*	✓	✓	✓	
		1600x900		VXX:*****=VXX:*****=1600:0900:*		*****=*****=1600:0900:*	✓	✓	✓	
		1600x1200		VXX:*****=VXX:*****=1600:1200:*		*****=*****=1600:1200:*	✓	✓	✓	
		1920x1080		VXX:*****=VXX:*****=1920:1080:*		*****=*****=1920:1080:*	✓	✓	✓	
		1920x1200		VXX:*****=VXX:*****=1920:1200:*		*****=*****=1920:1200:*	✓	✓	✓	
		2048x1080		VXX:*****=VXX:*****=2048:1080:*		*****=*****=2048:1080:*	✓	✓	✓	
		2560x1600		VXX:*****=VXX:*****=2560:1600:*		*****=*****=2560:1600:*	✓	✓	✓	
		3840x2400		VXX:*****=VXX:*****=3840:2400:*		*****=*****=3840:2400:*	✓	✓	✓	
* PARAMETER3		Progressive		VXX:*****=VXX:*****=*****:p		*****=*****=*****:p	✓	✓	✓	
		Interlace		VXX:*****=VXX:*****=*****:i		*****=*****=*****:i	✓	✓	✓	
				VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=:*****	✓	✓	✓	
				VXX:SLSS1=VXX:EDVI8=+*****		SLSS1=EDVI8=+*****	✓	✓	✓	
* PARAMETER1, 2		DisplayPort2		VXX:SLSS1=VXX:EDVI9=+*****		SLSS1=EDVI9=+*****	✓	✓	✓	
		DisplayPort3		VXX:SLSS2=VXX:EDVI8=+*****		SLSS2=EDVI8=+*****	✓	✓	✓	
		DisplayPort4		VXX:SLSS2=VXX:EDVI9=+*****		SLSS2=EDVI9=+*****	✓	✓	✓	
		60Hz		VXX:*****=VXX:*****=+06000		*****=*****=+06000	✓	✓	✓	
		50Hz		VXX:*****=VXX:*****=+05000		*****=*****=+05000	✓	✓	✓	
		48Hz		VXX:*****=VXX:*****=+04800		*****=*****=+04800	✓	✓	✓	
		30Hz		VXX:*****=VXX:*****=+03000		*****=*****=+03000	✓	✓	✓	
		25Hz		VXX:*****=VXX:*****=+02500		*****=*****=+02500	✓	✓	✓	
SLOT : DisplayPort : EDID RESOLUTION / VERTICAL SCAN FREQUENCY		* PARAMETER	24Hz		VXX:*****=VXX:*****=+02400		*****=*****=+02400	✓	✓	✓
					VXX:*****=VXX:*****=*****:*,*****	QVX:*****=QVX:*****	*****=*****=:*****	✓	✓	✓
			DisplayPort1		VXX:SLSS1=VXX:EDPS1=*****		SLSS1=EDPS1=*****	✓	✓	✓
			DisplayPort2		VXX:SLSS1=VXX:EDPS2=*****		SLSS1=EDPS2=*****	✓	✓	✓
	* PARAMETER1, 2	DisplayPort3		VXX:SLSS2=VXX:EDPS1=*****		SLSS2=EDPS1=*****	✓	✓	✓	
		DisplayPort4		VXX:SLSS2=VXX:EDPS2=*****		SLSS2=EDPS2=*****	✓	✓	✓	
		1024x768		VXX:*****=VXX:*****=1024:0768:*		*****=*****=1024:0768:*	✓	✓	✓	
		1280x720		VXX:*****=VXX:*****=1280:0720:*		*****=*****=1280:0720:*	✓	✓	✓	
	* PARAMETER3	1280x800		VXX:*****=VXX:*****=1280:0800:*		*****=*****=1280:0800:*	✓	✓	✓	
		1400x1050		VXX:*****=VXX:*****=1400:1050:*		*****=*****=1400:1050:*	✓	✓	✓	
		1600x900		VXX:*****=VXX:*****=1600:0900:*		*****=*****=1600:0900:*	✓	✓	✓	
		1600x1200		VXX:*****=VXX:*****=1600:1200:*		*****=*****=1600:1200:*	✓	✓	✓	
		1920x1080		VXX:*****=VXX:*****=1920:1080:*		*****=*****=1920:1080:*	✓	✓	✓	
		1920x1200		VXX:*****=VXX:*****=1920:1200:*		*****=*****=1920:1200:*	✓	✓	✓	
		2048x1080		VXX:*****=VXX:*****=2048:1080:*		*****=*****=2048:1080:*	✓	✓	✓	
		2560x1600		VXX:*****=VXX:*****=2560:1600:*		*****=*****=2560:1600:*	✓	✓	✓	
		3840x2400		VXX:*****=VXX:*****=3840:2400:*		*****=*****=3840:2400:*	✓	✓	✓	
		Progressive		VXX:*****=VXX:*****=*****:p		*****=*****=*****:p	✓	✓	✓	
		Interlace		VXX:*****=VXX:*****=*****:i		*****=*****=*****:i	✓	✓	✓	
		* PARAMETER4			VXX:*****=VXX:*****=*****:*,*****		*****=*****=*****:*,*****	✓	✓	✓
	60Hz			VXX:*****=VXX:*****=*****:*,*****		*****=*****=*****:*,*****	✓	✓	✓	
	50Hz			VXX:*****=VXX:*****=*****:*,*****		*****=*****=*****:*,*****	✓	✓	✓	
	48Hz			VXX:*****=VXX:*****=*****:*,*****		*****=*****=*****:*,*****	✓	✓	✓	
	30Hz			VXX:*****=VXX:*****=*****:*,*****		*****=*****=*****:*,*****	✓	✓	✓	
25Hz			VXX:*****=VXX:*****=*****:*,*****		*****=*****=*****:*,*****	✓	✓	✓		
24Hz			VXX:*****=VXX:*****=*****:*,*****		*****=*****=*****:*,*****	✓	✓	✓		
			VXX:*****=VXX:*****=*****:*,*****	QVX:*****=QVX:*****	*****=*****=:*****	✓	✓	✓		
SLOT : DisplayPort : EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER				QVX:*****=QVX:*****	*****=*****=:*****	✓	✓	✓	
		DisplayPort1				SLSS1=ESPS1=*****	✓	✓	✓	
		DisplayPort2				SLSS1=ESPS2=*****	✓	✓	✓	
		DisplayPort3				SLSS2=ESPS1=*****	✓	✓	✓	
	* PARAMETER1, 2	DisplayPort4				SLSS2=ESPS2=*****	✓	✓	✓	
		1024x768				*****=*****=1024:0768:*	✓	✓	✓	
		1280x720				*****=*****=1280:0720:*	✓	✓	✓	
		1280x800				*****=*****=1280:0800:*	✓	✓	✓	
		1400x1050				*****=*****=1400:1050:*	✓	✓	✓	
		1600x900				*****=*****=1600:0900:*	✓	✓	✓	
		1600x1200				*****=*****=1600:1200:*	✓	✓	✓	
		1920x1080				*****=*****=1920:1080:*	✓	✓	✓	
		1920x1200				*****=*****=1920:1200:*	✓	✓	✓	
		2048x1080				*****=*****=2048:1080:*	✓	✓	✓	
		2560x1600				*****=*****=2560:1600:*	✓	✓	✓	
		3840x2400				*****=*****=3840:2400:*	✓	✓	✓	
	* PARAMETER3	Progressive				*****=*****=*****:p	✓	✓	✓	
		Interlace				*****=*****=*****:i	✓	✓	✓	
		60Hz				*****=*****=*****:*,*****	✓	✓	✓	
		50Hz				*****=*****=*****:*,*****	✓	✓	✓	
	* PARAMETERS5	48Hz				*****=*****=*****:*,*****	✓	✓	✓	
		30Hz				*****=*****=*****:*,*****	✓	✓	✓	
		25Hz				*****=*****=*****:*,*****	✓	✓	✓	
		24Hz				*****=*****=*****:*,*****	✓	✓		

				CONTROL	QUERY				RQ35K2 SERIES	RZ34K2 SERIES	SRZ330KC SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK		RQ35K2 SRO350KC	RZ34K2 SRZ340KC	SRZ330C	
		* PARAMETER1, 2	12G SDI OPT2	VXX:SLSS1=VXX:OGMI2=*****		SLSS1=OGMI2=+*****		✓	✓	✓	
			12G SDI OPT1	VXX:SLSS2=VXX:OGMI1=*****		SLSS2=OGMI1=+*****		✓			
		* PARAMETER3	12G SDI OPT2	VXX:SLSS2=VXX:OGMI2=*****		SLSS2=OGMI2=+*****		✓			
			AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000		✓	✓	✓	
			TYPE1 / LEVEL A	VXX:*****=VXX:*****=+00001		*****=*****=+00001		✓	✓	✓	
			TYPE2 / LEVEL B	VXX:*****=VXX:*****=+00002		*****=*****=+00002		✓	✓	✓	
		SLOT : 12G SDI OPT : SYSTEM SELECTOR	* PARAMETER		VXX:*****=VXX:*****=*****	QVX:*****=QVX:*****	*****=*****=+*****		✓	✓	✓
			* PARAMETER1, 2	12G SDI OPT1	VXX:SLSS1=VXX:OSYI1=*****		SLSS1=OSYI1=+*****		✓	✓	✓
		12G SDI OPT2		VXX:SLSS1=VXX:OSYI2=*****		SLSS1=OSYI2=+*****		✓	✓	✓	
		12G SDI OPT1		VXX:SLSS2=VXX:OSYI1=*****		SLSS2=OSYI1=+*****		✓			
	12G SDI OPT2	VXX:SLSS2=VXX:OSYI2=*****			SLSS2=OSYI2=+*****		✓				
	* PARAMETER3	AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000		✓	✓	✓		
		RGB	VXX:*****=VXX:*****=+00001		*****=*****=+00001		✓	✓	✓		
		YPbPr 4:4:4	VXX:*****=VXX:*****=+00002		*****=*****=+00002		✓	✓	✓		
		YPbPr 4:2:2	VXX:*****=VXX:*****=+00003		*****=*****=+00003		✓	✓	✓		
	SLOT : 12G SDI OPT : BIT DEPTH	* PARAMETER		VXX:*****=VXX:*****=*****	QVX:*****=QVX:*****	*****=*****=+*****		✓	✓	✓	
		* PARAMETER1, 2	12G SDI OPT1	VXX:SLSS1=VXX:OBTI1=*****		SLSS1=OBTI1=+*****		✓	✓	✓	
	12G SDI OPT2		VXX:SLSS1=VXX:OBTI2=*****		SLSS1=OBTI2=+*****		✓	✓	✓		
	12G SDI OPT1		VXX:SLSS2=VXX:OBTI1=*****		SLSS2=OBTI1=+*****		✓				
	12G SDI OPT2		VXX:SLSS2=VXX:OBTI2=*****		SLSS2=OBTI2=+*****		✓				
	* PARAMETER3	AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000		✓	✓	✓		
		12-bit	VXX:*****=VXX:*****=+00001		*****=*****=+00001		✓	✓	✓		
		10-bit	VXX:*****=VXX:*****=+00002		*****=*****=+00002		✓	✓	✓		
			VXX:*****=VXX:*****=*****	QVX:*****=QVX:*****	*****=*****=+*****		✓	✓	✓		
		SLOT : 12G SDI OPT : SIGNAL LEVEL	* PARAMETER		VXX:*****=VXX:*****=*****	QVX:*****=QVX:*****	*****=*****=+*****		✓	✓	✓
			* PARAMETER1, 2	12G SDI OPT1	VXX:SLSS1=VXX:OSLI1=*****		SLSS1=OSLI1=+*****		✓	✓	✓
		12G SDI OPT2		VXX:SLSS1=VXX:OSLI2=*****		SLSS1=OSLI2=+*****		✓	✓	✓	
		12G SDI OPT1		VXX:SLSS2=VXX:OSLI1=*****		SLSS2=OSLI1=+*****		✓			
		12G SDI OPT2		VXX:SLSS2=VXX:OSLI2=*****		SLSS2=OSLI2=+*****		✓			
		* PARAMETER3	64-940	VXX:*****=VXX:*****=+00000		*****=*****=+00000		✓	✓	✓	
			4-1019	VXX:*****=VXX:*****=+00001		*****=*****=+00001		✓	✓	✓	
		SLOT : 12G SDI OPT : SDI OPT OUT	* PARAMETER		VXX:OOMS1=*:*:*****	QVX:OOMS1=*:*:*****	OOMS1=*:*:*****		✓	✓	✓
			* PARAMETER1	SLOT1	VXX:OOMS1=1:*:*****		OOMS1=1:*:*****		✓	✓	✓
				SLOT2	VXX:OOMS1=2:*:*****		OOMS1=2:*:*****		✓		
	SFP2			VXX:OOMS1=*:2:*****		OOMS1=*:2:*****		✓	✓	✓	
	* PARAMETER3	DISABLE	VXX:OOMS1=*:*:00000		OOMS1=*:*:00000		✓	✓	✓		
	ENABLE	VXX:OOMS1=*:*:00001		OOMS1=*:*:00001		✓	✓	✓			
	MULTI PROJECTOR SYNC - MODE	OFF		VXX:MPSI1=+00000	QVX:MPSI1	MPSI1=+00000		✓	✓	✓	
		MAIN		VXX:MPSI1=+00001		MPSI1=+00001		✓	✓	✓	
	SUB		VXX:MPSI1=+00002		MPSI1=+00002		✓	✓	✓		
	MULTI PROJECTOR SYNC - LINK STATUS	NO LINK			QVX:MPSI2	MPSI2=+00000		✓	✓	✓	
		LINKED				MPSI2=+00001		✓	✓	✓	
	MULTI PROJECTOR SYNC - CONTRAST STATUS	OFF			QVX:DCSI1	DCSI1=+00000		✓	✓	✓	
		DYNAMIC CONTRAST				DCSI1=+00001		✓	✓	✓	
		DYNAMIC CONTRAST NX				DCSI1=+00002		✓	✓	✓	
								✓	✓	✓	
	FRAME SYNC SETTING(MULTI PROJECTOR SYNC) - CONTRAST SYNC.	OFF		VXX:CSYI1=+00000	QVX:CSYI1	CSYI1=+00000		✓	✓	✓	
		ON		VXX:CSYI1=+00001		CSYI1=+00001		✓	✓	✓	
	MULTI PROJECTOR SYNC - SHUTTER SYNC.	OFF		VXX:SSYI1=+00000	QVX:SSYI1	SSYI1=+00000		✓	✓	✓	
		ON		VXX:SSYI1=+00001		SSYI1=+00001		✓	✓	✓	
	INPUT GUIDE	OFF		OID:0	QDI	0		✓	✓	✓	
		ON (SIMPLE)		OID:1		1		✓	✓	✓	
	OSD POSITION	UPPER LEFT		ODP:1	QDP	1		✓	✓	✓	
		CETRE LEFT		ODP:2		2		✓	✓	✓	
		LOWER LEFT		ODP:3		3		✓	✓	✓	
		TOP CENTER		ODP:4		4		✓	✓	✓	
		CENTER		ODP:5		5		✓	✓	✓	
		LOEER CENTER		ODP:6		6		✓	✓	✓	
		UPPER RIGHT		ODP:7		7		✓	✓	✓	
		CENTER RIGHT		ODP:8		8		✓	✓	✓	
		LOWER RIGHT		ODP:9		9		✓	✓	✓	
		OSD ROTATION	OFF		VXX:OSRI1=+00000	QVX:OSRI1	OSRI1=+00000		✓	✓	✓
	CLOCKWISE			VXX:OSRI1=+00001		OSRI1=+00001		✓	✓	✓	
	COUNTER CLOCKWISE			VXX:OSRI1=+00002		OSRI1=+00002		✓	✓	✓	
	OSD MEMORY	OFF		VXX:OMYI0=+00000	QVX:OMYI0	OMYI0=+00000		✓	✓	✓	
		ON		VXX:OMYI0=+00001		OMYI0=+00001		✓	✓	✓	
	ON SCREEN	OFF		OOS:0	QOS	0		✓	✓	✓	
		ON		OOS:1		1		✓	✓	✓	
	WARNING MESSAGE	OFF		VXX:WMDI0=+00000	QVX:WMDI0	WMDI0=+00000		✓	✓	✓	
		ON		VXX:WMDI0=+00001		WMDI0=+00001		✓	✓	✓	
	OSD DESIGN	1(YELLOW)		MOD:0	QOD	0		✓	✓	✓	
		2(BLUE)		MOD:1		1		✓	✓	✓	
		3(WHITE)		MOD:2		2		✓	✓	✓	
		4(GREEN)		MOD:3		3		✓	✓	✓	
		5(Peach)		MOD:4		4		✓	✓	✓	
		6(BROWN)		MOD:5		5		✓	✓	✓	
	MENU MODE	NORMAL		VXX:MMDI1=+00000	QVX:MMDI1	MMDI1=+00000		✓	✓	✓	
		SIMPLE		VXX:MMDI1=+00001		MMDI1=+00001		✓	✓	✓	
	SCREEN SETTING	16:10		VSF:0	QSF	0		✓	✓	✓	
		16:9		VSF:1		1		✓	✓	✓	
		4:3		VSF:2		2		✓	✓	✓	
	SCREEN POSITION-VERTICAL	min.		VXX:VSPI0=-00120	QVX:VSPI0	VSPI0=-00120	-120	-60	-60		
	max.		VXX:VSPI0=+00120		VSPI0=+00120	120	60	60			
	SCREEN POSITION-HORIZONTAL	min.		VXX:HSPI0=-00320	QVX:HSPI0	HSPI0=-00320	-320	-160	-160		
		max.		VXX:HSPI0=+00320		HSPI0=+00320	320	160	160		
	SCREEN MARKER	OFF		VXX:SSMI1=+00000	QVX:SSMI1	SSMI1=+00000		✓	✓	✓	
		ON		VXX:SSMI1=+00001		SSMI1=+00001		✓	✓	✓	
	SCREEN MARKER - UPPER	min.		VXX:SCMI1=+00000	QVX:SCMI1	SCMI1=+00000	0	0	0		
		max.		VXX:SCMI1=+02399		SCMI1=+02399	2399	1199	1199		
	SCREEN MARKER - LOWER	min.		VXX:SCMI2=+00000	QVX:SCMI2	SCMI2=+00000	0	0	0		
		max.		VXX:SCMI2=+02399		SCMI2=+02399	2399	1199	1199		
	SCREEN MARKER - LEFT	min.		VXX:SCMI3=+00000	QVX:SCMI3	SCMI3=+00000	0	0	0		
		max.		VXX:SCMI3=+03839		SCMI3=+03839	3839	1919	1919		
	SCREEN MARKER - RIGHT	min.		VXX:SCMI4=+00000	QVX:SCMI4	SCMI4=+00000	0	0	0		
		max.		VXX:SCMI4=+03839		SCMI4=+03839	3839	1919	1919		
	STARTUP LOGO	OFF		MLO:0	QLO	0		✓	✓	✓	
		USER LOGO		MLO:1		1		✓	✓	✓	
		DEFAULT LOGO		MLO:2		2		✓	✓	✓	
	UNIFORMITY-FLEXIBLE CORRECTION *	OFF		VXX:UFMI1=+00000	QVX:UFMI1	UFMI1=+00000		✓	✓	✓	
		ON(PRE)		VXX:UFMI1=+00011		UFMI1=+00011		✓	✓	✓	
ON(POST)			VXX:UFMI1=+00021		*		✓	✓	✓		
UNIFORMITY-INITILIZE	EXECUTE		VXX:UFMI2=+00001				✓	✓	✓		
UNIFORMITY-MODE	CHROMA ONLY		VXX:UFMI3=+00001	QVX:UFMI3	UFMI3=+00001		✓	✓	✓		
	LUMINACE/CHROMA		VXX:UFMI3=+00011		UFMI3=+00011		✓	✓	✓		
UNIFORMITY-WHITE/RED/GREEN/RED	* PARAMETER		E\$W:*,****,****	E\$R:*	*,****,****		✓	✓	✓		
	* PARAMETER 1	WHITE	E\$W:W,****,****	E\$R:W	*,****,****		✓	✓	✓		
		RED	E\$W:R,****,****	E\$R:R	*,****,****		✓	✓	✓		
		GREEN	E\$W:G,****,****	E\$R:G	*,****,****		✓	✓	✓		
		BLUE	E\$W:B,****,****	E\$R:B	*,****,****		✓	✓	✓		
	* PARAMETER 2	VERTICAL(-127)	E\$W:*, -127,****		*, -127,****		✓	✓	✓		
		VERTICAL(+127)	E\$W:*, +127,****		*, +127,****		✓	✓	✓		
	* PARAMETER 3	HORIZONTAL(-127)	E\$W:*, ****, -127		*, ****, -127		✓	✓	✓		
		HOROZONTAL(+127)	E\$W:*, ****, +127		*, ****, +127		✓	✓	✓		
		L1(ON)			1*, ****, ****		✓	✓	✓		
L2(OFF)				*0,****,****		✓	✓	✓			
SHUTTER SETTING-FADE IN	0.0s(OFF)		VXX:SEFS1=0.0	QVX:SEFS1	SEFS1=0.0		✓	✓	✓		
	0.5s		VXX:SEFS1=0.5		SEFS1=0.5		✓	✓	✓		
	1.0s		VXX:SEFS1=1.0		SEFS1=1.0		✓	✓	✓		
	1.5s		VXX:SEFS1=1.5		SEFS1=1.5		✓	✓	✓		
	2.0s		VXX:SEFS1=2.0		SEFS1=2.0		✓	✓	✓		
	2.5s		VXX:SEFS1=2.5		SEFS1=2.5		✓	✓	✓		
	3.0s		VXX:SEFS1=3.0		SEFS1=3.0		✓	✓	✓		
	3.5s		VXX:SEFS1=3.5		SEFS1=3.5		✓	✓	✓		
	4.0s		VXX:SEFS1=4.0		SEFS1=4.0		✓	✓	✓		
	5.0s		VXX:SEFS1=5.0		SEFS1=5.0		✓	✓	✓		
	7.0s		VXX:SEFS1=7.0		SEFS1=7.0		✓	✓	✓		
	10.0s		VXX:SEFS1=10.0		SEFS1=10.0		✓	✓	✓		
	SHUTTER SETTING-FADE OUT	0.0s(OFF)		VXX:SEFS2=0.0	QVX:SEFS2	SEFS2=0.0		✓	✓	✓	
0.5s			VXX:SEFS2=0.5		SEFS2=0.5		✓				

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ35K2 SERIES	RZ34K2 SERIES	Z330KC SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K2 SRQ350KC	RZ34K2 SRZ340KC	SRZ330C
		4.0s		VXX:SEFS2=4.0		SEFS2=4.0	✓	✓	✓
		5.0s		VXX:SEFS2=5.0		SEFS2=5.0	✓	✓	✓
		7.0s		VXX:SEFS2=7.0		SEFS2=7.0	✓	✓	✓
		10.0s		VXX:SEFS2=10.0		SEFS2=10.0	✓	✓	✓
	SHUTTER SETTING -MECHANICAL SHUTTER	DISABLE		VXX:SEFI5=+00000	QVX:SEFI5	SEFS5=+00000	✓	✓	✓
		ENABLE		VXX:SEFI5=+00001		SEFS5=+00001	✓	✓	✓
	SHUTTER SETTING-STARTUP	OPEN		VXX:SEFI3=+00000	QVX:SEFI3	SEFI3=+00000	✓	✓	✓
		CLOSE		VXX:SEFI3=+00001		SEFI3=+00001	✓	✓	✓
	SHUTTER SETTING-SHUT OFF	OPEN		VXX:SEFI4=+00000	QVX:SEFI4	SEFI4=+00000	✓	✓	✓
		CLOSE		VXX:SEFI4=+00001		SEFI4=+00001	✓	✓	✓
		KEEP CURRENT STATE		VXX:SEFI4=+00002		SEFI4=+00002	✓	✓	✓
	BACK COLOR	BLUE		OBC:0	QBC	0	✓	✓	✓
		BLACK		OBC:1		1	✓	✓	✓
		USER LOGO		OBC:2		2	✓	✓	✓
		DEFAULT LOGO		OBC:3		3	✓	✓	✓
	WAVEFORM MONITOR	OFF		OWM:0	QWM	0	✓	✓	✓
		LUMINANCE		OWM:5		5	✓	✓	✓
		RED		OWM:6		6	✓	✓	✓
		GREEN		OWM:7		7	✓	✓	✓
		BLUE		OWM:8		8	✓	✓	✓
	WAVEFORM MONITOR-LINE ADJ.	0		VXX:WMLI0=+00000	QVX:WMLI0	WMLI0=+00000	✓	✓	✓
		+2159		VXX:WMLI0=+02159		WMLI0=+02159	✓	✓	✓
	AC VOLTAGE				QVX:VMOI2	VMOI2=+00000	✓	✓	✓
	CUT OFF-RED	OFF		VXX:CUTI1=+00000	QVX:CUTI1	CUTI1=+00000	✓	✓	✓
		ON		VXX:CUTI1=+00001		CUTI1=+00001	✓	✓	✓
	CUT OFF-GREEN	OFF		VXX:CUTI2=+00000	QVX:CUTI2	CUTI2=+00000	✓	✓	✓
		ON		VXX:CUTI2=+00001		CUTI2=+00001	✓	✓	✓
	CUT OFF-BLUE	OFF		VXX:CUTI3=+00000	QVX:CUTI3	CUTI3=+00000	✓	✓	✓
		ON		VXX:CUTI3=+00001		CUTI3=+00001	✓	✓	✓
	PROJECTOR ID	0(ALL)		RIS:00			✓	✓	✓
		64		RIS:64			✓	✓	✓
	ID ALL	OFF		RVS:0	QVY	0	✓	✓	✓
		ON		RVS:1		1	✓	✓	✓
	PROJECTION METHOD INSTALLATION	FRONT/DESK		OIL:0	QSP	0	✓	✓	✓
		REAR/DESK		OIL:1		1	✓	✓	✓
		FRONT/CEILING		OIL:2		2	✓	✓	✓
		REAR/CEILING		OIL:3		3	✓	✓	✓
		FRONT/AUTO		OIL:4		4	✓	✓	✓
		REAR/AUTO		OIL:5		5	✓	✓	✓
	AUTO COOLING CONDITION-STATUS	FLOOR			QVX:ADRI1	ADRI1=+00000	✓	✓	✓
		CEILING				ADRI1=+00001	✓	✓	✓
		VERTICAL UP				ADRI1=+00002	✓	✓	✓
		VERTICAL DOWN				ADRI1=+00003	✓	✓	✓
		PORTRAIT				ADRI1=+00004	✓	✓	✓
	OPERATING MODE	NORMAL		VXX:OPEI1=+00000	QVX:OPEI1	OPEI1=+00000	✓	✓	✓
		ECO		VXX:OPEI1=+00001		OPEI1=+00001	✓	✓	✓
		QUIET1(QUIET)		VXX:OPEI1=+00021		OPEI1=+00021	✓	✓	✓
		USER1(USER)		VXX:OPEI1=+00101		OPEI1=+00101	✓	✓	✓
		USER2		VXX:OPEI1=+00102		OPEI1=+00102	✓	✓	✓
	LIGHT OUTPUT	min.		VXX:LOPI2=+00050	QVX:LOPI2	LOPI2=+00050	8%	8%	8%
		max.		VXX:LOPI2=+01000		LOPI2=+01000	100%	100%	100%
	MAX LIGHT OUTPUT	min.		VXX:LOPI3=+00050	QVX:LOPI3	LOPI3=+00050	8%	8%	8%
		max.		VXX:LOPI3=+01000		LOPI3=+01000	100%	100%	100%
	BRIGHTNESS CONTROL-SETUP-CONSTANT MODE	OFF		VXX:BCMI0=+00000	QVX:BCMI0	BCMI0=+00000	✓	✓	✓
		AUTO		VXX:BCMI0=+00001		BCMI0=+00001	✓	✓	✓
		PC		VXX:BCMI0=+00002		BCMI0=+00002	✓	✓	✓
	BRIGHTNESS CONTROL-SETUP-LINK	OFF		VXX:BCLI0=+00000	QVX:BCLI0	BCLI0=+00000	✓	✓	✓
		GROUP A		VXX:BCLI0=+00001		BCLI0=+00001	✓	✓	✓
		GROUP B		VXX:BCLI0=+00002		BCLI0=+00002	✓	✓	✓
		GROUP C		VXX:BCLI0=+00003		BCLI0=+00003	✓	✓	✓
		GROUP D		VXX:BCLI0=+00004		BCLI0=+00004	✓	✓	✓
	BRIGHTNESS CONTROL-SETUP APPLY SCHEDULE	APPLY		VXX:BCSI0=+00001			✓	✓	✓
		OFF		VXX:SCHI0=+00000	QVX:SCHI0	SCHI0=+00000	✓	✓	✓
		ON		VXX:SCHI0=+00001		SCHI0=+00001	✓	✓	✓
	SCHEDULE-PROGRAM ASSIGN	OFF		VXX:SPGI*=+00000	QVX:SPGI*	SPGI*=+00000	✓	✓	✓
		PROGRAM1		VXX:SPGI*=+00001		SPGI*=+00001	✓	✓	✓
		PROGRAM2		VXX:SPGI*=+00002		SPGI*=+00002	✓	✓	✓
		PROGRAM3		VXX:SPGI*=+00003		SPGI*=+00003	✓	✓	✓
		PROGRAM4		VXX:SPGI*=+00004		SPGI*=+00004	✓	✓	✓
		PROGRAM5		VXX:SPGI*=+00005		SPGI*=+00005	✓	✓	✓
		PROGRAM6		VXX:SPGI*=+00006		SPGI*=+00006	✓	✓	✓
		PROGRAM7		VXX:SPGI*=+00007		SPGI*=+00007	✓	✓	✓
		* PARAMETER	SUN	VXX:SPGI0=+0000*	QVX:SPGI0	SPGI0=+0000*	✓	✓	✓
			MON	VXX:SPGI1=+0000*	QVX:SPGI1	SPGI1=+0000*	✓	✓	✓
			TUE	VXX:SPGI2=+0000*	QVX:SPGI2	SPGI2=+0000*	✓	✓	✓
			WED	VXX:SPGI3=+0000*	QVX:SPGI3	SPGI3=+0000*	✓	✓	✓
			THU	VXX:SPGI4=+0000*	QVX:SPGI4	SPGI4=+0000*	✓	✓	✓
			FRI	VXX:SPGI5=+0000*	QVX:SPGI5	SPGI5=+0000*	✓	✓	✓
			SAT	VXX:SPGI6=+0000*	QVX:SPGI6	SPGI6=+0000*	✓	✓	✓
	SCHEDULE-COMMAND SETTING	COMMAND Del		VXX:SCCS*=**00****	QVX:SCCS*=**	SCCS*=**00****	✓	✓	✓
		STANDBY		VXX:SCCS*=**10****		SCCS*=**10****	✓	✓	✓
		POWER ON		VXX:SCCS*=**11****		SCCS*=**11****	✓	✓	✓
		SHUTTER OPEN		VXX:SCCS*=**20****		SCCS*=**20****	✓	✓	✓
		SHUTTER CLOSE		VXX:SCCS*=**21****		SCCS*=**21****	✓	✓	✓
		DVI-D INPUT		VXX:SCCS*=**51****		SCCS*=**51****	✓	✓	✓
		SDI1 INPUT		VXX:SCCS*=**52****		SCCS*=**52****	✓	✓	✓
		HDMI1 INPUT		VXX:SCCS*=**53****		SCCS*=**53****	✓	✓	✓
		SLOT1-1 INPUT		VXX:SCCS*=**68****		SCCS*=**68****	✓	✓	✓
		SLOT1-2 INPUT		VXX:SCCS*=**69****		SCCS*=**69****	✓	✓	✓
		SLOT2-3 INPUT		VXX:SCCS*=**6A****		SCCS*=**6A****	✓	✓	✓
		SLOT2-4 INPUT		VXX:SCCS*=**6B****		SCCS*=**6B****	✓	✓	✓
		SLOT1-3 INPUT		VXX:SCCS*=**6C****		SCCS*=**6C****	✓	✓	✓
		SLOT1-4 INPUT		VXX:SCCS*=**6D****		SCCS*=**6D****	✓	✓	✓
		SLOT2-1 INPUT		VXX:SCCS*=**6E****		SCCS*=**6E****	✓	✓	✓
		SLOT2-2 INPUT		VXX:SCCS*=**6F****		SCCS*=**6F****	✓	✓	✓
		NORMAL		VXX:SCCS*=**70****		SCCS*=**70****	✓	✓	✓
		ECO		VXX:SCCS*=**71****		SCCS*=**71****	✓	✓	✓
		USER1(USER)		VXX:SCCS*=**75****		SCCS*=**75****	✓	✓	✓
		USER2		VXX:SCCS*=**76****		SCCS*=**76****	✓	✓	✓
		USER3		VXX:SCCS*=**77****		SCCS*=**77****	✓	✓	✓
		SILENT1(QUIET1/QUIET)		VXX:SCCS*=**7A****		SCCS*=**7A****	✓	✓	✓
		DIGITAL LINK		VXX:SCCS*=**B0****		SCCS*=**B0****	✓	✓	✓
		INPUT 1		VXX:SCCS*=**B1****		SCCS*=**B1****	✓	✓	✓
		INPUT 2		VXX:SCCS*=**B2****		SCCS*=**B2****	✓	✓	✓
		INPUT 3		VXX:SCCS*=**B3****		SCCS*=**B3****	✓	✓	✓
		INPUT 4		VXX:SCCS*=**B4****		SCCS*=**B4****	✓	✓	✓
		INPUT 5		VXX:SCCS*=**B5****		SCCS*=**B5****	✓	✓	✓
		INPUT 6		VXX:SCCS*=**B6****		SCCS*=**B6****	✓	✓	✓
		INPUT 7		VXX:SCCS*=**B7****		SCCS*=**B7****	✓	✓	✓
		INPUT 8		VXX:SCCS*=**B8****		SCCS*=**B8****	✓	✓	✓
		INPUT 9		VXX:SCCS*=**B9****		SCCS*=**B9****	✓	✓	✓
		INPUT 10		VXX:SCCS*=**BA****		SCCS*=**BA****	✓	✓	✓
		* PARAMETER1	PROGRAM1	VXX:SCCS1=*****	QVX:SCCS1=**	SCCS1=*****	✓	✓	✓
			PROGRAM2	VXX:SCCS2=*****	QVX:SCCS2=**	SCCS2=*****	✓	✓	✓
			PROGRAM3	VXX:SCCS3=*****	QVX:SCCS3=**	SCCS3=*****	✓	✓	✓
			PROGRAM4	VXX:SCCS4=*****	QVX:SCCS4=**	SCCS4=*****	✓	✓	✓
			PROGRAM5	VXX:SCCS5=*****	QVX:SCCS5=**	SCCS5=*****	✓	✓	✓
			PROGRAM6	VXX:SCCS6=*****	QVX:SCCS6=**	SCCS6=*****	✓	✓	✓
			PROGRAM7	VXX:SCCS7=*****	QVX:SCCS7=**	SCCS7=*****	✓	✓	✓
		* PARAMETER2	COMMAND 1	VXX:SCCS*=01*****	QVX:SCCS*=01	SCCS*=01*****	✓	✓	✓
			COMMAND 16	VXX:SCCS*=16*****	QVX:SCCS*=16	SCCS*=16*****	✓	✓	✓
		* PARAMETER3	00:00	VXX:SCCS*=****0000		SCCS*=****0000	✓	✓	✓
			23:59	VXX:SCCS*=****2359		SCCS*=****2359	✓	✓	✓
	STARTUP INPUT SELECT	DVI-D		VXX:SISS1=DVI	QVX:SISS1	SISS1=DVI	✓	✓	✓
		HDMI1		VXX:SISS1=HD1		SISS1=HD1	✓	✓	✓
		DIGITAL LINK		VXX:SISS1=DL1		SISS1=DL1	✓	✓	✓
		SDI1		VXX:SISS1=SD1		SISS1=SD1	✓	✓	✓
		SLOT1 : SDI1		VXX:SISS1=AU1 , SD1		SISS1=AU1 , SD1	✓	✓	✓
		SLOT1 : SDI2		VXX:SISS1=AU1 , SD2		SISS1=AU1 , SD2	✓	✓	✓
		SLOT1 : SDI3		VXX:SISS1=AU1 , SD3		SISS1=AU1 , SD3	✓	✓	✓
		SLOT1 : SDI4		VXX:SISS1=AU1 , SD4		SISS1=AU1 , SD4	✓	✓	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ35K2 SERIES	RZ34K2 SERIES	Z330KC SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K2 SRQ350KC	RZ34K2 SRZ340KC	SRZ330C
PROJECTOR SETUP		SLOT2 : SD11		VXX:SISS1=AU2,SD1		SISS1=AU2,SD1	✓		
		SLOT2 : SD12		VXX:SISS1=AU2,SD2		SISS1=AU2,SD2	✓		
		SLOT2 : SD13		VXX:SISS1=AU2,SD3		SISS1=AU2,SD3	✓		
		SLOT2 : SD14		VXX:SISS1=AU2,SD4		SISS1=AU2,SD4	✓		
		SLOT1 : HDMI1		VXX:SISS1=AU1,HD1		SISS1=AU1,HD1	✓	✓	✓
		SLOT1 : HDMI2		VXX:SISS1=AU1,HD2		SISS1=AU1,HD2	✓	✓	✓
		SLOT2 : HDMI3		VXX:SISS1=AU2,HD3		SISS1=AU2,HD3	✓		
		SLOT2 : HDMI4		VXX:SISS1=AU2,HD4		SISS1=AU2,HD4	✓		
		SLOT1 : DV11		VXX:SISS1=AU1,DV1		SISS1=AU1,DV1	✓	✓	✓
		SLOT1 : DV12		VXX:SISS1=AU1,DV2		SISS1=AU1,DV2	✓		
		SLOT2 : DV13		VXX:SISS1=AU2,DV3		SISS1=AU2,DV3	✓		
		SLOT2 : DV14		VXX:SISS1=AU2,DV4		SISS1=AU2,DV4	✓		
		SLOT1 : DisplayPort1		VXX:SISS1=AU1,DP1		SISS1=AU1,DP1	✓	✓	✓
		SLOT1 : DisplayPort2		VXX:SISS1=AU1,DP2		SISS1=AU1,DP2	✓	✓	✓
		SLOT2 : DisplayPort3		VXX:SISS1=AU2,DP3		SISS1=AU2,DP3	✓		
		SLOT2 : DisplayPort4		VXX:SISS1=AU2,DP4		SISS1=AU2,DP4	✓		
		SLOT1 :12G SDI OPT1		VXX:SISS1=AU1,OP1		SISS1=AU1,OP1	✓	✓	✓
		SLOT1 : 12G SDI OPT2		VXX:SISS1=AU1,OP2		SISS1=AU1,OP2	✓	✓	✓
		SLOT2 : 12G SDI OPT1		VXX:SISS1=AU2,OP1		SISS1=AU2,OP1	✓		
		SLOT2 : 12G SDI OPT2		VXX:SISS1=AU2,OP2		SISS1=AU2,OP2	✓		
		LAST USED		VXX:SISS1=LSU		SISS1=LSU	✓	✓	✓
	STARTUP INPUT SELECT (DIGITAL LINK)	LAST USED		VXX:SISI2=+00000	QVX:SISI2	SISI2=+00000	✓	✓	✓
		INPUT1		VXX:SISI2=+00001		SISI2=+00001	✓	✓	✓
		INPUT2		VXX:SISI2=+00002		SISI2=+00002	✓	✓	✓
		INPUT3		VXX:SISI2=+00003		SISI2=+00003	✓	✓	✓
		INPUT4		VXX:SISI2=+00004		SISI2=+00004	✓	✓	✓
		INPUT5		VXX:SISI2=+00005		SISI2=+00005	✓	✓	✓
		INPUT6		VXX:SISI2=+00006		SISI2=+00006	✓	✓	✓
		INPUT7		VXX:SISI2=+00007		SISI2=+00007	✓	✓	✓
		INPUT8		VXX:SISI2=+00008		SISI2=+00008	✓	✓	✓
		INPUT9		VXX:SISI2=+00009		SISI2=+00009	✓	✓	✓
		INPIT10		VXX:SISI2=+00010		SISI2=+00010	✓	✓	✓
	NO SIGNAL SHUT-OFF	DISABLE		OAF:00	QAF	00	✓	✓	✓
		10min		OAF:10		10	✓	✓	✓
		20min		OAF:20		20	✓	✓	✓
		30min		OAF:30		30	✓	✓	✓
		40min		OAF:40		40	✓	✓	✓
		50min		OAF:50		50	✓	✓	✓
		60min		OAF:60		60	✓	✓	✓
		70min		OAF:70		70	✓	✓	✓
		80min		OAF:80		80	✓	✓	✓
		90min		OAF:90		90	✓	✓	✓
	NO SIGNAL LIGHTS-OUT	DISABLE		VXX:SLOI1=+00000	QVX:SLOI1	SLOI1=+00000	✓	✓	✓
		10SEC.		VXX:SLOI1=+00010		SLOI1=+00010	✓	✓	✓
		20SEC.		VXX:SLOI1=+00020		SLOI1=+00020	✓	✓	✓
		30SEC.		VXX:SLOI1=+00030		SLOI1=+00030	✓	✓	✓
		1MIN.		VXX:SLOI1=+00060		SLOI1=+00060	✓	✓	✓
		2MIN.		VXX:SLOI1=+00120		SLOI1=+00120	✓	✓	✓
		3MIN.		VXX:SLOI1=+00180		SLOI1=+00180	✓	✓	✓
		5MIN.		VXX:SLOI1=+00300		SLOI1=+00300	✓	✓	✓
	NO SIGNAL SETTING - SECONDARY INPUT	OFF		VXX:SINS1=OFF	QVX:SINS1	SINS1=OFF	✓	✓	✓
		DVI		VXX:SINS1=DVI		SINS1=DVI		✓	✓
		HDMI1		VXX:SINS1=HD1		SINS1=HD1	✓	✓	✓
		SDI		VXX:SINS1=SDI				✓	✓
		SDI1		VXX:SINS1=SD1		SINS1=SD1		✓	✓
		DIGITAL LINK		VXX:SINS1=DL1		SINS1=DL1	✓	✓	✓
		SLOT1 : SD11		VXX:SINS1=AU1,SD1		SINS1=AU1,SD1	✓	✓	✓
		SLOT1 : SD12		VXX:SINS1=AU1,SD2		SINS1=AU1,SD2	✓	✓	✓
		SLOT1 : SD13		VXX:SINS1=AU1,SD3		SINS1=AU1,SD3	✓	✓	✓
		SLOT1 : SD14		VXX:SINS1=AU1,SD4		SINS1=AU1,SD4	✓	✓	✓
		SLOT2 : SD11		VXX:SINS1=AU2,SD1		SINS1=AU2,SD1	✓		
		SLOT2 : SD12		VXX:SINS1=AU2,SD2		SINS1=AU2,SD2	✓		
		SLOT2 : SD13		VXX:SINS1=AU2,SD3		SINS1=AU2,SD3	✓		
		SLOT2 : SD14		VXX:SINS1=AU2,SD4		SINS1=AU2,SD4	✓		
		SLOT1 : HDMI1		VXX:SINS1=AU1,HD1		SINS1=AU1,HD1	✓	✓	✓
		SLOT1 : HDMI2		VXX:SINS1=AU1,HD2		SINS1=AU1,HD2	✓	✓	✓
		SLOT2 : HDMI3		VXX:SINS1=AU2,HD3		SINS1=AU2,HD3	✓		
		SLOT2 : HDMI4		VXX:SINS1=AU2,HD4		SINS1=AU2,HD4	✓		
		SLOT1 : DVI-D1		VXX:SINS1=AU1,DV1		SINS1=AU1,DV1	✓	✓	✓
		SLOT1 : DVI-D2		VXX:SINS1=AU1,DV2		SINS1=AU1,DV2	✓	✓	✓
		SLOT2 : DVI-D3		VXX:SINS1=AU2,DV3		SINS1=AU2,DV3	✓		
		SLOT2 : DVI-D4		VXX:SINS1=AU2,DV4		SINS1=AU2,DV4	✓		
		SLOT1 : DisplayPort1		VXX:SINS1=AU1,DP1		SINS1=AU1,DP1	✓	✓	✓
		SLOT1 : DisplayPort2		VXX:SINS1=AU1,DP2		SINS1=AU1,DP2	✓	✓	✓
		SLOT2 : DisplayPort3		VXX:SINS1=AU2,DP3		SINS1=AU2,DP3	✓		
		SLOT2 : DisplayPort4		VXX:SINS1=AU2,DP4		SINS1=AU2,DP4	✓		
		SLOT1 : 12G SDI OPT1		VXX:SINS1=AU1,OP1		SINS1=AU1,OP1	✓	✓	✓
		SLOT1 : 12G SDI OPT2		VXX:SINS1=AU1,OP2		SINS1=AU1,OP2	✓	✓	✓
		SLOT2 : 12G SDI OPT1		VXX:SINS1=AU2,OP1		SINS1=AU2,OP1	✓		
		SLOT2 : 12G SDI OPT2		VXX:SINS1=AU2,OP2		SINS1=AU2,OP2	✓		
	REMOTE2 - MODE	DEFAULT		VXX:RMPI0=+00000	QVX:RMPI0	RMPI0=+00000	✓	✓	✓
		USER		VXX:RMPI0=+00001		RMPI0=+00001	✓	✓	✓
	REMOTE2 - PIN2	NONE		VXX:RMPS1=P2<NONE	QVX:RMPS1=P2	RMPS1=P2<NONE	✓	✓	✓
		POWER		VXX:RMPS1=P2<POWER		RMPS1=P2<POWER	✓	✓	✓
	REMOTE2 - PIN3 - 7	* PARAMETER		VXX:RMPS1=P*<*****	QVX:RMPS1=P*		✓	✓	✓
		* PARAMETER1	PIN3	VXX:RMPS1=P3<*****		RMPS1=P3<*****	✓	✓	✓
			PIN4	VXX:RMPS1=P4<*****		RMPS1=P4<*****	✓	✓	✓
			PIN5	VXX:RMPS1=P5<*****		RMPS1=P5<*****	✓	✓	✓
			PIN6	VXX:RMPS1=P6<*****		RMPS1=P6<*****	✓	✓	✓
			PIN7	VXX:RMPS1=P7<*****		RMPS1=P7<*****	✓	✓	✓
		* PARAMETER2	NONE	VXX:RMPS1=P*<NONE		RMPS1=P*<NONE	✓	✓	✓
			DVI	VXX:RMPS1=P*<DVI		RMPS1=P*<DVI	✓	✓	✓
			HDMI	VXX:RMPS1=P*<HDMI		RMPS1=P*<HDMI	✓	✓	✓
			HDMI1	VXX:RMPS1=P*<HDMI1		RMPS1=P*<HDMI1	✓	✓	✓
			SDI1	VXX:RMPS1=P*<SD1		RMPS1=P*<SD1	✓	✓	✓
			DIGITAL LINK	VXX:RMPS1=P*<DLINK		RMPS1=P*<DLINK	✓	✓	✓
			SLOT1 : SD11	VXX:RMPS1=P*<AU1,SD1		RMPS1=P*<AU1,SD1	✓	✓	✓
			SLOT1 : SD12	VXX:RMPS1=P*<AU1,SD2		RMPS1=P*<AU1,SD2	✓	✓	✓
			SLOT1 : SD13	VXX:RMPS1=P*<AU1,SD3		RMPS1=P*<AU1,SD3	✓	✓	✓
			SLOT1 : SD14	VXX:RMPS1=P*<AU1,SD4		RMPS1=P*<AU1,SD4	✓	✓	✓
			SLOT2 : SD11	VXX:RMPS1=P*<AU2,SD1		RMPS1=P*<AU2,SD1	✓		
			SLOT2 : SD12	VXX:RMPS1=P*<AU2,SD2		RMPS1=P*<AU2,SD2	✓		
			SLOT2 : SD13	VXX:RMPS1=P*<AU2,SD3		RMPS1=P*<AU2,SD3	✓		
			SLOT2 : SD14	VXX:RMPS1=P*<AU2,SD4		RMPS1=P*<AU2,SD4	✓		
			SLOT1 : HDMI1	VXX:RMPS1=P*<AU1,HD1		RMPS1=P*<AU1,HD1	✓	✓	✓
			SLOT1 : HDMI2	VXX:RMPS1=P*<AU1,HD2		RMPS1=P*<AU1,HD2	✓	✓	✓
			SLOT2 : HDMI3	VXX:RMPS1=P*<AU2,HD3		RMPS1=P*<AU2,HD3	✓		
			SLOT2 : HDMI4	VXX:RMPS1=P*<AU2,HD4		RMPS1=P*<AU2,HD4	✓		
			SLOT1 : DV11	VXX:RMPS1=P*<AU1,DV1		RMPS1=P*<AU1,DV1	✓	✓	✓
			SLOT1 : DV12	VXX:RMPS1=P*<AU1,DV2		RMPS1=P*<AU1,DV2	✓	✓	✓
			SLOT2 : DV13	VXX:RMPS1=P*<AU2,DV3		RMPS1=P*<AU2,DV3	✓		
			SLOT2 : DV14	VXX:RMPS1=P*<AU2,DV4		RMPS1=P*<AU2,DV4	✓		
			SLOT1 : DisplayPort1	VXX:RMPS1=P*<AU1,DP1		RMPS1=P*<AU1,DP1	✓	✓	✓
			SLOT1 : DisplayPort2	VXX:RMPS1=P*<AU1,DP2		RMPS1=P*<AU1,DP2	✓	✓	✓
			SLOT2 : DisplayPort3	VXX:RMPS1=P*<AU2,DP3		RMPS1=P*<AU2,DP3	✓		
			SLOT2 : DisplayPort4	VXX:RMPS1=P*<AU2,DP4		RMPS1=P*<AU2,DP4	✓		
			SLOT1 : 12G SDI OPT1	VXX:RMPS1=P*<AU1,OP1		RMPS1=P*<AU1,OP1	✓	✓	✓
			SLOT1 : 12G SDI OPT2	VXX:RMPS1=P*<AU1,OP2		RMPS1=P*<AU1,OP2	✓	✓	✓
			SLOT2 : 12G SDI OPT1	VXX:RMPS1=P*<AU2,OP1		RMPS1=P*<AU2,OP1	✓		
			SLOT2 : 12G SDI OPT2	VXX:RMPS1=P*<AU2,OP2		RMPS1=P*<AU2,OP2	✓		
	REMOTE2 - PIN8	NONE	NONE	VXX:RMPS1=P8<NONE	QVX:RMPS1=P8	RMPS1=P8<NONE	✓	✓	✓
		SHUTTER	SHUTTER	VXX:RMPS1=P8<SHUTTER		RMPS1=P8<SHUTTER	✓	✓	✓
	FUNCTION - BUTTON	DISABLE		OFC:0	QFC	0	✓	✓	✓
		SYSTEM SELECTOR		OFC:1		1	✓	✓	✓
		SYSTEM DAYLIGHT VIEW		OFC:2		2	✓	✓	✓
		SUB MEMORY		OFC:3		3	✓	✓	✓
		FREEZE		OFC:4		4	✓	✓	✓
		WAVEFORM MONITOR		OFC:6		6	✓	✓	✓
		LENS MEMORY LOAD		OFC:7		7	✓	✓	✓
		LEFT/RIGHT SWAP		OFC:8		8		✓	✓
		PROJECTION METHOD		OFC:10		10	✓	✓	✓
		GEOMETRY		OFC:13		13	✓	✓	✓
		OSD POSITION		OFC:14		14	✓	✓	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ35K2 SERIES	RZ34K2 SERIES	Z330K2 SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K2 SRQ350KC	RZ34K2 SRZ340KC	SRZ330C
	DATE AND TIME-DATE SETTING	Year: yyyy Month: mm Date: dd Day:w(1~7:Mon~Sun)		TSD:201506151 TSD:yyyymmddw	QGD	201506161 yyyymmddw	✓	✓	✓
	DATE AND TIME-TIME SETTING	Hour: hh Minute: mm Second: ss		TST:154503 TST:hmmss	QGT	154503 hmmss	✓	✓	✓
	DATE AND TIME-NTP SYNCHRONIZATION	OFF ON		VXX:NTPI0=+00000 VXX:NTPI0=+00001	QVX:NTPI0	NTPI0=+00000 NTPI0=+00001	✓	✓	✓
	LENS TYPE	ET-D75LE6 ET-D75LE10 ET-D75LE20 ET-D75LE30 ET-D75LE40 ET-D75LE8 ET-D75LE95 ET-D75LE90 ET-D75LE50		VXX:LNEI1=+00001 VXX:LNEI1=+00002 VXX:LNEI1=+00003 VXX:LNEI1=+00004 VXX:LNEI1=+00005 VXX:LNEI1=+00006 VXX:LNEI1=+00007 VXX:LNEI1=+00008 VXX:LNEI1=+00009	QVX:LNEI1	LNEI1=+00001 LNEI1=+00002 LNEI1=+00003 LNEI1=+00004 LNEI1=+00005 LNEI1=+00006 LNEI1=+00007 LNEI1=+00008 LNEI1=+00009	✓	✓	✓
	LENS ID	All 1 255		VXX:LNEI4=+00000 VXX:LNEI4=+00001 VXX:LNEI4=+00255	QVX:LNEI4	LNEI4=+00000 LNEI4=+00001 LNEI4=+00255	✓	✓	✓
	LENS NAME			VXX:LNES5=LENSNAME	QVX:LNES5	LNES5=LENSNAME	✓	✓	✓
	LENS CALIBRATION	EXECUTE (ALL) EXECUTE (SHIFT) EXECUTE (FOCUS) EXECUTE (ZOOM) EXECUTE (SHIFT/FOCUS) EXECUTE (SHIFT/ZOOM) EXECUTE (FOCUS/ZOOM)		VXX:LNSI0=+00001 VXX:LNSI0=+00011 VXX:LNSI0=+00012 VXX:LNSI0=+00013 VXX:LNSI0=+00021 VXX:LNSI0=+00022 VXX:LNSI0=+00023			✓	✓	✓
	LENS MEMORY1 NAME CHANGE	LENSMEMORY1		VXX:NCGS5=LENSMEMORY1	QVX:NCGS5	NCGS5=LENSMEMORY1	✓	✓	✓
	LENS MEMORY2 NAME CHANGE	LENSMEMORY2		VXX:NCGS6=LENSMEMORY2	QVX:NCGS6	NCGS6=LENSMEMORY2	✓	✓	✓
	LENS MEMORY3 NAME CHANGE	LENSMEMORY3		VXX:NCGS7=LENSMEMORY3	QVX:NCGS7	NCGS7=LENSMEMORY3	✓	✓	✓
	LENS MEMORY4 NAME CHANGE	LENSMEMORY4		VXX:NCGS9=LENSMEMORY4	QVX:NCGS9	NCGS9=LENSMEMORY4	✓	✓	✓
	LENS MEMORY5 NAME CHANGE	LENSMEMORY5		VXX:NCGSA=LENSMEMORY5	QVX:NCGSA	NCGSA=LENSMEMORY5	✓	✓	✓
	LENS MEMORY6 NAME CHANGE	LENSMEMORY6		VXX:NCGSB=LENSMEMORY6	QVX:NCGSB	NCGSB=LENSMEMORY6	✓	✓	✓
	LENS MEMORY7 NAME CHANGE	LENSMEMORY7		VXX:NCGSC=LENSMEMORY7	QVX:NCGSC	NCGSC=LENSMEMORY7	✓	✓	✓
	LENS MEMORY8 NAME CHANGE	LENSMEMORY8		VXX:NCGSD=LENSMEMORY8	QVX:NCGSD	NCGSD=LENSMEMORY8	✓	✓	✓
	LENS MEMORY9 NAME CHANGE	LENSMEMORY9		VXX:NCGSE=LENSMEMORY9	QVX:NCGSE	NCGSE=LENSMEMORY9	✓	✓	✓
	LENS MEMORY10 NAME CHANGE	LENSMEMORY10		VXX:NCGSF=LENSMEMORY10	QVX:NCGSF	NCGSF=LENSMEMORY10	✓	✓	✓
	LENS MEMORY-LOAD	LENS MEMORY1 LENS MEMORY2 LENS MEMORY3 LENS MEMORY4 LENS MEMORY5 LENS MEMORY6 LENS MEMORY7 LENS MEMORY8 LENS MEMORY9 LENS MEMORY10		VXX:LNMI1=+00000 VXX:LNMI1=+00001 VXX:LNMI1=+00002 VXX:LNMI1=+00003 VXX:LNMI1=+00004 VXX:LNMI1=+00005 VXX:LNMI1=+00006 VXX:LNMI1=+00007 VXX:LNMI1=+00008 VXX:LNMI1=+00009			✓	✓	✓
	LENS MEMORY-SAVE	LENS MEMORY1 LENS MEMORY2 LENS MEMORY3 LENS MEMORY4 LENS MEMORY5 LENS MEMORY6 LENS MEMORY7 LENS MEMORY8 LENS MEMORY9 LENS MEMORY10		VXX:LNMI2=+00000 VXX:LNMI2=+00001 VXX:LNMI2=+00002 VXX:LNMI2=+00003 VXX:LNMI2=+00004 VXX:LNMI2=+00005 VXX:LNMI2=+00006 VXX:LNMI2=+00007 VXX:LNMI2=+00008 VXX:LNMI2=+00009			✓	✓	✓
	LENS MEMORY-DELETE	LENS MEMORY1 LENS MEMORY2 LENS MEMORY3 LENS MEMORY4 LENS MEMORY5 LENS MEMORY6 LENS MEMORY7 LENS MEMORY8 LENS MEMORY9 LENS MEMORY10		VXX:LNMI3=+00000 VXX:LNMI3=+00001 VXX:LNMI3=+00002 VXX:LNMI3=+00003 VXX:LNMI3=+00004 VXX:LNMI3=+00005 VXX:LNMI3=+00006 VXX:LNMI3=+00007 VXX:LNMI3=+00008 VXX:LNMI3=+00009			✓	✓	✓
	LENS MEMORY1-DEFAULT NAME	LENSMEMORY1		VXX:NCLI5=+00000			✓	✓	✓
	LENS MEMORY2-DEFAULT NAME	LENSMEMORY2		VXX:NCLI6=+00000			✓	✓	✓
	LENS MEMORY3-DEFAULT NAME	LENSMEMORY3		VXX:NCLI7=+00000			✓	✓	✓
	LENS MEMORY4-DEFAULT NAME	LENSMEMORY4		VXX:NCLI9=+00000			✓	✓	✓
	LENS MEMORY5-DEFAULT NAME	LENSMEMORY5		VXX:NCLIA=+00000			✓	✓	✓
	LENS MEMORY6-DEFAULT NAME	LENSMEMORY6		VXX:NCLIB=+00000			✓	✓	✓
	LENS MEMORY7-DEFAULT NAME	LENSMEMORY7		VXX:NCLIC=+00000			✓	✓	✓
	LENS MEMORY8-DEFAULT NAME	LENSMEMORY8		VXX:NCLID=+00000			✓	✓	✓
	LENS MEMORY9-DEFAULT NAME	LENSMEMORY9		VXX:NCLIE=+00000			✓	✓	✓
	LENS MEMORY10-DEFAULT NAME	LENSMEMORY10		VXX:NCLIF=+00000			✓	✓	✓
	INITIALIZE-ALL USER DATA	USER INITILIZE USER RESTORE		VXX:RSTS1=0password VXX:RSTS1=1password			✓	✓	✓
	INITIAL START UP	STANDBY ON LAST MEMORY		OPY:0 OPY:1 OPY:2	QPY	0 1 2	✓	✓	✓
	MODEL NAME	MODEL NAME			QID	MODELNAME	✓	✓	✓
	SERIAL NUMBER	SW0101234			QSN	SW0101234	✓	✓	✓
	PROJECTOR RUNTIME	7864320H			QVX:RTMS1	RTMS1=7864320	✓	✓	✓
	LAMP1(LIGHT1) RUNTIME	9999H			Q\$L:1	9999	✓	✓	✓
	LIGHT1 RUNTIME	7864320H			QVX:LRTS3=00	LRTS3=00:7864320	✓	✓	✓
	LIGHT STATUS	ALL OFF 1:ON, 2:OFF			QLS	0 1	✓	✓	✓
	CONTINUOUS LIGHTING TIME	7864320H00M			QVX:CLTS1	CLTS1=7864320:00	✓	✓	✓
	CONSOLIDATED RUNTIME	7864320H			QVX:CRTS1	CRTS1=7864320	✓	✓	✓
	LAMP(LIGHT) CONTROL STATUS	LAMP OFF In turning ON LAMP ON LAMP Cooling			Q\$S	0 1 2 3	✓	✓	✓
	POWER STATUS	POWER OFF In turning ON POWER ON Cooling			QVX:POWI1	POWI1=+00001 POWI1=+00002 POWI1=+00003 POWI1=+00004	✓	✓	✓
	MAC ADDRESS	AB0102030405			QMA	AB0102030405	✓	✓	✓
	MAIN FIRMWARE VERSION	V1.00.01			QVX:SVRS0	SVRS0=1.00.01	✓	✓	✓
	NETWORK FIRMWARE VERSION	V1.00			QVX:SVRS1	SVRS1=1.00	✓	✓	✓
	INPUT SIGNAL NAME	CHANNEL1 (MAIN CH)			QVX:NSGS1	NSGS1=****	✓	✓	✓
	TEMPERATURE (INTAKE)	0030/0080			QTM:0	0030/0080	✓	✓	✓
	TEMPERATURE (EXHAUST AIR)	0030/0080			QTM:1	0030/0080	✓	✓	✓
	LAN data Cloning Write protect	OFF ON		LCL:WRP0 LCL:WRP1	QCL:WRP	QCL:WRP0 QCL:WRP1	✓	✓	✓
	MECH. SHUTTER COUNT				QVX:MSCI0	MSCI0=+****	✓	✓	✓
	INFO MONITOR SETTING - DEFAULT	OFF USER VIEW		VXX:INFI1=+00000 VXX:INFI1=+00001	QVX:INFI1	INFI1=+00000 INFI1=+00001	✓	✓	✓
	INFO MONITOR SETTING - USER VIEW	INPUT SIGNAL AC VOLTAGE INTAKE AIR TEMP. EXHAUST AIR TEMP. SHUTTER OSD IP ADDRESS OFF ON		VXX:INFS2=01:**** VXX:INFS2=02:**** VXX:INFS2=03:**** VXX:INFS2=04:**** VXX:INFS2=05:**** VXX:INFS2=06:**** VXX:INFS2=07:**** VXX:INFS2=08:**** VXX:INFS2=*:00000 VXX:INFS2=*:00001	QVX:INFS2=01 QVX:INFS2=02 QVX:INFS2=03 QVX:INFS2=04 QVX:INFS2=05 QVX:INFS2=06 QVX:INFS2=07 QVX:INFS2=08	INFS2=01:**** INFS2=02:**** INFS2=03:**** INFS2=04:**** INFS2=05:**** INFS2=06:**** INFS2=07:**** INFS2=08:****	✓	✓	✓
	INFO MONITOR SETTING - DIRECTION	AUTO NORMAL FLIPPED		VXX:INFI3=+00000 VXX:INFI3=+00001 VXX:INFI3=+00002	QVX:INFI3	INFI3=+00000 INFI3=+00001 INFI3=+00002	✓	✓	✓
	INFO MONITOR SETTING - BRIGHTNESS	30% 100%		VXX:INFI4=+00030 VXX:INFI4=+00100	QVX:INFI4	INFI4=+00030 INFI4=+00100	✓	✓	✓
	TEST PATTERN	Off White Black Window Reversed Window Cross Hatch		OTS:00 OTS:01 OTS:02 OTS:05 OTS:06 OTS:07	QTS	00 01 02 05 06 07	✓	✓	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ35K2 SERIES	RZ34K2 SERIES	Z330KC SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K2 SRO350KC	RZ34K2 SRZ340KC	SRZ330C
TEST PATTERN		Color Bar V		OTS:08		08	✓	✓	✓
		Focus (Level 0%)		OTS:32		32	✓	✓	✓
		Focus (Level 50%)		OTS:33		33	✓	✓	✓
		Focus (Level 100%)		OTS:34		34	✓	✓	✓
		Color Bar Side		OTS:52		52	✓	✓	✓
		16:9/4:3		OTS:59		59	✓	✓	✓
		Focus Red		OTS:70		70	✓	✓	✓
		Focus Green		OTS:71		71	✓	✓	✓
		Focus Blue		OTS:72		72	✓	✓	✓
		Focus Cyan		OTS:73		73	✓	✓	✓
		Focus Magenta		OTS:74		74	✓	✓	✓
		Focus Yellow		OTS:75		75	✓	✓	✓
		Focus		OTS:78		78	✓	✓	✓
		3D-1		OTS:80		80		✓	✓
		3D-2		OTS:81		81		✓	✓
		3D-3		OTS:82		82		✓	✓
		3D-4		OTS:83		83		✓	✓
		CIRCLE		OTS:87		87	✓	✓	✓
SIGNAL LIST	SIGNAL LIST-REGISTRATION			OEM			✓	✓	✓
	SIGNAL LIST-DELETE	A1		ODM:A1			✓	✓	✓
		A2		ODM:A2			✓	✓	✓
		A7		ODM:A7			✓	✓	✓
		A8		ODM:A8			✓	✓	✓
		L1		ODM:L1			✓	✓	✓
		L2		ODM:L2			✓	✓	✓
		L7		ODM:L7			✓	✓	✓
		L8		ODM:L8			✓	✓	✓
	SUB MEMORY LIST-CHANGEOVER	01		OCS:01			✓	✓	✓
		96		OCS:96			✓	✓	✓
	SUB MEMORY LIST-CHANGEOVER (EXTENDED)	01		OCS:01-01			✓	✓	✓
		96		OCS:95-96			✓	✓	✓
	SUB MEMORY LIST-REGISTRATION			OES			✓	✓	✓
	SUB MEMORY LIST-DELETE	01		ODS:01-01			✓	✓	✓
		96		ODS:95-96			✓	✓	✓
	SUB MEMORY USAGE STATE	01			QSB	01	✓	✓	✓
		96				96	✓	✓	✓
SECURITY	SECURITY SETTING	OFF			QVX:SPWI1	SPWI1=+00000	✓	✓	✓
		ON				SPWI1=+00001	✓	✓	✓
	CONTROL DEVICE SETUP-CONTROL PANEL	DISABLE		VXX:CDSI1=+00000	QVX:CDSI1	CDSI1=+00000	✓	✓	✓
		ENABLE		VXX:CDSI1=+00001		CDSI1=+00001	✓	✓	✓
		USER		VXX:CDSI1=+00002		CDSI1=+00002	✓	✓	✓
	CONTROL DEVICE SETUP-REMOTE CONTROL	DISABLE		VXX:CDSI2=+00000	QVX:CDSI2	CDSI2=+00000	✓	✓	✓
		ENABLE		VXX:CDSI2=+00001		CDSI2=+00001	✓	✓	✓
		USER		VXX:CDSI2=+00002		CDSI2=+00002	✓	✓	✓
NETWORK	WIRELESS LAN	OFF(DISABLE)		ONS:0	QVX:WLSI1	WLSI1=+00000	✓	✓	✓
		ON(ENABLE)		ONS:14		WLSI1=+00014	✓	✓	✓
	DIGITAL LINK MODE	AUTO		VXX:DKMI1=+00001	QVX:DKMI1	DKMI1=+00001	✓	✓	✓
		DIGITAL LINK		VXX:DKMI1=+00002		DKMI1=+00002	✓	✓	✓
		ETHERNET		VXX:DKMI1=+00003		DKMI1=+00003	✓	✓	✓
		LONG REACH MODE		VXX:DKMI1=+00004		DKMI1=+00004	✓	✓	✓
	DIGITAL LINK STATUS-LINK	NO LINK			QVX:DKSI1	DKSI1=+00000	✓	✓	✓
		DIGITAL LINK				DKSI1=+00001	✓	✓	✓
		LPM				DKSI1=+00002	✓	✓	✓
		ETHERNET				DKSI1=+00003	✓	✓	✓
	DIGITAL LINK STATUS-HDCP STATUS	NO SIGNAL			QVX:DKSI2	DKSI2=+00000	✓	✓	✓
		OFF				DKSI2=+00001	✓	✓	✓
		ON				DKSI2=+00002	✓	✓	✓
	DIGITAL LINK STATUS-SIGNAL QUALITY (MIN)	-255			QVX:DKSI3	DKSI3=-00255	✓	✓	✓
		0				DKSI3=+00000	✓	✓	✓
	DIGITAL LINK STATUS-SIGNAL QUALITY (MAX)	-255			QVX:DKSI4	DKSI4=-00255	✓	✓	✓
		0				DKSI4=+00000	✓	✓	✓
	DIGITAL LINK INPUT CH LIST	HD1:HDMI1,HD2:HDMI2...			QVX:DL1S1	DL1S1=HD1:HDMI1,****:***	✓	✓	✓
	PROJECTOR NAME SETTING	PROJECTOR1		VXX:NCGS8=PROJECTOR1	QVX:NCGS8	NCGS8=PROJECTOR1	✓	✓	✓
	NFC SETTING	OFF		VXX:NFCI1=+00000	QVX:NFCI1	NFCI1=+00000	✓	✓	✓
		READ ONLY		VXX:NFCI1=+00001		NFCI1=+00001	✓	✓	✓
		READ/WRITE		VXX:NFCI1=+00003		NFCI1=+00003	✓	✓	✓
	Art-Net SETUP	OFF		VXX:DANI1=+00000	QVX:DANI1	DANI1=+00000	✓	✓	✓
		ON(2.*.*)		VXX:DANI1=+00002		DANI1=+00002	✓	✓	✓
		ON(10.*.*)		VXX:DANI1=+00003		DANI1=+00003	✓	✓	✓
		ON(MANUAL)		VXX:DANI1=+00004		DANI1=+00004	✓	✓	✓
	Art-Net SETUP-START ADDRESS	1		VXX:DANI3=+00001	QVX:DANI3	DANI3=+00001	✓	✓	✓
		501		VXX:DANI3=+00501		DANI3=+00501	✓	✓	✓
	Art-Net SETUP-NET	0		VXX:DANI4=+00000	QVX:DANI4	DANI4=+00000	✓	✓	✓
		127		VXX:DANI4=+00127		DANI4=+00127	✓	✓	✓
	Art-Net SETUP-SUB NET	0		VXX:DANI5=+00000	QVX:DANI5	DANI5=+00000	✓	✓	✓
		15		VXX:DANI5=+00015		DANI5=+00015	✓	✓	✓
	Art-Net SETUP-UNIVERS	0		VXX:DANI6=+00000	QVX:DANI6	DANI6=+00000	✓	✓	✓
		15		VXX:DANI6=+00015		DANI6=+00015	✓	✓	✓
	Art-Net SETUP-CHANNEL SETTING	DEFAULT		VXX:DANI8=+00000	QVX:DANI8	DANI8=+00000	✓	✓	✓
		1		VXX:DANI8=+00001		DANI8=+00001	✓	✓	✓
		2		VXX:DANI8=+00002		DANI8=+00002	✓	✓	✓
		USER		VXX:DANI8=+00100		DANI8=+00100	✓	✓	✓
	PRESHOW MODE	OFF			QVX:PSMI1	PSMI1=+00000	✓	✓	✓
		ON				PSMI1=+00001	✓	✓	✓

Note: The commands or parameters with "*" shows available commands or parameters for the projector which has been activated by the Upgrade Kit.