

					RQ45K SERIES	
CATEGORY	EndPoint	body1	body2	Parameter	RQ45K	
Basic Control	/api/{version}/power	power-state		standby	✓	
				on	✓	
	/api/{version}/input			HDMI1	✓	
				HDMI2	✓	
				SLOT1	✓	
				SLOT2	✓	
				SDI	✓	
					GET only	
	/api/{version}/input-image					
	/api/{version}/av-mute	av-mute-state		on	✓	
				off	✓	
	/api/{version}/freeze	freeze-state		on	✓	
				off	✓	
	/api/{version}/on-screen-display	osd-state		on	✓	
				off	✓	
	/api/{version}/pre-show-mode	pre-show-mode-state		on	✓	
				off	✓	
	/api/{version}/test-pattern	test-pattern-state		white	✓	
				black	✓	
				colorbar-vertical	✓	
				colorbar-horizontal	✓	
				focus	✓	
				aspect	✓	
				window	✓	
				window-invert	✓	
				crosshatch-white	✓	
				crosshatch-red	✓	
			crosshatch-green	✓		
			crosshatch-blue	✓		
			crosshatch-cyan	✓		
			crosshatch-magenta	✓		
			crosshatch-yellow	✓		
			circle	✓		
			user1	✓		
			user2	✓		
			user3	✓		
			user4	✓		
			off	✓		
		test-pattern-users	test-pattern-user-image-file		✓	
			test-pattern-user-image-name		✓	
	/api/{version}/test-pattern/{test-pattern-id}	test-pattern-user-image-file			PUT only	
	/api/{version}/lens	lens-shift-horizontal			✓	
		lens-shift-vertical			✓	
		lens-zoom			✓	
		lens-focus			✓	
	/api/{version}/lens-memories	lens-memories		lens-memory-id	✓	
				lens-memory-name	✓	
				lens-memory-shift-horizontal	✓	
				lens-memory-shift-vertical	✓	
				lens-memory-zoom	✓	
				lens-memory-focus	✓	
	/api/{version}/back-color	back-color-state		blue	✓	
				black	✓	
				user1	✓	
				user2	✓	
				user3	✓	
				user4	✓	
				default-logo	✓	
Setting	/api/{version}/ntp	ntp-sync		on	✓	
		ntp-server		off	✓	
	/api/{version}/https	https-state		on	✓	
				off	✓	
	/api/{version}/network	network-ip-version		ipv4	✓	
				ipv6	✓	
				ipv4-and-ipv6	✓	
				on	✓	
				off	✓	
		network-wired-dhcp			✓	
		network-wired-ipv4-ip-address			✓	
		network-wired-ipv4-subnetmask			✓	
		network-wired-ipv4-default-gateway			✓	
		network-wired-ipv4-dns1-ip-address			✓	
		network-wired-ipv4-dns2-ip-address			✓	
		network-wired-ipv6-auto-configuration			✓	
		network-wired-ipv6-temporary-address			✓	
		network-wired-ipv6-ip-address			✓	
		network-wired-ipv6-prefix-length			✓	
		network-wired-ipv6-default-gateway			✓	
		network-wired-ipv6-link-local-address			✓	
		network-wired-ipv6-stateful-address			✓	
		network-wired-ipv6-stateless-addresses	network-wired-ipv6-stateless-address-id		✓	
		network-wired-ipv6-temporary-addresses	network-wired-ipv6-temporary-address-id		✓	
		network-wireless-state	network-wired-ipv6-temporary-address		✓	
		network-wireless-key		on	✓	
		network-wireless-ssid		off	✓	
		network-wireless-authentication			✓	
		network-wireless-encryption			✓	
		network-wireless-ipv4-ip-address			✓	
		network-wireless-ipv4-subnetmask			✓	
		network-wireless-ipv4-default-gateway			✓	
		/api/{version}/light-output	light-output-state			✓
			light-output-max			✓
		/api/{version}/operating-mode	operating-mode-state		normal	✓
					eco	✓
					quiet	✓
					user1	✓
					user2	✓
				user3	✓	
	/api/{version}/clock	clock-year			GET only	
		clock-month			GET only	
		clock-day			GET only	
		clock-hour			GET only	
		clock-minute			GET only	
		clock-second			GET only	
	/api/{version}/command-protect	command-protect-state		disable	✓	
				enable-md5	✓	
				enable-sha-256	✓	
	/api/{version}/schedule	schedule-state		on	✓	
				off	✓	
	/api/{version}/pilight	pilight-password			PUT only	
	/api/{version}/crestron	crestron-state		on	GET only	
				off	GET only	
	/api/{version}/update	update-firmware-progress			GET only	
		update-firmware			PUT only	
	/api/{version}/https-csr-key	update-time			GET only	
		rsa-length			GET only	
	/api/{version}/https-csr-request	https-csr-host-name			PUT only	
		https-csr-country-code			PUT only	
		https-csr-prefectures-name			PUT only	
		https-csr-city-name			PUT only	
		https-csr-organization-name			PUT only	
		https-csr-department-name			PUT only	
	/api/{version}/https-csr-file				GET only	
	/api/{version}/https-intermediate-certificate	state			PUT only	
	/api/{version}/https-server-certificate	state			PUT only	
Status	/api/{version}/error	errors	error-kind	no error	GET only	
			error-category	warning	GET only	
				error	GET only	
				none	GET only	
				fan	GET only	
				light	GET only	
				temperature	GET only	
				cover open	GET only	
				filter	GET only	
				other	GET only	
			error-code		GET only	
			error-message		GET only	
	/api/{version}/lights	lights	light-id		GET only	
			light-name		GET only	
			light-state		GET only	
			light-runtime		GET only	
	/api/{version}/lights/{light-id}	light-id			GET only	
		light-name			GET only	
		light-state			GET only	
		light-runtime			GET only	
	/api/{version}/device-information	model-name			GET only	
		serial-no			GET only	
		projector-name			GET only	
		mac-address			GET only	
		power-on-times			GET only	
		device-runtime			GET only	
		ac-voltage			GET only	
/api/{version}/version	main-version			GET only		
/api/{version}/temperatures	temperatures	temperature-id		GET only		
		temperature-name		GET only		
		temperature-celsius		GET only		
		temperature-fahrenheit		GET only		
/api/{version}/temperatures/{temperature-id}	temperature-id			GET only		
	temperature-name			GET only		
	temperature-celsius			GET only		
	temperature-fahrenheit			GET only		
/api/{version}/packet-information	packet-info-collision			GET only		
	packet-info-recv-packet			GET only		
	packet-info-recv-packet-error			GET only		
	packet-info-recv-packet-drop			GET only		
	packet-info-recv-packet-overflow			GET only		
	packet-info-recv-packet-frame			GET only		
	packet-info-send-packet			GET only		
	packet-info-send-packet-error			GET only		
	packet-info-send-packet-drop			GET only		
	packet-info-send-packet-overflow			GET only		
	packet-info-send-packet-carrier			GET only		
/api/{version}/fans	fans	fan-id		GET only		
		fan-name		GET only		
		fan-rotation-speed		GET only		
/api/{version}/fans/{fan-id}	fan-id			GET only		
	fan-name			GET only		
	fan-rotation-speed			GET only		
/api/{version}/angle-sensor	roll-angle			GET only		
	pitch-angle			GET only		
/api/{version}/signal	signal-information			GET only		