					VMQ85 SERIES
CATEGORY	EndPoint	body1	body2	Parameter	VMQ85
Basic Control	/api/{version}/power	power-state		standby	✓
				on	✓
				reset	✓
	/api/{version}/input			HDMI1	✓
				HDMI2	✓
				MEMORY VIEWER	✓
				NETWORK	✓
				DIGITAL LINK	✓
	/api/{version}/av-mute	av-mute-state		on	✓
				off	✓
	/api/{version}/freeze	freeze-state		on	✓
				off	✓
	/api/{version}/on-screen-display	osd-state		on	✓
				off	✓
	/api/{version}/test-pattern	test-pattern-state		white	✓
				colorbar-vertical	✓
				colorbar-horizontal	✓
				aspect	✓
				whitecross-black	✓
				blackcross-white	✓
				crosshatch-black	✓
				off	✓
	/api/{version}/back-color	back-color-state		blue	✓
				black	✓
				user1	✓
				default-logo	✓
Setting	/api/{version}/ntp	ntp-sync		on	✓
				off	✓
		ntp-server			✓
	/api/{version}/https	https-state		on	✓
				off	✓
	/api/{version}/network	network-ip-version		ipv4	✓
				ipv6	✓
				ipv4-and-ipv6	✓
		network-wired-dhcp		on	✓
				off	✓
		network-wired-ipv4-ip-address			✓
		network-wired-ipv4-subnetmask			✓
		network-wired-ipv4-default-gateway			✓
		network-wired-ipv4-dns1-ip-address			✓
		network-wired-ipv4-dns2-ip-address			✓
		network-wired-ipv6-auto-configuration		on	✓
				off	✓
		network-wired-ipv6-temporary-address		on	✓
				off	✓
		network-wired-ipv6-ip-address			✓
		network-wired-ipv6-prefix-length			✓
		network-wired-ipv6-default-gateway			✓
		network-wired-ipv6-link-local-address			✓
		network-wired-ipv6-stateful-address			✓
		network-wired-ipv6-stateless-addresses	network-wired-ipv6-stateless-address-id		✓
			network-wired-ipv6-stateless-address		✓
		network-wired-ipv6-temporary-addresses	network-wired-ipv6-temporary-address-id		✓
			network-wired-ipv6-temporary-address		✓
		network-wireless-state		on	✓
				off	✓
		network-wireless-ssid			✓
		network-wireless-authentication			✓
		network-wireless-encryption			✓
		network-wireless-ipv4-ip-address			✓
		network-wireless-ipv4-subnetmask			✓
		network-wireless-ipv4-default-gateway			✓
	/api/{version}/light-output	light-output-state			✓
	/api/{version}/operating-mode	operating-mode-state		normal	✓
				eco	✓
				quiet1	✓
				quiet2	✓
				user1	✓
	/api/{version}/clock	clock-year			✓
		clock-month			✓
		clock-day			✓
		clock-hour			✓
		clock-minute			✓
		clock-second			✓
	/api/{version}/command-protect	command-protect-state		disable	✓
				enable-md5	✓
				enable-sha-256	✓
	/api/{version}/schedule	schedule-state		on	✓
				off	✓
	/api/{version}/pjlink	pjlink-state		on	✓
				off	✓
		pjlink-password			✓
	/api/{version}/crestron	crestron-state		on	✓
				off	✓
	/api/{version}/sound	sound-volume			✓
	/api/{version}/https-csr-key	update-time			✓
		rsa-length			✓
	/api/{version}/https-csr-request	https-csr-host-name			✓
		https-csr-country-code			✓
		https-csr-prefectures-name			✓
		https-csr-city-name			✓
		https-csr-organization-name			✓
		https-csr-department-name			✓
	/api/{version}/https-csr-file				✓
	/api/{version}/https-intermediate-certificate	state			✓
	/api/{version}/https-server-certificate	state			✓
Status	/api/{version}/error	errors	error-kind	no error	✓
				warning	✓
				error	✓
			error-category	none	✓
				fan	✓
				light	✓
				temperature	✓
				cover open	✓
				filter	✓
				other	✓
			error-code		✓
			error-message		✓
	/api{version}/lights	lights	light-id		✓
			light-name		✓
			light-state		✓
			light-runtime		✓
	/api/{version}/lights/{light-id}	light-id			✓
		light-name			✓
		light-state			✓
		light-runtime			✓
	/api/{version}/device-information	model-name			✓
		serial-no			✓
		projector-name			✓
		mac-address			✓
		power-on-times			✓
		device-runtime			✓
	/api/{version}/version	main-version			✓
		sub-version			✓
	/api/{version}/temperatures	temperatures	temperature-id		✓
			temperature-name		✓
			temperature-celsius		✓
			temperature-fahrenheit		✓
	/api/{version}/temperatures/{temperature-id}	temperature-id			✓
		temperature-name			✓
		temperature-celsius			✓
		temperature-fahrenheit			✓
	/api/{version}/packet-information	packet-info-collision			✓
		packet-info-recv-packet			✓
		packet-info-recv-packet-error			✓
		packet-info-recv-packet-drop			✓
		packet-info-recv-packet-overrun			✓
		packet-info-recv-packet-frame			✓
		packet-info-send-packet			✓
		packet-info-send-packet-error			✓
		packet-info-send-packet-drop			✓
	/api/{version}/fans	fans	fan-id		✓
			fan-name		✓
			fan-rotation-speed		✓
	/api/{version}/fans/{fan-id}	fan-id			✓
		fan-name			✓
		fan-rotation-speed			✓
	/api/{version}/angle-sensor	roll-angle			✓
		pitch-angle			✓
	/api/{version}/signal	signal-information			✓