

WX-SZ600 Networked Desktop Charging Station

Charge up to four Panasonic wireless microphone transmitters when not in use*. The following combinations of Panasonic wireless mic transmitters can be supported: 2 x WX-ST200 + 2 x WX-ST400 or 4 x WX-ST400, or 2 x WX-ST600 or 4 x WX-ST400, or 2 x WXst200 + 2 x WX-ST700. The WX-SZ600 also features a network port so the charging status of Panasonic wireless microphones can be monitored remotely over the network for easy service and support. Contactless charging ports makes this a breeze to clean. *Note: AA Rechargeable Ni-MH battery in Panasonic wireless microphone transmitters required.



Key Features:

- Conveniently charges Panasonic Wireless Microphone transmitters
- Network port for remote monitoring of device
- Features Contactless Charging for Easy Cleaning

WX-SZ600 Specifications

Charging Ports:	4 (2: flat surface)
Charging Time:	Approx. 6 hours for WX-ST200, WX-ST400 Approx. 10 hours for WX-ST600, WX-ST700 (at ambient temperature of 77° F / 25° C, using AA Ni-MH battery BK-3MCCA)
LED Indicators:	Power, Charging indicators (per charge port)
Operating Ambient Temperature:	41° F to 95° (5°C to 35° C)
Operating Humidity Range:	10% to 90% (no condensation)
Power Source:	AC 120 V 60 Hz (AC adapter DC 12V included)
Power Consumption:	12 Watts Maximum
Warranty (Parts & Labor):	3 years
Dimensions (W x H x D):	7-7/8 in W x 3-90/32 in H x 7-3/32 in D (200mm W x 83mm H x 180mm D)
Weight:	1.34 lbs. (610 g)

Leveraging Panasonic's 20-year experience in DECT wireless audio communications, the WX-SR200P 1.9 GHz digital wireless microphone system is the best-in-class solution for classroom or corporate presentations providing low latency for hybrid in-room/virtual presentations. Panasonic's digital wireless microphone system is easy to set up, easy to integrate with third-party control systems (such as Crestron, Extron, and Q-SYS) and easy to use. Setup is a breeze - the wireless microphones pair wirelessly with Panasonic's digital wireless mic receiver and assigns channels automatically, eliminating the need for manual channel assignment. The system can be expandable to suit a variety of spaces, from small classrooms, medium sized classrooms / conference rooms, to large auditoriums. Up to 8 separate antennas (per receiver) can be mounted to the wall or the ceiling in the room and connected via CAT5 back to the receiver locked away in a cabinet or closet and multiple digital wireless microphone receivers can be installed to add wireless microphone channels to the room.

